

Maintaining Targets

Directory Server target definitions and their associated qualified URLs can be maintained using the System Management Hub.

Note:

Some Software AG products that use the Directory Server may need to be stopped and restarted if you make changes to Directory Server qualified URLs while the Software AG product is running. One example of such a product is Entire Net-Work 7 (open systems).

This chapter covers the following topics:


- Listing the Targets
 - Adding Targets
 - Maintaining Qualified URLs
 - Setting the Target Type
 - Changing the Target Name
 - Changing the Host
 - Changing the Protocol
 - Deleting a Target
-

Listing the Targets

 **To list the targets defined in a Directory Server:**

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. Click and expand the name of the Directory Server or the partition within a Directory Server whose targets you wish to review in the tree-view frame of SMH.

The targets for that Directory Server are listed in the detail-view frame and under the Directory Server or partition name in the tree-view frame. Targets are identified by the red circle icon ().



Partition ⇅	Target ⇅	Qualifier ⇅	URL ⇅
WCPTEST	140	access	tcpip://DB01:9010
WCPTEST	140	listen	tcpip://DB01:9010
XP01	59	access	tcpip://DB02:9010
XP01	59	listen	tcpip://DB02:9010
	NETWORK73_SMH	access	TCPIP://host1:49155? WCPKERNEL=ON
	NETWORK	access	TCPIP://host1:49154? WCPKERNEL=ON

Targets are initially listed by partition, in the order they appear in the Directory Server. You can change the sort order of the target list by clicking on the arrows in the column headings of the table in the detail-view frame. If you click on an up arrow in the column heading, the display is sorted alphabetically by the contents in that column. If you click on a down arrow in the column heading, the display is sorted in reverse alphabetic order by the contents in that column.

Adding Targets

You can add targets to the Directory Server directly, within a partition of the Directory Server, or both. For information on the use of partitions in a Directory Server, read *Partitioning a Directory Server*.

When you add a target definition, an "access" qualified URL and a "listen" qualified URL are automatically created. In the case of ADATCP and Entire Net-Work 7.x, the "listen" URL is not required and can be deleted. For information on deleting qualified URLs, read *Deleting Qualified URLs*.

For information on modifying or adding additional qualified URLs for the target definition, including specifying parameters for the URL, read *Maintaining Qualified URLs*.

▶ To add a target definition:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server to which you want to define the target.

The partitions and targets already defined for that Directory Server are listed in the detail-view frame and under the Directory Server name in the tree-view frame.

3. Optionally, if you want to define the target to a specific partition, click and expand the a name of the partition in the tree-view frame of SMH.
4. Click on the **Add Target** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the Directory Server or partition to which you wish to add the target..

The first panel in the **Add Target** panel series appears in the detail-view frame. In the following sample panel, the target is being added to the Directory Server directly and not to a partition within the Directory Server.

Add Target

Enter the Target Name or ID:

Select the Target Type:

- ☒ Server
- ☐ Replicated Server
- ☐ Proxy
- ☐ Entire Net-Work (2.x,5.x) Accessed Database via a Proxy

Next>

Cancel

5. Enter the database ID (DBID) into the **Target Name or ID** field.
6. Ensure that the **Server** option is selected.
 - The **Server** option is usually the option you should select.
 - The **Replicated Server** option is reserved for future use by Software AG.
 - The **Proxy** option is only applicable to configurations requiring a proxy. It is provided for compatibility with Software AG products that still require a proxy. If your Software AG product requires a proxy, refer to the documentation for your Software AG product for information about proxies and how to configure them in SMH.
7. Click **Next**.

The next panel in the **Add Target** panel series appears in the detail-view frame.

Add Target

- ☐ Target will be Accessed by Clients Directly
- ☐ Target will be Accessed by Clients via Proxy

<Back

Next>

Cancel

8. Select the **Target will be Accessed by Clients Directly** option, then click **Next**.

Note:


The **Target will be Accessed by Clients via Proxy** option is only provided for compatibility with Software AG products that still require a proxy. If your Software AG product requires a proxy, refer to the documentation for your Software AG product for information about them.

The next panel in the **Add Target** panel series appears in the detail-view frame.

Add Target

Select the Listen Protocol:

- ☒ TCPIP
- ☐ HTTP11
- ☐ SSL
- ☐ RDA



9. Select the listen protocol, then click **Next**. In most cases, the listen protocol will be **TCPIP**. For a complete description of these protocols, read *Protocols*.

Note:

Although the HTTP11 protocol is still listed on Directory Server administration screens in the System Management Hub, it is no longer supported.

The final panel in the **Add Target** panel series appears in the detail-view frame.

Add Target

Enter the Target Host Name:

Enter the Host IP Address ONLY when the Host Name is not known. The IP Address is Ignored when the Host contains a value.

Enter the Target IPv4 Address:

Enter the Target Listen Port:

Enter Alternate Ports

- Specify the host name of the middleware in the **Target Host Name** field. This is the Entire Net-Work version 7 or ADATCP host name.

Note:

Host names are case-sensitive in SMH.

Or:

Specify an IP address as an alternative to a host name. We do not recommend specifying IP addresses instead of host names as the IP address may change.

- Enter the middleware's listen port into the **Target Listen Port** field.

Note:

You can leave the **Alternate Ports** field blank, unless you want to enter alternate listen ports.

- Click **Finish**.

A message displays indicating that the new target definition was added, and the added target displays in the tree-view frame.

Maintaining Qualified URLs

Qualifiers identify the use of a target URL. Three qualifiers are supported in the Software AG Directory Server: access, connect, and listen. For more information about each qualifier, read *Qualifiers*

Using SMH, you can add and delete qualified URLs for a target. For more information about qualified URLs, read *Qualified URL Structure*, elsewhere in this guide.

This section covers the following topics:

- Listing Qualified URLs
- Adding Qualified URLs for the Target
- Deleting Qualified URLs
- Maintaining Qualified URL Parameters
- Changing Protocol, Host, and Port Values of the Qualified URL

Listing Qualified URLs

To list the qualified URLs of a target:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server containing the qualified URLs you wish to list.

The partitions and targets for that Directory Server are listed in the detail-view frame.

3. Click and expand the target whose qualified URLs you wish to list. If the target is in a partition, you must first select the partition and then click on the target.

The qualified URLs for the target are listed in the detail-view frame and under the target in the tree-view frame.

Adding Qualified URLs for the Target

When you add qualifiers (qualified URLs) for a target, the entire target entry is created, including the qualifier and full URL of the entry.

To add a qualified URL for a target:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server in which you want to add a qualifier.

The partitions and targets for that Directory Server are listed in the detail-view frame.


3. Click and expand the target in which you want to add a qualifier. If the target is in a partition, you must first select the partition and then click on the target.

- Click on the **Add Qualifier** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the target to which you want to add a qualifier.

The first panel in the **Add Qualifier** panel series appears in the detail-view frame.

Add Qualifier

Select the Qualifier Type to be Built:



Select 'access' to define direct client access to target.

Select 'listen' to allow connects to the target.

Select 'connect' to define a connect from this target to another target.

Next>

Cancel

- Select the qualifier type (URL use) to be defined for this target entry. Three types of qualifiers are supported in the Software AG Directory Server: access, connect, and listen. For complete information on these qualifiers, read *Qualifiers*.
- Click **Next**.

Depending on the qualifier you specified in the previous step, different SMH panels appear. The rest of this section describes how to create target URL entries for each of these different qualifiers.

- Creating an access URL
- Creating a connect URL
- Creating a listen URL

Creating an access URL


▶ To create an access URL for a target:

- Complete the first 4 steps described in *Adding Qualified URLs for the Target*. When you get to Step 5, select **access** for the qualifier type. Then click **Next**.

A second panel appears in the detail-view frame, asking you to indicate how this target will be accessed.

Add Qualifier

- ☒ Target will be Accessed by Clients Directly
- ☐ Target will be Accessed by Clients via Proxy



2. Select the first option, **Target will be Accessed by Clients Directly**, and click **Next**.

Note:


The **Target will be Accessed by Clients via Proxy** option is only provided for compatibility with Software AG products that still require a proxy. If your Software AG product requires a proxy, refer to the documentation for your Software AG product for information about them.

A protocol selection panel appears in the detail-view frame.

Add Qualifier

Select Protocol:

- ☒ TCPIP
- ☐ HTTP11
- ☐ SSL
- ☐ RDA



3. Select the protocol for the qualified URL and click **Next**. In most cases, the protocol will be **TCPIP**. For more information on the supported protocols, read *Protocols*.

Note:

Although the HTTP11 protocol is still listed on Directory Server administration screens in the System Management Hub, it is no longer supported.

The final panel in the **Add Qualifier** series of panels appears, requesting the host and port information for the qualified URL.

Add Qualifier

Enter the Target Host Name:

Enter the Host IP Address ONLY when the Host Name is not known. The IP Address is Ignored when the Host contains a value.

Enter the Target IPv4 Address:

Enter the Target Listen Port:

Enter Alternate Ports

- Specify the host name of the middleware in the **Target Host Name** field. This is the Entire Net-Work version 7 or ADATCP host name.

Note:

Host names are case-sensitive in SMH.

Or:

Specify an IP address as an alternative to a host name. We do not recommend specifying IP addresses instead of host names as the IP address may change.

- Enter the middleware's listen port in the **Enter the Target Listen Port** field.

Note:

You can leave the **Enter Alternate Ports** field blank, unless you want to enter alternate listen ports.

- Click **Finish**.

A message displays indicating that the new qualified access URL was added, and the added URL appears in the tree-view frame.

Creating a connect URL

▶ **To create a connect URL for a target:**

1. Complete the first 4 steps described in *Adding Qualified URLs for the Target*. When you get to Step 5, select **connect** for the qualifier type. Then click **Next**.

A second panel appears in the detail-view frame, asking you to indicate to what this target will connect.

Add Qualifier

- ☒ Connect to an Existing Server
- ☐ Connect to an Existing Proxy
- ☐ Connect to Other

<Back

Next>

Cancel

2. Select the **Connect to an Existing Server** or **Connect to Other** option, and click **Next**.

Note:

The **Connect to an Existing Proxy** option is only provided for compatibility with Software AG products that still require a proxy. If your Software AG product requires a proxy, refer to the documentation for your Software AG product for information about them.

A protocol selection panel appears in the detail-view frame.

Add Qualifier

Select Protocol:

- ☒ TCPIP
- ☐ HTTP11
- ☐ SSL
- ☐ RDA

<Back

Next>

Cancel

3. Select the protocol for the qualified URL and click **Next**. In most cases, the protocol will be **TCPIP**. For more information on the supported protocols, read *Protocols*.

Note:

Although the HTTP11 protocol is still listed on Directory Server administration screens in the System Management Hub, it is no longer supported.

The final panel in the **Add Qualifier** series of panels appears, requesting the host and port information for the qualified URL.

Add Qualifier

Enter the Target Host Name:

Enter the Host IP Address ONLY when the Host Name is not known. The IP Address is Ignored when the Host contains a value.

Enter the Target IPv4 Address:

Enter the Target Listen Port:

Enter Alternate Ports

- Specify the host name of the middleware in the **Target Host Name** field. This is the Entire Net-Work version 7 or ADATCP host name.

Note:

Host names are case-sensitive in SMH.

Or:

Specify an IP address as an alternative to a host name. We do not recommend specifying IP addresses instead of host names as the IP address may change.

- Enter the middleware's listen port in the **Enter the Target Listen Port** field.

Note:

You can leave the **Enter Alternate Ports** field blank, unless you want to enter alternate listen ports.

- Click **Finish**.

A message displays indicating that the new qualified connect URL was added, and the added URL appears in the tree-view frame.

Creating a listen URL

► To create a listen URL for a target:

1. Complete the first 4 steps described in *Adding Qualified URLs for the Target*. When you get to Step 5, select **listen** for the qualifier type. Then click **Next**.

A protocol selection panel appears in the detail-view frame.

Add Qualifier

Select Protocol:

- ☒ TCPIP
☐ HTTP11
☐ SSL
☐ RDA

<Back

Next>

Cancel

2. Select the protocol for the qualified URL and click **Next**. In most cases, the protocol will be **TCPIP**. For more information on the supported protocols, read *Protocols*.

Note:

Although the HTTP11 protocol is still listed on Directory Server administration screens in the System Management Hub, it is no longer supported.

The final panel in the **Add Qualifier** series of panels appears, requesting the host and port information for the qualified URL.

Add Qualifier

Enter the Target Host Name:

Enter the Host IP Address ONLY when the Host Name is not known. The IP Address is Ignored when the Host contains a value.

Enter the Target IPv4 Address:

Enter the Target Listen Port:

Enter Alternate Ports

3. Specify the host name of the middleware in the **Target Host Name** field. This is the Entire Net-Work version 7 or ADATCP host name.

Note:

Host names are case-sensitive in SMH.

Or:

Specify an IP address as an alternative to a host name. We do not recommend specifying IP addresses instead of host names as the IP address may change.

4. Enter the middleware's listen port in the **Enter the Target Listen Port** field.

Note:

You can leave the **Enter Alternate Ports** field blank, unless you want to enter alternate listen ports.

5. Click **Finish**.

A message displays indicating that the new qualified listen URL was added, and the added URL appears in the tree-view frame.

Deleting Qualified URLs

To delete a qualifier from a target:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server containing the qualifier you wish to delete.

The partitions and targets for that Directory Server are listed in the detail-view frame.

3. Click and expand the target containing the qualifier you wish to delete. If the target is in a partition, you must first select the partition and then click on the target.
4. Click on the qualifier you wish to delete.
5. Click on the **Delete Qualifier** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier you wish to delete.

The Delete Qualifier panel appears in the detail-view frame.

6. Click OK.

The qualifier definition is deleted.

Maintaining Qualified URL Parameters

This section covers the following topics:

- Setting Reconnect Parameters
- Setting Basic Parameters
- Setting Advanced Parameters
- Setting JSSE Parameters
- Setting OpenSSL Parameters
- Setting RDA-MHDR Parameters

Setting Reconnect Parameters

Using SMH, you can set or alter the values of the `reconnect`, `retry`, and `retryint` parameters for a qualified URL. These parameters control:

- Whether or not reconnection is attempted if the connection is disconnected due to some system failure
- The number of times the reconnection is attempted
- The interval, in seconds, between reconnection attempts.

To set the reconnect parameters for a qualified URL:

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.
2. Click on the qualified URL whose reconnect parameters you want to change.
3. Select the **Set Reconnect Parms** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set Reconnect Parms** panel appears in the detail-view frame of SMH.

Set Reconnect Parms

Attempt Reconnection on Failure

☐ Reconnect

Reconnect Retry Count:

Reconnect Retry Interval:

seconds

OK

Cancel

4. Click the **Reconnect** check box if you want reconnection attempts to occur if the connection is disconnected due to some failure in the system. If this check box is not checked, no reconnection attempt is made.

When this check box is checked, the `reconnect` parameter appears in the qualified URL.

5. Specify the number of times reconnection should be attempted in the **Reconnect Retry Count** field. The valid range is "0" through "2147483648". The default value is "0" (no reconnection attempts).

When a value other than "0" is specified, the `retry` parameter appears in the qualified URL.

6. Specify the number of seconds to wait between reconnection attempts. The valid range is "0" through "2147483648". The default value is "60000" seconds.

When a value other than "60000" is specified, the `retryint` parameter appears in the qualified URL.

7. Click OK.

The reconnection parameters for the qualified URL are set.

Setting Basic Parameters

Using SMH, you can set or alter the value of the `chirpinterval` parameter for a qualified URL. This parameter controls the interval, in seconds, at which chirping occurs. Chirping is the communication mechanism used to validate the availability of the connection.

Note:

The `ttl` (**Time To Live**) and `priority` (**Message Priority**) parameters are not available at this time. They are reserved for future use.

▶ **To set the basic parameters for a qualified URL:**

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.
2. Click on the qualified URL whose reconnect parameters you want to change.
3. Select the **Set Basic Parm**s command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set Basic Parm**s panel appears in the detail-view frame of SMH.

Set Basic Parm

Time To Live:

Message Priority:

Chirp Interval:

 seconds

OK

Cancel

Note:

The `ttl` (**Time To Live**) and `priority` (**Message Priority**) parameters are not available at this time. They are reserved for future use.

4. Specify the number of seconds to wait between chirp attempts in the **Chirp Interval** field. The valid range is "0" through the maximum integer that can be stored by your operating system. The default value is "300"seconds (5 minutes). A value of "0" implies the default, "300".Chirping is the communication mechanism used to validate the availability of the connection specified by the URL.

When a value other than "300" is specified, the `chirpinterval` parameter appears in the qualified URL.

5. Click OK.

The basic parameters for the qualified URL are set.

Setting Advanced Parameters

Using SMH, you can set or alter the values of advanced parameters `raw`, `recvtimeout`, `sendtimeout`, and various custom parameters for a qualified URL. These parameters control:

- Whether transport subsystem headers are sent
- The timeout value in seconds to receive messages on this connection
- The timeout value in seconds to send messages on this connection
- Other custom parameter either set automatically by the Software AG application for the qualified URL or with assistance from Software AG Customer Support.

To set the advanced parameters for a qualified URL:

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.
2. Click on the qualified URL whose reconnect parameters you want to change.
3. Select the **Set Advanced Parms** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set Advanced Parms** panel appears in the detail-view frame of SMH.

Set Advanced Parms

☐ Raw Mode

Receive Timeout:

seconds

Send Timeout:

seconds

Custom Parameters:

OK

Cancel

4. Click the **Raw Mode** check box if you want transport subsystem headers sent with messages on this connection. If this check box is checked, proxy operations are not possible.

When this check box is checked, the `raw` parameter appears in the qualified URL.

5. Specify the number of seconds to wait before timing out a message being received on this connection in the **Receive Timeout** field. The valid range is "0" through the maximum integer that can be stored by your operating system. The default value is "60" seconds. A value of "0" implies the default, "60".

When a value other than "0" or "60" is specified, the `recvtimeout` parameter appears in the qualified URL.

6. Specify the number of seconds to wait before timing out a message being sent on this connection in the **Send Timeout** field. The valid range is "0" through the maximum integer that can be stored by your operating system. The default value is "60" seconds. A value of "0" implies the default, "60".

When a value other than "0" or "60" is specified, the `sendtimeout` parameter appears in the qualified URL.

7. Specify other custom parameters in the **Custom Parameters** field, as directed by Software AG Customer Support.

Note:

Some custom parameters are specified automatically when the qualified URL is initially defined.

These custom parameters appear in the qualified URL.

8. Click OK.

The advanced parameters for the qualified URL are set.

Setting JSSE Parameters

Using SMH, you can set or alter the values of the Java security `KEYSTORE`, `KEYSTORE_PASSWD`, `TRUSTSTORE`, `TRUSTSTORE_PASSWD`, `VERSION`, and `VERIFY` parameters for a qualified URL. These parameters control:

- The Java keystore to use for the SSL connection
- The password for the Java keystore
- The Java truststore to use for the SSL connection
- The password for the Java truststore
- The SSL version that should be used for the SSL connection
- The verification processing level for the SSL connection.

To set the JSSE parameters for a qualified URL:

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.

- Click on the qualified URL whose reconnect parameters you want to change.
- Select the **Set JSSE Parms** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set JSSE Parms** panel appears in the detail-view frame of SMH.

Set JSSE Parms

Browse File Pattern:

Browse and Select Java Keystore File

Browse...

☐ Trim File Path

Java KeyStore Password:

Browse and Select Java Truststore File

Browse...

☐ Trim File Path

Java TrustStore Password:

Version:

TLSv1

- Defaults to TLSv1

Verification Level:

0

- Defaults to 0

OK

Cancel

- Optionally specify a browse file pattern in the **Browse File Pattern** field. This pattern is used to initially list files in the specified pattern when you click on any of the **Browse** buttons on this panel. However, once you get to the **Choose a File** panel produced by clicking on a **Browse** button, you can change the pattern if you choose.
- Click in the **Browse and Select Java Keystore File** field and specify the name of the Java keystore. You can click the **Browse** button for this field to locate and select the Java keystore file using a **Choose a File** panel.

Note:

The **Trim File Path** checkbox, when checked, will trim off the path if you specify a fully qualified path and file name.

When a value is specified, the `keyStore` parameter appears in the qualified URL.

- Click in the **Java KeyStore Password** field and specify the password required to extract information from the Java keystore.

When a value is specified, the `keystore_passwd` parameter appears in the qualified URL.

7. Click in the **Browse and Select Java Truststore File** field and specify the name of the Java truststore. You can click the **Browse** button for this field to locate and select the Java truststore file using a **Choose a File** panel.

Note:

The **Trim File Path** checkbox, when checked, will trim off the path if you specify a fully qualified path and file name.

When a value is specified, the `truststore` parameter appears in the qualified URL.

8. Click in the **Java TrustStore Password** field and specify the password required to extract information from the Java truststore.

When a value is specified, the `truststore_passwd` parameter appears in the qualified URL.

9. Select the version of SSL that should be used by selecting one from the dropdown list provided for the **Version** field. The default is "TLSv1".

When a value other than "TLSv1" is specified, the `version` parameter appears in the qualified URL.

10. Specify the certificate processing level by selecting one from the dropdown list provided for the **Verification Level** field. The default is "0".

For Java applications, valid values are:

0 (No peer verification occurs. This is the default value.)

1 (The application requests that the peer certificate be verified.)

2 (The application requests that the peer certificate be verified. A fatal condition occurs if there is no certificate.)

Values 4 and 8 are not valid for Java.

When a value is specified, the `verify` parameter appears in the qualified URL.

11. Click OK.

The JSSE parameters for the qualified URL are set.

Setting OpenSSL Parameters

Using SMH, you can set or alter the values of the OpenSSL security `VERSION`, `VERIFY`, `RANDOM_FILE`, `CAPATH`, `CAFILE`, `CERT_FILE`, `KEY_FILE`, and `CERT_PASSWD` parameters for a qualified URL. These parameters control:

- The SSL version that should be used for the SSL connection
- The verification processing level for the SSL connection
- The random file to use for the SSL connection

- The path for the Certificate Authority file that stores the trusted CA certificates
- The name of the Certificate Authority file that stores the trusted CA certificates
- The name of the file containing the participant's certificate
- The name of the file containing the server's private key
- The password for extracting information from the participant's certificate.

 To set the OpenSSL parameters for a qualified URL:

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.
2. Click on the qualified URL whose reconnect parameters you want to change.
3. Select the **Set OpenSSL Parms** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set OpenSSL Parms** panel appears in the detail-view frame of SMH.

Set OpenSSL Parms

Version:	TLSv1 - Defaults to TLSv1	Verification Level:	0 - Defaults to 0
Browse and Select Random File	Browse...	☐ Trim File Path	
Browse and Select Certificate Authority Path:	Browse...		
Browse and Select Certificate Authority File:	Browse...	☐ Trim File Path	
Browse and Select Certificate File:	Browse...	☐ Trim File Path	
Browse and Select Key File:	Browse...	☐ Trim File Path	
Certificate Password:			
OK Cancel			

4. Select the version of SSL that should be used by selecting one from the dropdown list provided for the **Version** field. The default is "TLSv1".

When a value other than "TLSv1" is specified, the **version** parameter appears in the qualified URL.

5. Specify the certificate processing level by selecting one from the dropdown list provided for the **Verification Level** field. The default is "0".

For C applications, valid values are:

- 0 (No peer verification occurs. This is the default value.)
- 1 (The application requests that the peer certificate be verified.)
- 2 (The application requests that the peer certificate be verified. A fatal condition occurs if there is no certificate.)
- 4 (The application requests that the peer certificate be verified only once.)
- 8 (The application requests that the issuer name is checked against the host name.)

Values "1", "2", and "4" can be specified simultaneously, but only if you use the **Custom Parameter** field on the **Set Advanced Parms** panel.

If no client certificate is available, certification fails.

When a value is specified, the `verify` parameter appears in the qualified URL.

6. Click in the **Browse and Select Random File** field and specify the name of the text file to be used by encryption routines to ensure that encryption itself occurs in a random manner. This text file contains at least 14 random characters. You can click the **Browse** button for this field to locate and select the random text file using a **Choose a File** panel.

Note:

The **Trim File Path** checkbox, when checked, will trim off the path if you specify a fully qualified path and file name.

When a value is specified, the `random_file` parameter appears in the qualified URL.

7. Click in the **Browse and Select Certificate Authority Path** field and specify the path where the Certificate Authority file that stores the trusted CA certificates resides. You can click the **Browse** button for this field to locate and select the path using a **Choose a File** panel.

When a value is specified, the `capath` parameter appears in the qualified URL.

8. Click in the **Browse and Select Certificate Authority File** field and specify the name of the Certificate Authority file that stores the trusted CA certificates. You can click the **Browse** button for this field to locate and select the file using a **Choose a File** panel.

Note:

The **Trim File Path** checkbox, when checked, will trim off the path if you specify a fully qualified path and file name.

When a value is specified, the `cafile` parameter appears in the qualified URL.

9. Click in the **Browse and Select Certificate File** field and specify the name of the file containing the participant's certificate. You can click the **Browse** button for this field to locate and select the file using a **Choose a File** panel.

Note:

The **Trim File Path** checkbox, when checked, will trim off the path if you specify a fully qualified path and file name.

When a value is specified, the `cert_file` parameter appears in the qualified URL.

10. Click in the **Browse and Select Key File** field and specify the name of the file containing the server's private key. You can click the **Browse** button for this field to locate and select the file using a **Choose a File** panel.

Note:

The **Trim File Path** checkbox, when checked, will trim off the path if you specify a fully qualified path and file name.

When a value is specified, the `key_file` parameter appears in the qualified URL.

11. Click in the **Certificate Password** field and specify the password required to extract information from the certificate file.

When a value is specified, the `cert_passwd` parameter appears in the qualified URL.

12. Click OK.

The OpenSSL parameters for the qualified URL are set.

Setting RDA-MHDR Parameters

Using SMH, you can set or alter the values of the RDA node, `nodename`, `charset`, and `security` parameters for a qualified URL. These parameters control:

- The node ID by which this node is known to a classic Entire Net-Work installation
- The node name by which this node is known to a classic Entire Net-Work installation
- The character encoding of the classic Entire Net-Work node associated with the URL
- The name of a security file containing a list of IP addresses authorized to access this protocol..

To set the RDA parameters for a qualified URL:

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.
2. Click on the qualified URL whose reconnect parameters you want to change.
3. Select the **Set RDA-MHDR Parms** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set RDA-MHDR Parms** panel appears in the detail-view frame of SMH.

Set RDA-MHDR Parms

Entire Net-Work Node ID:

Entire Net-Work Node Name:

Select the Charset:

Security:

OK

Cancel

4. Specify the node ID by which this node is known to a classic Entire Net-Work installation in the **Entire Net-Work Node ID** field.

When a value is specified for this field, the `node` parameter appears in the qualified URL.

- The name of a security file containing a list of IP addresses authorized to access this protocol..
5. Specify the node name by which this node is known to a classic Entire Net-Work installation in the **Entire Net-Work Node Name** field.

When a value is specified for this field, the `nodename` parameter appears in the qualified URL.

6. Specify the character encoding of the classic Entire Net-Work node associated with the URL in the **Select the Charset** field.

When a value is specified for this field, the `charset` parameter appears in the qualified URL.

7. Specify the name of a security file containing a list of IP addresses authorized to access this protocol in the **Security** field.

When a value is specified for this field, the `security` parameter appears in the qualified URL.

8. Click OK.

The RDA-MHDR parameters for the qualified URL are set.

Changing Protocol, Host, and Port Values of the Qualified URL

Using SMH, you can change the protocol, host name, host IP address, port, or alternate ports for a qualified URL.

To change these values for a qualified URL:

1. Locate and list the qualified URL you want to change as described in *Listing Qualified URLs*.
2. Click on the qualified URL whose reconnect parameters you want to change.
3. Select the **Set Protocol, Host, and Port Values** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the qualifier.

The **Set Protocol, Host, and Port Values** panel appears in the detail-view frame of SMH.

Set Protocol, Host, and Port Values

Protocol:

- ☒ TCPIP
☐ HTTP11
☐ SSL
☐ RDA

Host Name:

Enter the Host IP Address ONLY when the Host Name is not known. The IP Address is Ignored when the Host contains a value.

Enter the Target IPv4 Address:

Port:

Alternate Ports:

OK Cancel

- Click on the appropriate protocol checkbox in the **Protocol** field. In most cases, the protocol will be **TCPIP**. For a complete description of these protocols, read *Protocols*.

Note:

Although the HTTP11 protocol is still listed on Directory Server administration screens in the System Management Hub, it is no longer supported.

- Specify the host name of the middleware in the **Host Name** field. This is the Entire Net-Work version 7 or ADATCP host name.

Note:

Host names are case-sensitive in SMH.

Or:

Specify an IP address as an alternative to a host name. We do not recommend specifying IP addresses instead of host names as the IP address may change.

- Enter the middleware's listen port into the **Port** field.

Note:

You can leave the **Alternate Ports** field blank, unless you want to enter alternate listen ports.

7. Click OK.

The protocol, host, and port values for the qualified URL are set.

Setting the Target Type

You can globally change the target type of a target definition using the System Management Hub. When you do this, some of the qualified URLs assigned the target definition are updated with the new target type, as appropriate for the protocol specified in the URL.

To change the target type of a target definition:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server containing the target definition you want to modify.

The partitions and targets already defined for that Directory Server are listed in the detail-view frame and under the Directory Server name in the tree-view frame.

3. Click on the target you want to modify. If the target is in a partition, you must first select the partition and then click on the target.
4. Click on the **Set Target Type** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the target.

The **Set Target Type** panel appears in the detail-view frame.

Set Target Type

Select the Target Type:

- ☒ Server
☐ Replicated Server
☐ Proxy

Enter Server|Master Listening Port:

Enter Alternate or Replicated listening ports:

Proxy Administration Listening Port:

5. Select the appropriate option in the **Select the Target Type** area for the target type you want used for the target definition.
 - The **Server** option is usually the option you should select.
 - The **Replicated Server** option is reserved for future use by Software AG.
 - The **Proxy** option is only applicable to configurations requiring a proxy. It is provided for compatibility with Software AG products that still require a proxy. If your Software AG product requires a proxy, refer to the documentation for your Software AG product for information about proxies and how to configure them in SMH.
6. Optionally, change the listening ports used by the target in the **Enter Server/Master Listening Port**, **Enter Alternate or Replicated listening ports**, or **Proxy Administration Listening Port** fields.

Note:

The **Proxy Administration Listening Port** field is only applicable to configurations requiring a proxy. It is provided for compatibility with Software AG products that still require a proxy. If your Software AG product requires a proxy, refer to the documentation for your Software AG product for information about them.

7. Click **OK**.

The target type is changed for the target definition and the qualified URLs of the target definition are updated with the new target type, depending on the protocol specified in each URL.

Changing the Target Name

You can change the name of a target definition using the System Management Hub. When you do this, all of the qualified URLs assigned the target definition are updated with the new name.

▶ To change the name of a target:


1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server containing the target definition you want to modify.

The partitions and targets already defined for that Directory Server are listed in the detail-view frame and under the Directory Server name in the tree-view frame.

3. Click on the target you want to modify. If the target is in a partition, you must first select the partition and then click on the target.
4. Click on the **Change Target Name** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the target.

The **Change Target Name** panel appears in the detail-view frame.

Change Target Name



A dialog box titled "Change Target Name" with a label "Change Target Name To:" above a text input field. Below the input field are two buttons: "OK" and "Cancel".

5. Specify a new target name in the **Change Target Name To** field.

Note:

Target names are case-sensitive.

6. Click **OK**.

The name of the target definition is changed and all of its qualified URLs are updated with the new name.

Changing the Host

You can globally change the host setting of URLs in a target definition using the System Management Hub. For information on doing this, read *Changing Hosts*.

Changing the Protocol

You can globally change the protocol settings of URLs in a target definition using the System Management Hub.

 To change the protocol settings of URLs in a target definition:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click and expand the name of the Directory Server containing the target definition you want to modify.

The partitions and targets already defined for that Directory Server are listed in the detail-view frame and under the Directory Server name in the tree-view frame.

3. Click on the target you want to modify. If the target is in a partition, you must first select the partition and then click on the target.
4. Click on the **Change Protocol** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the target.

The **Change Protocol** panel appears in the detail-view frame.

Note:

Although the HTTP11 protocol is still listed on Directory Server administration screens in the System Management Hub, it is no longer supported.

Change Protocol

Select the From protocol:

- ☐ TCPIP
- ☐ HTTP11
- ☐ SSL
- ☐ RDA

Select the To protocol:

- ☐ TCPIP
- ☐ HTTP11
- ☐ SSL
- ☐ RDA

OK

Cancel

5. Click on the checkbox in the **Select the From protocol** area for the protocol you want to change. All URLs for the target definition using this protocol will be changed when these steps are completed.
6. Click on the checkbox in the **Select the To protocol** area for the protocol you want to use instead. The URLs using the protocol you specified in the previous step will be changed to use the protocol you select in this step.
7. Click **OK**.

A URLs in the target definition with the protocol selected in the **Select the From protocol** area are changed to use the protocol selected in the **Select the To protocol** area.

Deleting a Target

▶ To delete a target definition:

1. Access the Directory Server administration area, as described in *The Directory Server Administration Area*.
2. In the tree-view frame of SMH, click on the name of the Directory Server containing the the target definition you wish to delete.

The partitions and targets for that Directory Server are listed in the detail-view frame.

3. Click on the target you wish to delete. If the target is in a partition, you must first select the partition and then click on the target.
4. Click on the **Delete Target** command in the **Commands** menu of SMH. You can also see this menu by right-clicking on the name of the target.

The Delete Target panel appears in the detail-view frame.

5. Click OK.

The target definition is deleted.