

# XTS\* - Software AG Internal Transport Subsystem Messages

The Software AG internal transport subsystem Messages and Codes documentation provides information for each warning and error message that you can encounter using the internal transport subsystem of Software AG products.

This documentation is organized as follows:

<i>Warnings</i>	Provides the message ID, message text, and a brief explanation for each warning message.
<i>Errors</i>	Provides the message ID, message text, and a brief explanation for each error message.
<i>Generic TCP/IP Messages</i>	Lists the message ID and message text for each generic TCP/IP error. For complete information on the TCP/IP error conditions, refer to your TCP/IP documentation.

## Note:

The internal component API returns warnings as positive values and errors as negative values.

---

## Warnings

### Overview of Messages

XTS0000W | XTS0001W | XTS0003W | XTS0004W | XTS0005W | XTS0006W |  
 XTS0007W | XTS0008W | XTS0009W | XTS0010W | XTS0011W | XTS0012W |  
 XTS0013W | XTS0014W | XTS0015W

#### **XTS0000W      XTS Success**

**Explanation**      The transport subsystem processing completed successfully.

#### **XTS0001W      XTS No LISTEN has been issued**

**Explanation**      A server has only XTSconnect entries and no XTSlisten. It is possible for a server to connect only to a proxy, and the warning helps applications determine if XTSlisten is missing.

#### **XTS0003W      XTS Load message file failed**

**Explanation**      The transport subsystem failed to load the *XTS.MSG* file. This file contains text for the error messages; there is an internal table also, so *XTS.MSG* is not mandatory.

**XTS0004W XTS Client already registered**

**Explanation** Multiple `XtsBindClient` calls occurred for the same client. Only the first call is considered.

**XTS0005W XTS More data**

**Explanation** The receive buffer defined by a transport subsystem send and wait call is not big enough to get all data received by the transport subsystem. A subsequent call has to be made to receive all data.

**XTS0006W XTS No SSL random file warning**

**Explanation** There is no random file defined for a transport subsystem/Secure Sockets Layer (SSL) application; a random file usage by SSL is highly recommended.

**XTS0007W XTS Notify connect**

**Explanation** This is a receive callback notification for an incoming connection.

**XTS0008W XTS Notify disconnect**

**Explanation** This is a receive callback notification for a disconnection.

**XTS0009W XTS Notify chirp**

**Explanation** This is a receive callback notification for a chirp.

**XTS0010W XTS Notify unsupported**

**Explanation** This is a receive callback notification when protocols set by `XTSlisten` are not supported.

**XTS0011W XTS Notify message reference dead**

**Explanation** This is a receive callback notification indicating the active message references are deleted when a client disconnects.

**XTS0012W XTS Notify outbound connect**

**Explanation** This is a receive callback notification for an outbound connection.

**XTS0013W XTS Notify listen failure**

**Explanation** This is a notification to the callback routine submitted by XtsRegisterByTargetName or XtsRegisterByTargetId indicating a failure of an XTSlisten URL.

**XTS0014W XTS Notify connect failure**

**Explanation** This is a notification to the callback routine submitted by XtsRegisterByTargetName or XtsRegisterByTargetId indicating a failure of an XTSconnect URL.

**XTS0015W XTS Notify unchirp**

**Explanation** This is a notification to the callback routine submitted by XtsRegisterByTargetName or XtsRegisterByTargetId indicating an unchirp message was received from another node.

## Errors

### Overview of Messages

XTS0050E	XTS0051E	XTS0052E	XTS0053E	XTS0054E	XTS0055E
XTS0056E	XTS0057E	XTS0058E	XTS0059E	XTS0060E	XTS0061E
XTS0062E	XTS0063E	XTS0064E	XTS0065E	XTS0066E	XTS0069E
XTS0070E	XTS0071E	XTS0072E	XTS0073E	XTS0074E	XTS0075E
XTS0077E	XTS0078E	XTS0079E	XTS0082E	XTS0083E	XTS0084E
XTS0085E	XTS0086E	XTS0087E	XTS0088E	XTS0089E	XTS0090E
XTS0094E	XTS0095E	XTS0096E	XTS0097E	XTS0098E	XTS0100E
XTS0101E	XTS0102E	XTS0103E	XTS0104E	XTS0105E	XTS0106E
XTS0107E	XTS0108E	XTS0109E	XTS0110E	XTS0111E	XTS0112E
XTS0113E	XTS0114E	XTS0115E	XTS0116E	XTS0117E	XTS0118E
XTS0119E	XTS0120E	XTS0121E	XTS0122E	XTS0123E	XTS0124E
XTS0126E	XTS0127E	XTS0128E	XTS0129E	XTS0130E	XTS0131E
XTS0132E	XTS0150E	XTS0151E	XTS0152E	XTS0153E	XTS0154E
XTS0155E	XTS0156E	XTS0157E	XTS0158E	XTS0159E	XTS0163E
XTS0167E	XTS0168E	XTS0169E	XTS0170E	XTS0171E	XTS0172E
XTS0173E	XTS0174E	XTS0200E	XTS0201E	XTS0203E	XTS0204E
XTS0205E	XTS0207E	XTS0209E	XTS0214E	XTS0215E	XTS0218E
XTS0219E	XTS0220E	XTS0221E	XTS0222E	XTS0223E	XTS0224E
XTS0225E	XTS0226E	XTS0227E	XTS0228E	XTS0229E	XTS1000E

**XTS0050E XTS Semaphore Error**

**Explanation** A failure to create a semaphore occurred. Contact Software AG customer support.

**XTS0051E XTS Memory Allocation Error**

**Explanation** A failure to allocate memory occurred. Contact Software AG customer support.

**XTS0052E            XTS Server already registered**

**Explanation**            The transport subsystem server is already registered.

**XTS0053E    XTS Incorrect URL**

**Explanation**    A URL with a syntax error was encountered. Check the Directory Server repositories.

**XTS0054E    XTS Failure Loading Protocol Handler**

**Explanation**    A failure to load protocol handlers (for example, *Xtstcp.lib*) occurred. It was probably caused by a configuration problem. Contact Software AG customer support.

**XTS0055E    XTS Protocol Init failed**

**Explanation**    A protocol initialization failure occurred. Contact Software AG customer support.

**XTS0056E    XTS Invalid protocol type**

**Explanation**    The specified protocol is not supported by the transport subsystem. This is possibly an error in URL syntax.

**XTS0057E    XTS Listen Failed**

**Explanation**    A listen failed. Check the log file for protocol-specific errors. This is caused mostly by trying to listen on a port taken by another server.

**XTS0058E    XTS Accept Failed**

**Explanation**    The accept failed. Check the log file for protocol-specific errors.

**XTS0059E    XTS Connect Failed**

**Explanation**    The connect failed. Check the log file for protocol-specific errors.

**XTS0060E    XTS No directory information**

**Explanation**    No XTSaccess information is provided for the server to which the application wants to connect. Please add a target definition through the Directory Server.

**XTS0061E      XTS Failure to create a thread**

**Explanation**      A failure to create a thread occurred. Contact Software AG customer support

**XTS0062E      XTS Timeout error**

**Explanation**      A failure to connect or send data in the time set by the user occurred. To complete the connect or send, repeat the call or increase the timeout value.

**XTS0063E      XTS Send Failed**

**Explanation**      A completion code is returned to the send callback routine when send fails. Check the log file for the protocol-specific error code.

**XTS0064E              XTS Invalid reference**

**Explanation**              An invalid message reference was passed by the user.

**XTS0065E              XTS Send incomplete**

**Explanation**              A send was interrupted by a client disconnection.

**XTS0066E      XTS No such server**

**Explanation**      A nonexistent server name was passed by the user. It applies to the transport subsystem statistics and dumps calls.

**XTS0069E      XTS Resolve Target failed**

**Explanation**      The client failed to send a handshake message to the server; Error caused by the server going down or a protocol send error.

**XTS0070E      XTS Resolve Target Reply failed**

**Explanation**      The server failed to reply to the client during handshaking. This error is caused by the client going down or by a protocol send error.

**XTS0071E      XTS Target cannot be resolved**

**Explanation**      The client failed to resolve the target name. This error is caused by different names used by the server and the client but with the same address.

**XTS0072E XTS Not initialized**

**Explanation** The transport subsystem call was submitted before the transport subsystem was initialized. Errors were returned by XtsShutdown, XtsSendMessageByRT, and the transport subsystem statistics call.

**XTS0073E XTS Bind Client failed**

**Explanation** The client bind failed because of a protocol send error or because the server went down.

**XTS0074E XTS Too many user threads**

**Explanation** The number of user threads in existence reached the maximum (64). Stop creating new user threads or reduce their time to live (timeout).

**XTS0075E XTS Created thread failed**

**Explanation** The transport subsystem failed to create a new user thread. This is an SMP error, possibly because of the limitations of the number of threads that a system can support. Contact Software AG customer support.

**XTS0077E XTS Conversion failed**

**Explanation** The conversion between wide character and MBNS failed. Contact Software AG customer support.

**XTS0078E XTS No Target Name**

**Explanation** The target name is a zero pointer. Pass a valid string.

**XTS0079E XTS No Client Name**

**Explanation** The client name is a zero pointer. Pass a valid string.

**XTS0082E XTS Zero Length not accepted**

**Explanation** The length of the data to be sent is zero, Make the length a positive number.

**XTS0083E XTS Target ID Out of Range**

**Explanation** The target ID value is bigger than "2113929215".

**XTS0084E XTS Channel Inactive**

**Explanation** The server-client connection was no longer active when XtsSendByRt or XtsBindClient were called. This error is generated by a client going down during the call.

**XTS0085E XTS Disconnect message**

**Explanation** A client or server disconnection was detected during a transport subsystem call.

**XTS0086E XTS Hash table error**

**Explanation** An internal transport subsystem hash table error occurred. Contact Software AG customer support.

**XTS0087E XTS Thread key error**

**Explanation** An allocate/delete thread memory failure occurred. Contact Software AG customer support.

**XTS0088E XTS No CONNECT or LISTEN has been issued**

**Explanation** A server registration failed to submit at least one listen or connect. Check the XTSlisten or XTSconnect URL parameters.

**XTS0089E XTS Protocol not supported**

**Explanation** An attempt was made to use XtsBindClient over the RAW or XTSDS protocol. This feature is not supported.

**XTS0090E XTS Single Thread not supported**

**Explanation** This error code is returned when the transport subsystem call does not support the single thread feature. Examples include XtsRegisterServerByName(ID) and XtsGiveThread.

**XTS0094E XTS Zero pointer**

**Explanation** A zero pointer was passed by the user. This is an invalid value.

**XTS0095E     XTS Hash table full**

**Explanation**     An internal transport subsystem hash table error occurred. Contact Software AG customer support.

**XTS0096E             XTS Send User Exit failed**

**Explanation**             The user exit send routine failed. Check the user exit code.

**XTS0097E             XTS Recv User Exit failed**

**Explanation**             The user exit receive routine failed. Check the user exit code.

**XTS0098E     XTS Load User Exit failed**

**Explanation**     The transport subsystem failed to load the user exit library. Check the environment or the user exit routine names.

**XTS0100E     XTS Shutdown in process**

**Explanation**     This error code is returned when the transport subsystem is in shutdown mode (because XtsShutdown was called by another thread).

**XTS0101E     XTS Route Timeout**

**Explanation**     The proxy cannot deliver the message because the route timeout was insufficient. Change the route timeout.

**XTS0102E     XTS Route Table overflow**

**Explanation**     The proxy cannot deliver the message because of a route table overflow. Repeat the transport subsystem call.

**XTS0103E     XTS Route TTL expired**

**Explanation**     The proxy cannot deliver the message because the route time to live was insufficient. Change the time to live time.

**XTS0104E     XTS Route failed**

**Explanation**     The proxy cannot deliver the message because of a route failure. Repeat the transport subsystem call.



**XTS0105E      XTS Null parameter**

**Explanation**    A null parameter is encountered when a notify callback routine registration is called.

**XTS0106E            XTS Connection Rejected**

**Explanation**            The connection was rejected by the notify callback routine.

**XTS0107E            XTS Replica redirected**

**Explanation**            The connection was redirected by the callback routine.

**XTS0108E    XTS timeout - connect in progress**

**Explanation**    A timeout error occurred, but connection is in progress. Submit the call again or increase the timeout value.

**XTS0109E      XTS invalid session**

**Explanation**      An invalid session handle was used by the transport subsystem session calls.

**XTS0110E      XTS invalid key**

**Explanation**      An invalid session handle was used by the transport subsystem session calls.

**XTS0111E            XTS Count converters failed**

**Explanation**            The count of available converter names failed.

**XTS0112E            XTS Convert enum failed**

**Explanation**            The enumeration of text converter names failed.

**XTS0113E            XTS Buffer too small**

**Explanation**            The text conversion buffer is not big enough..

**XTS0114E            XTS No more ports available**

**Explanation**            No replicated server ports are available .

**XTS0115E XTS Text converter library load failed**

**Explanation** The load of the transport subsystem converter ending failed.

**XTS0116E XTS Text converter resolve failed**

**Explanation** The text converter interface function could not be resolved.

**XTS0117E XTS Name to EDDkey map failed**

**Explanation** The ICU converter name to Software AG ECS EDD key conversion failed..

**XTS0118E XTS XDS library loading failed**

**Explanation** The XDS library used by ADVDIR could not be loaded.

**XTS0119E XTS DS access time out error**

**Explanation** A timeout occurred accessing the Directory Server (the default timeout is one minute).

**XTS0120E XTS Failed to set ECS environment**

**Explanation** A failure occurred when setting the ECS environment.

**XTS0121E XTS Set UDP Port failed**

**Explanation** The UDP port selected by user cannot be used (because it is used by another application).

**XTS0122E XTS Sync and async send in raw mode not allowed**

**Explanation** Using synchronous and asynchronous calls on the same channel is not allowed.

**XTS0123E XTS Unknown received buffer**

**Explanation** The transport subsystem received an unknown buffer from an application.

**XTS0124E XTS Function retired**

**Explanation** The transport subsystem function is not supported any longer.

**XTS0126E XTS invalid duplicate server**

**Explanation** This error is generated when the same server is registered again with a different protocol than the one used when it was first registered.

**XTS0127E XTS Fatal error**

**Explanation** An internal error occurred, indicating a severe transport subsystem code problem. Contact Software AG customer support.

**XTS0128E XTS Load library failed**

**Explanation** The transport subsystem failed to load a library (the log file indicates which one).

**XTS0129E XTS Key not found**

**Explanation** The key used to retrieve transport subsystem parameters does not exist.

**XTS0130E XTS Xts.Config Key not found**

**Explanation** The key used by the user to retrieve transport subsystem parameters from *xts.config* file does not exist.

**XTS0131E XTS No directory information for XTS profile**

**Explanation** The profile is not defined in the Directory Server.

**XTS0132E XTS Load function failed**

**Explanation** A failure occurred loading a function (the name of the function and the name of the library are in the log file).

**XTS0150E XTS SSL init failed**

**Explanation** The transport subsystem failed to initialize the Secure Sockets Layer (SSL) library. Check the log file for the SSL error messages.

**XTS0151E XTS SSL Verify CA locations failed**

**Explanation** The Secure Sockets Layer (SSL) failed to load the CA certificates. Probable causes include an invalid path specification or nonexistent CA certificates.

**XTS0152E            XTS SSL Certificate file not specified**

**Explanation**            No Secure Sockets Layer (SSL) certificate was specified.

**XTS0153E            XTS SSL Invalid Certificate**

**Explanation**            The URL-specified Secure Sockets Layer (SSL) certificate has an invalid format.

**XTS0154E            XTS SSL Invalid Key File**

**Explanation**            The URL-specified Secure Sockets Layer (SSL) key file has an invalid format.

**XTS0155E            XTS SSL Invalid Key**

**Explanation**            The Secure Sockets Layer (SSL) key specified by the user is invalid.

**XTS0156E            XTS SSL Connect failed**

**Explanation**            A Secure Sockets Layer (SSL) connect failed (caused by an SSL handshaking error).  
Check the log file for the Secure Sockets Layer (SSL) error messages.

**XTS0157E            XTS SSL Accept failed**

**Explanation**            A Secure Sockets Layer (SSL) accept failed (caused by an SSL handshaking error).  
Check the log file for the SSL error messages.

**XTS0158E            XTS SSL Read failed**

**Explanation**            A Secure Sockets Layer (SSL) read failed. Check the log file for the SSL error messages.

**XTS0159E            XTS SSL Write failed**

**Explanation**            A Secure Sockets Layer (SSL) write failed. Check the log file for the SSL error messages.

**XTS0163E            XTS SSL Failed loading library**

**Explanation**            A failure to load the Secure Sockets Layer (SSL) library occurred. Check the environment.

**XTS0167E XTS SSL Illegal host name**

**Explanation** The peer certificate subject name and host name are different, indicating an illegal connection.

**XTS0168E XTS SSL No local certificate**

**Explanation** There is no local Secure Sockets Layer (SSL) certificate.

**XTS0169E XTS SSL No remote certificate**

**Explanation** There is no local Secure Sockets Layer (SSL) certificate.

**XTS0170E XTS SSL insufficient user memory**

**Explanation** There is insufficient user memory for returning the requested data.

**XTS0171E XTS SSL certificate rejected**

**Explanation** The certificate was rejected during verification.

**XTS0172E XTS SSL zero length message return**

**Explanation** The Secure Sockets Layer (SSL) write or read routines returned an invalid zero value. Contact Software AG customer support.

**XTS0173E XTS SSL want read error**

**Explanation** The Secure Sockets Layer (SSL) write routine returned want read error code. Contact Software AG customer support. This is a transport subsystem internal sequence error.

**XTS0174E XTS SSL want write error**

**Explanation** The Secure Sockets Layer (SSL) read routine returned want write error code. Contact Software AG customer support. This is a transport subsystem internal sequence error.

**XTS0200E DS Open File failed**

**Explanation** A failure to open a file occurred. Check if the file exists and that the path is correct.

**XTS0201E      DS Incomplete Entry**

**Explanation**      A URL syntax error occurred. Check the log file for detailed information.

**XTS0203E      DS Service not provided**

**Explanation**      An invalid Directory Service selection was made.

**XTS0204E      DS Null parameter**

**Explanation**      A Directory Service call was encountered with a null parameter.

**XTS0205E      DS Incomplete Entry**

**Explanation**      An attempt to add an incomplete URL record was made.

**XTS0207E      DS Unknown request**

**Explanation**      An unknown XTSDS request was encountered. Check the syntax of the Directory Server call.

**XTS0209E      DS Delete Failed**

**Explanation**      A Directory Service delete call failed. Check the log file for detailed information.

**XTS0214E      DS Already Exists**

**Explanation**      An attempt was made to add a record that already exists.

**XTS0215E      DS Failure Loading Service Handler**

**Explanation**      A failure occurred loading a directory service. Check the environment. Contact Software AG customer support.

**XTS0218E      DS Invalid target Name**

**Explanation**      The target name contains one of the following characters: "#", ".", "[", "]", "=", "\", "\", or "\*". The target name is invalid.

**XTS0219E DS Incomplete request**

**Explanation** An incomplete XTSDS request was caused by a zero value of the target, qualifier, or user data.

**XTS0220E DS No URL entries**

**Explanation** The XTSDS server does not have any URL to return for the retrieve call.

**XTS0221E DS XDS error**

**Explanation** An XDS processing error occurred..

**XTS0222E DS Rollback is not implemented**

**Explanation** No Directory Service rollback was performed..

**XTS0223E DS OVO error**

**Explanation** An OVO error occurred during Directory Service processing.

**XTS0224E DS One time set violation**

**Explanation** A one-time setting function was called multiple times. A programs encoding mode cannot change once it is set.

**XTS0225E DS Encoding conflict**

**Explanation** The INIDIR file encoding conflicts with programs encoding.

**XTS0226E DS Create file failed**

**Explanation** The file creation failed during Directory Service processing..

**XTS0227E DS IO file failed**

**Explanation** A file I/O error occurred during Directory Service processing.

**XTS0228E DS Wrong file format'**

**Explanation** The INIDIR file format was not recognized.

**XTS0229E DS Send buffer bigger than maximum allowed**

**Explanation** An internal transport subsystem error occurred, generated when a URL is added or deleted from the Directory Server and its size exceeds 65520 bytes.

**XTS1000E XTS Unknown error = code**

**Explanation** This message is returned by XtsGetMessage when it cannot find text for a given error code.

## Generic TCP/IP Messages

### Overview of Messages

XTS1001E	XTS1002E	XTS1003E	XTS1004E	XTS1005E	XTS1006E
XTS1007E	XTS1008E	XTS1009E	XTS1010E	XTS1011E	XTS1012E
XTS1013E	XTS1014E	XTS1015E	XTS1016E	XTS1017E	XTS1018E
XTS1019E	XTS1020E	XTS1021E	XTS1022E	XTS1023E	XTS1024E
XTS1025E	XTS1026E	XTS1027E	XTS1028E	XTS1029E	XTS1030E
XTS1031E	XTS1032E	XTS1033E	XTS1034E	XTS1035E	XTS1036E
XTS1037E	XTS1038E	XTS1039E	XTS1040E	XTS1041E	XTS1042E
XTS1043E	XTS1044E	XTS1045E	XTS1046E	XTS1047E	XTS1048E
XTS1049E	XTS1050E	XTS1051E	XTS1052E	XTS1053E	XTS1054E
XTS1055E	XTS1056E	XTS1057E	XTS1058E	XTS1059E	XTS1060E
XTS1061E	XTS1062E	XTS1063E	XTS1064E	XTS1065E	XTS1066E
XTS1067E	XTS1068E	XTS1069E	XTS1070E	XTS1071E	XTS1072E
XTS1073E	XTS1074E	XTS1075E	XTS1076E	XTS1077E	XTS1078E
XTS1079E	XTS1080E	XTS1081E	XTS1082E	XTS1083E	XTS1084E
XTS1085E	XTS1086E	XTS1087E	XTS1088E	XTS1089E	XTS1090E
XTS1091E	XTS1092E	XTS1093E	XTS1094E	XTS1095E	XTS1096E
XTS1097E	XTS1098E	XTS1099E	XTS1100E	XTS1101E	XTS1102E
XTS1103E	XTS1104E	XTS1105E	XTS1106E	XTS1107E	XTS1108E
XTS1109E	XTS1111E	XTS1112E	XTS1113E	XTS1114E	XTS1115E
XTS1116E	XTS1118E	XTS1119E	XTS1120E	XTS1122E	XTS1123E
XTS1124E	XTS1125E	XTS1126E	XTS1127E	XTS1128E	XTS1129E
XTS1130E	XTS1131E	XTS1132E	XTS1133E	XTS1134E	XTS1135E
XTS1136E	XTS1137E	XTS1138E	XTS1139E	XTS1140E	XTS1141E
XTS1142E	XTS1143E	XTS1144E	XTS1145E	XTS1146E	XTS1147E
XTS1148E	XTS1149E	XTS1150E	XTS1151E	XTS1152E	XTS1153E
XTS1154E	XTS1155E	XTS1156E	XTS1157E	XTS1158E	XTS1159E
XTS1160E	XTS1161E	XTS1162E	XTS1163E	XTS1164E	XTS1165E
XTS1166E	XTS1167E	XTS1168E	XTS1169E		

**XTS1001E TCP/IP Operation not permitted**

**XTS1002E TCP/IP No such file or directory**



<b>XTS1003E</b>	<b>TCP/IP No such process</b>
<b>XTS1004E</b>	<b>TCP/IP Interrupted function call</b>
<b>XTS1005E</b>	<b>TCP/IP I/O error</b>
<b>XTS1006E</b>	<b>TCP/IP No such device or address</b>
<b>XTS1007E</b>	<b>TCP/IP Arg list too long</b>
<b>XTS1008E</b>	<b>TCP/IP Exec format error</b>
<b>XTS1009E</b>	<b>TCP/IP Bad file number</b>
<b>XTS1010E</b>	<b>TCP/IP No children</b>
<b>XTS1011E</b>	<b>TCP/IP Operation would cause deadlock</b>
<b>XTS1012E</b>	<b>TCP/IP Not enough core</b>
<b>XTS1013E</b>	<b>TCP/IP Permission denied</b>
<b>XTS1014E</b>	<b>TCP/IP Bad address</b>
<b>XTS1015E</b>	<b>TCP/IP Block device required</b>
<b>XTS1016E</b>	<b>TCP/IP Mount device busy</b>
<b>XTS1017E</b>	<b>TCP/IP File exists</b>
<b>XTS1018E</b>	<b>TCP/IP Cross-device link</b>
<b>XTS1019E</b>	<b>TCP/IP No such device</b>

<b>XTS1020E</b>	<b>TCP/IP Not a directory</b>
<b>XTS1021E</b>	<b>TCP/IP Is a directory</b>
<b>XTS1022E</b>	<b>TCP/IP Invalid argument</b>
<b>XTS1023E</b>	<b>TCP/IP File table overflow</b>
<b>XTS1024E</b>	<b>TCP/IP Too many open sockets</b>
<b>XTS1025E</b>	<b>TCP/IP Inappropriate ioctl for device</b>
<b>XTS1026E</b>	<b>TCP/IP Text file busy</b>
<b>XTS1027E</b>	<b>TCP/IP File too large</b>
<b>XTS1028E</b>	<b>TCP/IP No space left on device</b>
<b>XTS1029E</b>	<b>TCP/IP Illegal seek</b>
<b>XTS1030E</b>	<b>TCP/IP Read-only file system</b>
<b>XTS1031E</b>	<b>TCP/IP Too many links</b>
<b>XTS1032E</b>	<b>TCP/IP Broken pipe</b>
<b>XTS1033E</b>	<b>TCP/IP Argument too large</b>
<b>XTS1034E</b>	<b>TCP/IP Result too large</b>
<b>XTS1035E</b>	<b>TCP/IP Resource temporarily unavailable</b>
<b>XTS1036E</b>	<b>TCP/IP Operation now in progress</b>

<b>XTS1037E</b>	<b>TCP/IP Operation already in progress</b>
<b>XTS1038E</b>	<b>TCP/IP Socket operation on non-socket</b>
<b>XTS1039E</b>	<b>TCP/IP Destination address required</b>
<b>XTS1040E</b>	<b>TCP/IP Message too long</b>
<b>XTS1041E</b>	<b>TCP/IP Protocol wrong type for socket</b>
<b>XTS1042E</b>	<b>TCP/IP Bad protocol option</b>
<b>XTS1043E</b>	<b>TCP/IP Protocol not supported</b>
<b>XTS1044E</b>	<b>TCP/IP Socket type not supported</b>
<b>XTS1045E</b>	<b>TCP/IP Operation not supported</b>
<b>XTS1046E</b>	<b>TCP/IP Protocol Family not supported</b>
<b>XTS1047E</b>	<b>TCP/IP Address family not supported by protocol family</b>
<b>XTS1048E</b>	<b>TCP/IP Address already in use</b>
<b>XTS1049E</b>	<b>TCP/IP Cannot assign requested address</b>
<b>XTS1050E</b>	<b>TCP/IP Network is down</b>
<b>XTS1051E</b>	<b>TCP/IP Network is unreachable</b>
<b>XTS1052E</b>	<b>TCP/IP Network dropped connection on reset</b>
<b>XTS1053E</b>	<b>TCP/IP Software caused connection abort</b>

<b>XTS1054E</b>	<b>TCP/IP Connection reset by peer</b>
<b>XTS1055E</b>	<b>TCP/IP No buffer space available</b>
<b>XTS1056E</b>	<b>TCP/IP Socket is already connected</b>
<b>XTS1057E</b>	<b>TCP/IP Socket is not connected</b>
<b>XTS1058E</b>	<b>TCP/IP Cannot send after socket shutdown</b>
<b>XTS1059E</b>	<b>TCP/IP Too many references</b>
<b>XTS1060E</b>	<b>TCP/IP Connection timed out</b>
<b>XTS1061E</b>	<b>TCP/IP Connection refused</b>
<b>XTS1062E</b>	<b>TCP/IP Too many levels of symbolic links</b>
<b>XTS1063E</b>	<b>TCP/IP File name too long</b>
<b>XTS1064E</b>	<b>TCP/IP Host is down</b>
<b>XTS1065E</b>	<b>TCP/IP No route to host</b>
<b>XTS1066E</b>	<b>TCP/IP Directory not empty</b>
<b>XTS1067E</b>	<b>TCP/IP Too many processes</b>
<b>XTS1068E</b>	<b>TCP/IP Too many users</b>
<b>XTS1069E</b>	<b>TCP/IP Disc quota exceeded</b>
<b>XTS1070E</b>	<b>TCP/IP Stale NFS file handle</b>

<b>XTS1071E</b>	<b>TCP/IP Too many levels of remote in path</b>
<b>XTS1072E</b>	<b>TCP/IP Device not ready</b>
<b>XTS1073E</b>	<b>TCP/IP Write-protected media</b>
<b>XTS1074E</b>	<b>TCP/IP Unformatted media</b>
<b>XTS1075E</b>	<b>TCP/IP No connection</b>
<b>XTS1076E</b>	<b>TCP/IP Old, currently unused AIX errno</b>
<b>XTS1077E</b>	<b>TCP/IP Restart the system call</b>
<b>XTS1078E</b>	<b>TCP/IP Invalid file system control data</b>
<b>XTS1079E</b>	<b>TCP/IP Media surface error</b>
<b>XTS1080E</b>	<b>TCP/IP I/O completed, but needs relocation</b>
<b>XTS1081E</b>	<b>TCP/IP No attribute found</b>
<b>XTS1082E</b>	<b>TCP/IP Out of STREAM resources</b>
<b>XTS1083E</b>	<b>TCP/IP System call timed out</b>
<b>XTS1084E</b>	<b>TCP/IP Next message has wrong type</b>
<b>XTS1085E</b>	<b>TCP/IP Protocol error</b>
<b>XTS1086E</b>	<b>TCP/IP No message on stream read queue</b>
<b>XTS1087E</b>	<b>TCP/IP fd not associated with a stream</b>

<b>XTS1088E</b>	<b>TCP/IP Security authentication denied</b>
<b>XTS1089E</b>	<b>TCP/IP Not a trusted program</b>
<b>XTS1090E</b>	<b>TCP/IP Illegal byte sequence</b>
<b>XTS1091E</b>	<b>TCP/IP Network subsystem is unavailable</b>
<b>XTS1092E</b>	<b>TCP/IP WINSOCK.DLL version out of range</b>
<b>XTS1093E</b>	<b>TCP/IP Successful WSAShutdown not yet performed</b>
<b>XTS1094E</b>	<b>TCP/IP Cross mount point (not really error)</b>
<b>XTS1095E</b>	<b>TCP/IP cannot start operation</b>
<b>XTS1096E</b>	<b>TCP/IP Cannot access a needed shared library</b>
<b>XTS1097E</b>	<b>TCP/IP operation (now) in progress</b>
<b>XTS1098E</b>	<b>TCP/IP Lib section in a.out corrupted</b>
<b>XTS1099E</b>	<b>TCP/IP Attempting to link in too many shared libraries</b>
<b>XTS1100E</b>	<b>TCP/IP Cannot exec a shared library directly</b>
<b>XTS1101E</b>	<b>TCP/IP Graceful shutdown in progress</b>
<b>XTS1102E</b>	<b>TCP/IP Streams pipe error</b>
<b>XTS1103E</b>	<b>TCP/IP Structure needs cleaning</b>
<b>XTS1104E</b>	<b>TCP/IP Not a XENIX named tip file</b>

**XTS1105E**                    **TCP/IP No XENIX semaphores available**

**XTS1106E**                    **TCP/IP Is a named type file**

**XTS1107E**                    **TCP/IP Remote I/O error**

**XTS1108E**                    **TCP/IP No medium found**

**XTS1109E**                    **TCP/IP Wrong medium type**

**XTS1111E**                    **TCP/IP Host not found**

**XTS1112E**                    **TCP/IP Non-authoritative host not found**

**XTS1113E**                    **TCP/IP This is a non-recoverable error**

**XTS1114E**                    **TCP/IP Valid name, no data record of requested type**

**XTS1115E**                    **TCP/IP Resource unavailable**

**XTS1116E**                    **TCP/IP Operation canceled**

**XTS1118E**                    **TCP/IP Disc quota exceeded**

**XTS1119E**                    **TCP/IP Identifier removed**

**XTS1120E**                    **TCP/IP Too many open files**

**XTS1122E**                    **TCP/IP Multihop attempted**

**XTS1123E**                    **TCP/IP No locks available**

**XTS1124E**                    **TCP/IP The link has been severed**

<b>XTS1125E</b>	<b>TCP/IP No message of the desired type</b>
<b>XTS1126E</b>	<b>TCP/IP Function not supported</b>
<b>XTS1127E</b>	<b>TCP/IP Directory not empty</b>
<b>XTS1128E</b>	<b>TCP/IP Operation not supported</b>
<b>XTS1129E</b>	<b>TCP/IP Value too large to be stored in data</b>
<b>XTS1130E</b>	<b>TCP/IP Stale NFS file handle</b>
<b>XTS1131E</b>	<b>TCP/IP There is no more data available</b>
<b>XTS1132E</b>	<b>TCP/IP The call has been canceled</b>
<b>XTS1133E</b>	<b>TCP/IP Invalid procedure table from service provider</b>
<b>XTS1134E</b>	<b>TCP/IP Invalid service provider version number</b>
<b>XTS1135E</b>	<b>TCP/IP Unable to initialize a service provider</b>
<b>XTS1136E</b>	<b>TCP/IP System call failure</b>
<b>XTS1137E</b>	<b>TCP/IP Service not found</b>
<b>XTS1138E</b>	<b>TCP/IP Type not found</b>
<b>XTS1139E</b>	<b>TCP/IP There is no more data available</b>
<b>XTS1140E</b>	<b>TCP/IP The call has been canceled</b>
<b>XTS1141E</b>	<b>TCP/IP Refused</b>



**XTS1142E** TCP/IP Cbannel number out of range

**XTS1143E** TCP/IP Level 2 not synchronized

**XTS1144E** TCP/IP Level 3 halted

**XTS1145E** TCP/IP Level 3 reset

**XTS1146E** TCP/IP Link number out of range

**XTS1147E** TCP/IP Protocol driver not attached

**XTS1148E** TCP/IP No 43 CSI structure available

**XTS1149E** TCP/IP Level 2 halted

**XTS1150E** TCP/IP Invalid exchange

**XTS1151E** TCP/IP Invalid request descriptor

**XTS1152E** TCP/IP Exchange full

**XTS1153E** TCP/IP No anode

**XTS1154E** TCP/IP Invalid request code

**XTS1155E** TCP/IP Invalid slot

**XTS1156E** TCP/IP File locking deadlock error

**XTS1157E** TCP/IP Bad fon file fmt

**XTS1158E** TCP/IP Process died with the lock

<b>XTS1159E</b>	<b>TCP/IP Lock is not recoverable</b>
<b>XTS1160E</b>	<b>TCP/IP Machine is not on the network</b>
<b>XTS1161E</b>	<b>TCP/IP Package not installed</b>
<b>XTS1162E</b>	<b>TCP/IP The object is remote</b>
<b>XTS1163E</b>	<b>TCP/IP Advertise error</b>
<b>XTS1164E</b>	<b>TCP/IP Mount error</b>
<b>XTS1165E</b>	<b>TCP/IP Communication error on send</b>
<b>XTS1166E</b>	<b>TCP/IP Locked lock was unmapped</b>
<b>XTS1167E</b>	<b>TCP/IP Name not unique on network</b>
<b>XTS1168E</b>	<b>TCP/IP FD invalid for this operation</b>
<b>XTS1169E</b>	<b>TCP/IP Remote address changed</b>