

Entire System Server

Entire System Server for Linux Messages

Version 2.1.17

September 2025

This document applies to Entire System Server Version 2.1.17 and all subsequent releases.

Specifications contained herein are subject to change and these changes will be reported in subsequent release notes or new editions.

Copyright © 1991-2025 Software GmbH, Darmstadt, Germany and/or its subsidiaries and/or its affiliates and/or their licensors.

The name Software AG and all Software GmbH product names are either trademarks or registered trademarks of Software GmbH and/or its subsidiaries and/or its affiliates and/or their licensors. Other company and product names mentioned herein may be trademarks of their respective owners.

Detailed information on trademarks and patents owned by Software GmbH and/or its subsidiaries is located at <https://softwareag.com/licenses>.

Use of this software is subject to adherence to Software GmbH's licensing conditions and terms. These terms are part of the product documentation, located at <https://softwareag.com/licenses> and/or in the root installation directory of the licensed product(s).

This software may include portions of third-party products. For third-party copyright notices, license terms, additional rights or restrictions, please refer to "License Texts, Copyright Notices and Disclaimers of Third-Party Products". For certain specific third-party license restrictions, please refer to section E of the Legal Notices available under "License Terms and Conditions for Use of Software GmbH Products / Copyright and Trademark Notices of Software GmbH Products". These documents are part of the product documentation, located at <https://softwareag.com/licenses> and/or in the root installation directory of the licensed product(s).

Use, reproduction, transfer, publication or disclosure is prohibited except as specifically provided for in your License Agreement with Software GmbH.

Document ID: NPRUX-MESSAGES-2117-20250930

Table of Contents

1 About this Documentation	1
Document Conventions	2
Online Information and Support	2
Data Protection	3
2 Entire System Server for Linux Messages	5
Entire System Server for Linux Messages NPR3251-NPR3300	6
Entire System Server Messages for Linux NPR3301-NPR3350	6
Entire System Server Messages for Linux NPR3351-NPR3400	12
Entire System Server Messages for Linux NPR3401-NPR3449	16
Entire System Server Messages for Linux NPR3450-NPR3500	19
Entire System Server Messages for Linux NPR3501-NPR3550	22
Entire System Server Messages for Linux NPR3601-NPR3999	26
Entire System Server Messages for Linux NPR4000-NPR4099	30
Entire System Server Messages for Linux NPR4100-NPR4199	33
Entire System Server Messages for Linux NPR9951-NPR9999	34

1 About this Documentation

- Document Conventions 2
- Online Information and Support 2
- Data Protection 3

Document Conventions

Convention	Description
Bold	Identifies elements on a screen.
Monospace font	Identifies service names and locations in the format <code>folder.subfolder.service</code> , APIs, Java classes, methods, properties.
<i>Italic</i>	Identifies: Variables for which you must supply values specific to your own situation or environment. New terms the first time they occur in the text. References to other documentation sources.
Monospace font	Identifies: Text you must type in. Messages displayed by the system. Program code.
{ }	Indicates a set of choices from which you must choose one. Type only the information inside the curly braces. Do not type the { } symbols.
	Separates two mutually exclusive choices in a syntax line. Type one of these choices. Do not type the symbol.
[]	Indicates one or more options. Type only the information inside the square brackets. Do not type the [] symbols.
...	Indicates that you can type multiple options of the same type. Type only the information. Do not type the ellipsis (...).

Online Information and Support

Product Documentation

You can find the product documentation on our documentation website at <https://documentation.softwareag.com>.

Product Training

You can find helpful product training material on our Learning Portal at <https://learn.software-ag.com>.

Tech Community

You can collaborate with Software GmbH experts on our Tech Community website at <https://tech-community.softwareag.com>. From here you can, for example:

- Browse through our vast knowledge base.
- Ask questions and find answers in our discussion forums.
- Get the latest Software GmbH news and announcements.
- Explore our communities.
- Go to our public GitHub and Docker repositories at <https://github.com/softwareag> and <https://hub.docker.com/publishers/softwareag> and discover additional Software GmbH resources.

Product Support

Support for Software GmbH products is provided to licensed customers via our Empower Portal at <https://empower.softwareag.com>. Many services on this portal require that you have an account. If you do not yet have one, you can request it at <https://empower.softwareag.com/register>. Once you have an account, you can, for example:

- Download products, updates and fixes.
- Search the Knowledge Center for technical information and tips.
- Subscribe to early warnings and critical alerts.
- Open and update support incidents.
- Add product feature requests.

Data Protection

Software AG products provide functionality with respect to processing of personal data according to the EU General Data Protection Regulation (GDPR). Where applicable, appropriate steps are documented in the respective administration documentation.

2 Entire System Server for Linux Messages

▪ Entire System Server for Linux Messages NPR3251-NPR3300	6
▪ Entire System Server Messages for Linux NPR3301-NPR3350	6
▪ Entire System Server Messages for Linux NPR3351-NPR3400	12
▪ Entire System Server Messages for Linux NPR3401-NPR3449	16
▪ Entire System Server Messages for Linux NPR3450-NPR3500	19
▪ Entire System Server Messages for Linux NPR3501-NPR3550	22
▪ Entire System Server Messages for Linux NPR3601-NPR3999	26
▪ Entire System Server Messages for Linux NPR4000-NPR4099	30
▪ Entire System Server Messages for Linux NPR4100-NPR4199	33
▪ Entire System Server Messages for Linux NPR9951-NPR9999	34

This chapter contains the following messages:

Entire System Server for Linux Messages NPR3251-NPR3300

NPR3300: NPR3300 NPR Service name exceeds :1: bytes - :2:

Text	NPR3300 NPR Service name exceeds :1: bytes - :2:
Explanation	The Broker service name used for the start of NPR/Linux is too long.
Action	Use a valid service name.

Entire System Server Messages for Linux NPR3301-NPR3350

NPR3301: NPR3301 NPR Service :1: starting on :2, PID :3

Text	NPR3301 NPR Service :1: starting on :2, PID :3
Explanation	Start message of NPR/Linux. The message contains the service name, the host name and the process ID

NPR3302: NPR3302 Variable :1: not found

Text	NPR3302 Variable :1: not found
Explanation	An environment variable or built-in variable could not be found.

NPR3303: NPR3303 NPR Service :1: reuses existing Broker service

Text	NPR3303 NPR Service :1: reuses existing Broker service
Explanation	The service was already registered at the Broker.
Action	No action required.

NPR3304: NPR3304 NPR Service :1: stopped, PID :2:, exit code :3:

Text	NPR3304 NPR Service :1: stopped, PID :2:, exit code :3:
Explanation	The shutdown of NPR/Linux is completed. The message contains the exit code of the NPR/Linux service.

NPR3305: NPR3305 NPR Service :1: - begin serving [SC :2:, SN :3:, SV :4:]

Text	NPR3305 NPR Service :1: - begin serving [SC :2:, SN :3:, SV :4:]
Explanation	If this message is logged, the NPR/Linux service has a functioning connection to the Broker, and is able to handle requests. Abbreviations: SC Service class (usually NPR) SN Server name SV Service name

NPR3306: NPR3306 NPR Service :1: - Broker Response :2: :3:

Text	NPR3306 NPR Service :1: - Broker Response :2: :3:
Explanation	The message contains the Broker message number and Broker message text. A Broker error might have occurred.
Action	Please refer to "EntireX Communicator Messages and Codes" for a detailed message description.

NPR3307: NPR3307 NPR Service :1: - connection to Broker :2: active (again)

Text	NPR3307 NPR Service :1: - connection to Broker :2: active (again)
Explanation	The connection to the Broker is active (again). The NPR/Linux service is able to handle requests.

NPR3308: NPR3308 "Integration_Mechanism" is invalid

Text	NPR3308 "Integration_Mechanism" is invalid
Explanation	The parameter "Integration_Mechanism" in the file npr.ini has an invalid value.

NPR3309: NPR3309 Not executing as Windows Service

Text	NPR3309 Not executing as Windows Service
Explanation	NPR/Windows: npretb.exe was not started as a Windows service. NPR/Windows is installed as a Windows service and must be executed as Windows service.

NPR3310: NPR3310 Windows Service started

Text	NPR3310 Windows Service started
Explanation	NPR/Windows: The Windows service for NPR/Windows was started.

NPR3311: NPR3311 NPR Service :1: registered at Broker :2:

Text	NPR3311 NPR Service :1: registered at Broker :2:
------	--

NPR3312: NPR3312 NPR Service :1: deregistered at Broker :2:

Text	NPR3312 NPR Service :1: deregistered at Broker :2:
------	--

NPR3313: NPR3313 NPR Service :1: is already running

Text	NPR3313 NPR Service :1: is already running
Explanation	Either a duplicate NPR/Linux start was attempted, or a previous NPR/Linux was not deregistered correctly at the Broker.
Action	Use "ETB_Dup_Check=no" in npr.ini, or invoke startnpr with the "-f" (force) option (or both), to force a NPR/Linux start.

NPR3314: NPR3314 NPR Service duplicate check not performed

Text	NPR3314 NPR Service duplicate check not performed
Explanation	The parameter "ETB_Dup_Check" has the value "no".

NPR3315: NPR3315 NPR Service :1: check, RC :2:

Text	NPR3315 NPR Service :1: check, RC :2:
Explanation	The check of the NPR Service ended erroneously. The return code is contained in the message.

NPR3316: NPR3316 NPR Service :1: already running (PID :2:, shared memory :3:)

Text	NPR3316 NPR Service :1: already running (PID :2:, shared memory :3:)
Explanation	A duplicate NPR service start was attempted. The original process remains running and the duplicate process will be terminated.

NPR3317: NPR3317 Current Directory: :1:

Text	NPR3317 Current Directory: :1:
Explanation	The current directory during startup of NPR/Linux or NPR/Windows.

NPR3318: NPR3318 Operating System: :1:

Text	NPR3318 Operating System: :1:
Explanation	The operating system, under which NPR/Linux resp. NPR/Windows executes. The message also shows the addressing mode (32 bit or 64 bit).

NPR3319: NPR3319 Invalid Object :1:

Text	NPR3319 Invalid Object :1:
Explanation	The calling program passed an invalid object.

NPR3322: NPR3322 :1: not defined; you must modify :2:

Text	NPR3322 :1: not defined; you must modify :2:
Explanation	A parameter is missing in the npr.ini file.
Action	Add the requested parameter in the npr.ini file.

NPR3323: NPR3323 Entry :1: in :2: - wrong value :3:

Text	NPR3323 Entry :1: in :2: - wrong value :3:
Explanation	A parameter value in npr.ini has an invalid content.
Action	Correct the npr.ini file and try to restart the NPR service.

NPR3324: NPR3324 NPR Service :1: - Broker :2: not accessible - retrying ...

Text	NPR3324 NPR Service :1: - Broker :2: not accessible - retrying ...
Explanation	The connection to the Broker is lost. NPR/Linux remains alive and tries to re-establish the Broker connection periodically.

NPR3325: NPR3325 Function :1: not defined for :2:

Text	NPR3325 Function :1: not defined for :2:
Explanation	The calling program passed an invalid function for the object.

NPR3326: NPR3326 PID :1: not assigned to :2:

Text	NPR3326 PID :1: not assigned to :2:
Explanation	JOB/CANCEL, Linux: The auxiliary output file contained an unexpected process ID.

NPR3327: NPR3327 PID :1: not found

Text	NPR3327 PID :1: not found
Explanation	The displayed PID could not be found in the system.

NPR3328: NPR3328 Fatal Error: Cannot execute :1:

Text	NPR3328 Fatal Error: Cannot execute :1:
------	---

NPR3329: NPR3329 :1:

Text	NPR3329 :1:
Explanation	A system error occurred. The message contains the message number and/or message text. The origin of the message text may be the operating system.

NPR3330: NPR3330 Invalid file handle :1:

Text	NPR3330 Invalid file handle :1:
Explanation	The file handle passed by the calling program is invalid.

NPR3331: NPR3331 Too many files for :1:

Text	NPR3331 Too many files for :1:
------	--------------------------------

NPR3332: NPR3332 Invalid access restrictions :1: for file :2:

Text	NPR3332 Invalid access restrictions :1: for file :2:
------	--

NPR3333: NPR3333 Cannot get :1: for user :2:

Text	NPR3333 Cannot get :1: for user :2:
Explanation	The internal uid or gid for the given user can not be obtained from the system.

NPR3334: NPR3334 Can not get user name for :1:

Text	NPR3334 Can not get user name for :1:
------	---------------------------------------

NPR3335: NPR3335 Successful operation

Text	NPR3335 Successful operation
Explanation	The function has been performed successfully.

NPR3336: NPR3336 Memory allocation failed for :1:

Text	NPR3336 Memory allocation failed for :1:
------	--

NPR3338: NPR3338 No match for :1:

Text	NPR3338 No match for :1:
------	--------------------------

NPR3339: NPR3339 Object not found

Text	NPR3339 Object not found
------	--------------------------

NPR3340: NPR3340 Shared memory access error :1:

Text	NPR3340 Shared memory access error :1:
------	--

NPR3341: NPR3341 Function :1: not yet implemented

Text	NPR3341 Function :1: not yet implemented
------	--

NPR3342: NPR3342 No "Administrator" defined

Text	NPR3342 No "Administrator" defined
Explanation	The parameter "Administrator" must be defined in npr.ini.

NPR3345: NPR3345 More objects available

Text	NPR3345 More objects available
------	--------------------------------

NPR3346: NPR3346 No more data

Text	NPR3346 No more data
------	----------------------

NPR3347: NPR3347 Bad buffer format :1:

Text	NPR3347 Bad buffer format :1:
Explanation	The calling program passed an invalid buffer format.
Action	Contact Software AG support.

NPR3348: NPR3348 Record length not multiple of :1:

Text	NPR3348 Record length not multiple of :1:
------	---

NPR3349: NPR3349 Bad network path

Text	NPR3349 Bad network path
------	--------------------------

Entire System Server Messages for Linux NPR3351-NPR3400

NPR3354: NPR3354 Exit code message not found

Text	NPR3354 Exit code message not found
Explanation	No 'exit code' message could be found in the SYSOUT file of a job.

NPR3355: NPR3355 Exit code :1:

Text	NPR3355 Exit code :1:
Explanation	The message contains the exit code of the executed script or executable.

NPR3356: NPR3356 Environment variable :1: set to :2:

Text	NPR3356 Environment variable :1: set to :2:
Explanation	An environment variable was set.

NPR3357: NPR3357 Environment variable :1: has value :2:

Text	NPR3357 Environment variable :1: has value :2:
Explanation	This message is displayed for information purposes.

NPR3358: NPR3358 Environment variable :1: can not be defined

Text	NPR3358 Environment variable :1: cannot be defined
------	--

NPR3359: NPR3359 Environment variable :1: is not defined

Text	NPR3359 Environment variable :1: is not defined
------	---

NPR3360: NPR3360 Cannot open :1:

Text	NPR3360 Cannot open :1:
Explanation	A file or directory cannot be opened for reading.

NPR3361: NPR3361 Cannot write :1:

Text	NPR3361 Cannot write :1:
Explanation	A file cannot be opened for writing.

NPR3362: NPR3362 Cannot create :1:

Text	NPR3362 Cannot create :1:
Explanation	A file or directory cannot be created.

NPR3366: NPR3366 Permission denied for :1:

Text	NPR3366 Permission denied for :1:
------	-----------------------------------

NPR3367: NPR3367 Not found: :1:

Text	NPR3367 Not found: :1:
------	------------------------

NPR3368: NPR3368 Cannot get group name for :1:

Text	NPR3368 Cannot get group name for :1:
------	---------------------------------------

NPR3369: NPR3369 Group :1: not for user :2:

Text	NPR3369 Group :1: not for user :2:
Explanation	The user :2: is not member of the group :1:.

NPR3370: NPR3370 User :1: undefined

Text	NPR3370 User :1: undefined
------	----------------------------

NPR3371: NPR3371 Access denied for user

Text	NPR3371 Access denied for user
------	--------------------------------

NPR3372: NPR3372 Wrong NPR version :1;; function :2: not supported by this

Text	NPR3372 Wrong NPR version :1;; function :2: not supported by this version.
------	--

NPR3373: NPR3373 Not logged in

Text	NPR3373 Not logged in
Explanation	For this function a login is required.

NPR3374: NPR3374 Password invalid for the user

Text	NPR3374 Password invalid for the user
Action	Please login with a valid password.

NPR3375: NPR3375 Operation is not allowed for the user

Text	NPR3375 Operation is not allowed for the user
------	---

NPR3376: NPR3376 NPR has no 'root' rights

Text	Text NPR3376 NPR has no 'root' rights
Explanation	Functions requiring 'root' rights can't be performed during this NPR session.

NPR3377: NPR3377 Version error

Text	NPR3377 Version error
Explanation	There is a mismatch between the versions of npretb and libnpr.so(sl) (resp. npretb.exe and libnpr.dll on Windows). This is an installation error. The message shows the versions of the affected modules.
Action	Correct your installation.

NPR3380: NPR3380 Line :1:: :2:

Text	NPR3380 Line :1:: :2:
------	-----------------------

NPR3390: NPR3390 Signal :1: received

Text	NPR3390 Signal :1: received
Explanation	The signal handler of NPR/Linux or NPR/Windows received the displayed signal from the operating system.

NPR3391: NPR3391 Shutdown was requested by signal :1:

Text	NPR3391 Shutdown was requested by signal :1:
------	--

NPR3392: NPR3392 Exiting due to signal :1:

Text	NPR3392 Exiting due to signal :1:
Explanation	The NPR/Linux or NPR/Windows service is terminating.

NPR3393: NPR3393 System shutdown in progress

Text	NPR3393 System shutdown in progress
Explanation	Windows: An operating system shutdown is in progress.

NPR3394: NPR3394 Shutdown during Broker timeout

Text	NPR3394 Shutdown during Broker timeout
------	--

NPR3395: NPR3395 Command line: :1:

Text	NPR3395 Command line: :1:
Explanation	The message shows the command line, with which npretb (Windows: npretb.exe) was invoked.

NPR3398: NPR3398 Shared Memory :1: started

Text	NPR3398 Shared Memory :1: started
------	-----------------------------------

NPR3399: NPR3399 Shared Memory :1: stopped

Text	NPR3399 Shared Memory :1: stopped
------	-----------------------------------

Entire System Server Messages for Linux NPR3401-NPR3449

NPR3401: NPR3401 Mode set to :1: for :2:

Text	NPR3401 Mode set to :1: for :2:
------	---------------------------------

NPR3402: NPR3402 Current directory could not be determined. Exiting.

Text	NPR3402 Current directory could not be determined. Exiting.
------	---

NPR3403: NPR3403 Environment variable or directory access error. Exiting.

Text	NPR3403 Environment variable or directory access error. Exiting.
------	--

NPR3404: NPR3404 Empty message

Text	NPR3404 Empty message
------	-----------------------

NPR3405: NPR3405 Message not found: :1: (size :2:)

Text	NPR3405 Message not found: :1: (size :2:)
Explanation	A message text could not be found.
Action	Please contact Software AG Support.

NPR3406: NPR3406 Exit code message not found

Text	NPR3406 Exit code message not found.
Explanation	NPR could not find a message in the SYSOUT of a process that contains it's exit code.

NPR3407: NPR3407 Exit code not found

Text	NPR3407 Exit code not found
------	-----------------------------

NPR3411: NPR3411 Job could not be started

Text	NPR3411 Job could not be started
------	----------------------------------

NPR3412: NPR3412 User :1:, pam_start error :2:

Text	NPR3412 User :1:, pam_start error :2:
Explanation	Linux: A PAM error occurred.

NPR3413: NPR3413 User :1:, pam_authenticate error :2:

Text	NPR3413 User :1:, pam_authenticate error :2:
Explanation	Linux: A PAM error occurred.

NPR3414: NPR3414 User :1:, no permission for getuserpw (owner root ?)

Text	NPR3414 User :1:, no permission for getuserpw (owner root ?)
Action	Please check if npretb has root rights and if the bits are set.

NPR3415: NPR3415 User :1: undefined (getuserpw) - :2:

Text	NPR3415 User :1: undefined (getuserpw) - :2:
------	--

NPR3416: NPR3416 User :1: undefined or invalid password

Text	NPR3416 User :1: undefined or invalid password
Action	Please use a valid user ID and/or password.

NPR3417: NPR3417 SE_TCB_NAME privilege not held

Text	NPR3417 SE_TCB_NAME privilege not held
Explanation	This message is Windows specific.

NPR3418: NPR3418 User :1:: batch logon not granted

Text	NPR3418 User :1:: batch logon not granted
Explanation	Windows: The user must have the right to execute batch jobs.

NPR3419: NPR3419 Logon user :1;, Windows error :2:

Text	NPR3419 Logon user :1;, Windows error :2:
Explanation	Windows: A Windows error occurred during the logon processing.

NPR3421: NPR3421 Synchron file not found: :1:

Text	NPR3421 Synchron file not found: :1:
------	--------------------------------------

NPR3422: NPR3422 Library file not found: :1:

Text	NPR3422 Library file not found: :1:
------	-------------------------------------

NPR3423: NPR3423 Library :1: loaded

Text	NPR3423 Library :1: loaded
------	----------------------------

NPR3424: NPR3424 Library :1:: at least one entry not found

Text	NPR3424 Library :1:: at least one entry not found
Explanation	The loading of the library failed.
Action	Please contact Software AG support.

NPR3425: NPR3425 Library :1: not loaded. Usage disabled.

Text	NPR3425 Library :1: not loaded. Usage disabled.
------	---

NPR3429: NPR3429 PAM module ":1:" is unknown

Text	NPR3429 PAM module ":1:" is unknown
------	-------------------------------------

NPR3431: NPR3431 NetWare API's can be used

Text	NPR3431 NetWare API's can be used
------	-----------------------------------

NPR3440: NPR3440 Drive :1: released. Assignment was :2:

Text	NPR3440 Drive :1: released. Assignment was :2:
------	--

NPR3441: NPR3441 Drive :1: assigned to :2: (type :3:)

Text	NPR3441 Drive :1: assigned to :2: (type :3:)
------	--

NPR3442: NPR3442 Drive :1: assignment to :2: kept

Text	NPR3442 Drive :1: assignment to :2: kept
------	--

Entire System Server Messages for Linux NPR3450-NPR3500**NPR3450: NPR3450 Target file cannot be created**

Text	NPR3450 Target file cannot be created
------	---------------------------------------

NPR3451: NPR3451 Path not fully qualified

Text	NPR3451 Path not fully qualified
Action	Please use a fully qualified path name.

NPR3452: NPR3452 File name missing

Text	NPR3452 File name missing
------	---------------------------

NPR3453: NPR3453 Directory not found

Text	NPR3453 Directory not found
------	-----------------------------

NPR3454: NPR3454 Directory access denied

Text	NPR3454 Directory access denied
------	---------------------------------

NPR3455: NPR3455 Directory creation error

Text	NPR3455: NPR3455 Directory creation error
------	---

NPR3458: NPR3458 Environment variable :1: not determinable- - no session

Text	NPR3458 Environment variable :1: not determinable- - no session
Explanation	The environment variable can be determined only if a session exists.

NPR3459: NPR3459 Environment variable :1: is empty

Text	NPR3459 Environment variable :1: is empty
------	---

NPR3461: NPR3461 IPC_Prefix must be hexadecimal (000 - ffff)

Text	NPR3461 IPC_Prefix must be hexadecimal (000 - ffff)
------	---

NPR3462: NPR3462 Same (old) service with PID :1: found - forcing start

Text	NPR3462 Same (old) service with PID :1: found - forcing start
------	---

NPR3463: NPR3463 Killing old service :1: with PID :2: (shared memory :3:)

Text	NPR3463 Killing old service :1: with PID :2: (shared memory :3:)
------	--

NPR3469: NPR3469 NPR Service :1: - using INI file section [:2:]

Text	NPR3469 NPR Service :1: - using INI file section [:2:]
------	--

NPR3470: NPR3470 NPR Service :1: - section missing in INI file

Text	NPR3470: NPR3470 NPR Service :1: - section missing in INI file
------	--

NPR3471: NPR3471 NPR Service :1: PID :2: - start aborted

Text	NPR3471 NPR Service :1: PID :2: - start aborted
------	---

NPR3472: NPR3472 NPR Service :1: is active

Text	NPR3472 NPR Service :1: is active
------	-----------------------------------

NPR3473: NPR3473 NPR Service :1: is not registered at :2:

Text	NPR3473 NPR Service :1: is not registered at :2:
------	--

NPR3475: NPR3475 NPR Service :1: deregistered during shutdown, Broker :2:

Text	NPR3475 NPR Service :1: deregistered during shutdown, Broker :2:
------	--

NPR3479: NPR3479 NPR Service :1: was inactive since :2:

Text	NPR3479 NPR Service :1: was inactive since :2:
------	--

NPR3481: NPR3481 NPR Service :1: - Password for :2: could not be deciphered

Text	NPR3481 NPR Service :1: - Password for :2: could not be deciphered .
Action	Please use the utility nprpwc (resp. nprpwc.exe) for password ciphering.

NPR3490: NPR3490 Broker Service: :1:

Text	NPR3490 Broker Service: :1:
------	-----------------------------

NPR3491: NPR3491 Broker: :1:

Text	NPR3491 Broker: :1:
Explanation	This message is being used for several status informations about the Broker and the Broker stub.

NPR3492: NPR3492 Last Broker response time: :1:

Text	NPR3492 Last Broker response time: :1:
------	--

NPR3499: NPR3499 Broker Stub: :1:

Text	NPR3499 Broker Stub: :1:
------	--------------------------

Entire System Server Messages for Linux NPR3501-NPR3550

NPR3501: NPR3501 Current umask (octal): :1:

Text	NPR3501 Current umask (octal): :1:
Explanation	The message shows the umask, which is in effect during the startup of NPR/Linux.

NPR3502: NPR3502 Current uid: :1: (:2:)

Text	NPR3502 Current uid: :1: (:2:)
Explanation	The message shows the uid, which is in effect during the startup of NPR/Linux.

NPR3504: NPR3504 Current User: :1: - Group: :2:

Text	NPR3504 Current User: :1: - Group: :2:
------	--

NPR3505: NPR3505 Current User: :1:

Text	NPR3504 Current User: :1:
------	---------------------------

NPR3506: NPR3506 Executing under :1:

Text	NPR3506 Executing under :1:
------	-----------------------------

NPR3507: NPR3507 Built with :1:

Text	NPR3507 Built with :1:
Explanation	The message shows the compiler version, with which NPR was built.

NPR3508: NPR3508 NPR Version :1: (:2:)

Text	NPR3508 NPR Version :1: (:2:)
------	-------------------------------

NPR3509: NPR3509 Executing in :1: bit mode

Text	NPR3509 Executing in :1: bit mode
Explanation	The message shows, whether NPR executes in 32 bit mode or in 64 bit mode.

NPR3510: NPR3510 Size of time variables (time_t): :1:

Text	NPR3510 Size of time variables (time_t): :1:
------	--

NPR3511: NPR3511 Locale_String from system: :1:

Text	NPR3511 Locale_String from system: :1:
------	--

NPR3512: NPR3512 Explicit Locale_String : :1:

Text	NPR3512 Explicit Locale_String: :1:
------	-------------------------------------

NPR3513: NPR3513 Locale_String=no

Text	NPR3513 Locale_String=no
------	--------------------------

NPR3519: NPR3519 Server: :1:

Text	NPR3519 Server: :1:
------	---------------------

NPR3520: NPR3520 Windows Service: :1:

Text	NPR3520 Windows Service: :1:
------	------------------------------

NPR3521: NPR3521 Executable: :1:

Text	NPR3521 Executable: :1:
Explanation	The fully qualified path of the NPR executable.

NPR3522: NPR3522 S_ISUID and S_ISGID are set

Text	NPR3522 S_ISUID and S_ISGID are set
------	-------------------------------------

NPR3523: NPR3523 S_ISUID and / or S_ISGID is not set

Text	NPR3523 S_ISUID and / or S_ISGID is not set
------	---

NPR3524: NPR3524 s-Bits were not checked

Text	NPR3524 s-Bits were not checked
------	---------------------------------

NPR3529: NPR3529 Windows Service :1: is already running

Text	NPR3529 Windows Service :1: is already running
------	--

NPR3530: NPR3530 No PAM authentication

Text	NPR3530 No PAM authentication
------	-------------------------------

NPR3531: NPR3531 Using PAM authentication

Text	NPR3531 Using PAM authentication
------	----------------------------------

NPR3535: NPR3535 Open file timeout: :1: seconds

Text	NPR3535 Open file timeout: :1: seconds
------	--

NPR3541: NPR3541 No matching session

Text	NPR3541 No matching session
------	-----------------------------

NPR3545: NPR3545 Log directory: :1:

Text	NPR3545 Log directory: :1:
------	----------------------------

NPR3546: NPR3546 Log file: :1:

Text	NPR3546 Log file: :1:
------	-----------------------

NPR3551: NPR3551 :1: set to :2:

Text	NPR3551 :1: set to :2:
------	------------------------

NPR3552: NPR3552 Using trace file (prefix) :1:

Text	NPR3552 Using trace file (prefix) :1:
------	---------------------------------------

NPR3561: NPR3561 Using INI file :1:

Text	NPR3561 Using INI file :1:
------	----------------------------

NPR3562: NPR3562 INI file not found: :1:

Text	NPR3562 INI file not found: :1:
------	---------------------------------

NPR3563: NPR3563 :1: has value :2:

Text	NPR3563 :1: has value :2:
------	---------------------------

NPR3564: NPR3564 INI value not found: :1:

Text	NPR3564 INI value not found: :1:
------	----------------------------------

NPR3571: NPR3571 Using minimum value :1: for :2:

Text	NPR3571 Using minimum value :1: for :2:
------	---

NPR3581: NPR3581 Waiting :1: second(s) for retry

Text	NPR3581 Waiting :1: second(s) for retry
------	---

NPR3585: NPR3585 Waiting for reconnection

Text	NPR3585 Waiting for reconnection
------	----------------------------------

Entire System Server Messages for Linux NPR3601-NPR3999

NPR3601: NPR3601 Signal :1: ignored

Text	NPR3601 Signal :1: ignored
------	----------------------------

NPR3611: NPR3611 Invalid PID :1:

Text	NPR3611 Invalid PID :1:
------	-------------------------

NPR3631: NPR3631 Total commands: :1:, total elapsed time: :2: seconds

Text	NPR3631 Total commands: :1:, total elapsed time: :2: seconds
------	--

NPR3651: NPR3651 Password has expired

Text	NPR3651 Password has expired
------	------------------------------

NPR3660: NPR3660 Group :1: undefined

Text	NPR3660 Group :1: undefined
------	-----------------------------

NPR3661: NPR3661 User :1:, authentication service unavailable

Text	NPR3661 User :1:, authentication service unavailable
------	--

NPR3681: NPR3681 File Info Table full (> :1:)

Text	NPR3681 File Info Table full (> :1:)
Action	Please contact Software AG Support.

NPR3701: NPR3701 Permanent SSL error

Text	NPR3701 Permanent SSL error
------	-----------------------------

NPR3801: NPR3801 Function not available for :1:

Text	NPR3801 Function not available for :1:
------	--

NPR3811: NPR3811 Command is empty

Text	NPR3811 Command is empty
------	--------------------------

NPR3812: NPR3812 Command error

Text	NPR3812 Command error
------	-----------------------

NPR3813: NPR3813 Malformed e-mail address: :1:

Text	NPR3813 Malformed e-mail address: :1:
Explanation	One or more e-mail addresses in the command are invalid.

NPR3821: NPR3821 System error :1:

Text	NPR3821 System error :1:
Explanation	The message shows an error issued by the operating system.
Action	In case of unexpected or unusual error codes, please contact Software AG Support.

NPR3822: NPR3822 :1: - Access denied

Text	NPR3822 :1: - Access denied
------	-----------------------------

NPR3825: NPR3825 Output file not found

Text	NPR3825 Output file not found
------	-------------------------------

NPR3830: NPR3830 closeFile - unexpected file name

Text	NPR3830 closeFile - unexpected file name
Explanation	The file name passed by the caller is invalid for the file handle. The file handle was assigned to another file.

NPR3831: NPR3831 File not decodable – HTML mode :1: - Codepage Id :2:

Text	NPR3831 File not decodable – HTML mode :1: - Codepage Id :2:
------	--

NPR3835: NPR3835 File contains more than :1: records

Text	NPR3835 File contains more than :1: records
------	---

NPR3839: NPR3839 Record is longer than :1: bytes

Text	NPR3839 Record is longer than :1: bytes
------	---

NPR3841: NPR3841 Bad data buffer type :1:

Text	NPR3841 Bad data buffer type :1:
Action	Please contact Software AG Support.

NPR3845: NPR3845 Bad buffer content, buffer format :1:

Text	NPR3845 Bad buffer content, buffer format :1:
Action	Please contact Software AG Support.

NPR3846: NPR3846 Invalid buffer position :1;, buffer size :2:

Text	NPR3846 Invalid buffer position :1;, buffer size :2:
Action	Please contact Software AG Support.

NPR3849: NPR3849 Bad record separator :1:

Text	NPR3849 Bad record separator :1:
------	----------------------------------

NPR3851: NPR3851 Directory :1:

Text	NPR3851 Directory :1:
------	-----------------------

NPR3852: NPR3852 File :1:

Text	NPR3852 File :1:
------	------------------

NPR3853: NPR3853 ... user :1;, group :2;, access restrictions :3:

Text	NPR3853 ... user :1;, group :2;, access restrictions :3:
------	--

NPR3854: NPR3854 Access rights of :1: adjusted

Text	NPR3854 Access rights of :1: adjusted
Explanation	The access rights of a directory or file were adjusted automatically by NPR.

NPR3860: NPR3860 Tool :1: found: :2:

Text	NPR3860 Tool :1: found: :2:
Explanation	The message contains the location of the tool.

NPR3861: NPR3861 Tool :1: not found

Text	NPR3861 Tool :1: not found
------	----------------------------

Entire System Server Messages for Linux NPR4000-NPR4099

NPR4000: NPR4000 Command line is too long

Text	NPR4000 Command line is too long
------	----------------------------------

NPR4002: NPR4002 Syntax error: Unexpected end of command

Text	NPR4002 Syntax error: Unexpected end of command
------	---

NPR4003: NPR4003 Syntax error: :1: unexpected

Text	NPR4003 Syntax error: :1: unexpected
------	--------------------------------------

NPR4004: NPR4004 NPR Service :1: is already active

Text	NPR4004 NPR Service :1: is already active
------	---

NPR4005: NPR4005 NPR Service :1: will be started

Text	NPR4005 NPR Service :1: will be started
------	---

NPR4006: NPR4006 Unable to start NPR Service :1:

Text	NPR4006 Unable to start NPR Service :1:
------	---

NPR4007: NPR4007 NPR Service :1: - 'Server=:2:' definition not found

Text	NPR4007 NPR Service :1: - 'Server=:2:' definition not found
------	---

NPR4008: NPR4008 NPR Service :1: on :2: is active

Text	NPR4008 NPR Service :1: on :2: is active
------	--

NPR4009: NPR4009 NPR Service :1: on :2: is active (local, PID :3:)

Text	NPR4009 NPR Service :1: on :2: is active (local, PID :3:)
------	---

NPR4010: NPR4010 NPR Service :1: on :2: is not active or not accessible

Text	NPR4010 NPR Service :1: on :2: is not active or not accessible
------	--

NPR4011: NPR4011 NPR Service :1: - Stop in progress

Text	NPR4011 NPR Service :1: - Stop in progress
------	--

NPR4012: NPR4012 No service specified; all services will be displayed

Text	NPR4012 No service specified; all services will be displayed
------	--

NPR4013: NPR4013 Operation is allowed for user :1: only

Text	NPR4013 Operation is allowed for user :1: only
------	--

NPR4014: NPR4014 Stop request comes from own machine (:1:)

Text	NPR4014 Stop request comes from own machine (:1:)
------	---

NPR4015: NPR4015 NPR Service :1: - (external) SERVER/STOP received

Text	NPR4015 NPR Service :1: - (external) SERVER/STOP received
------	---

NPR4016: NPR4016 Cannot start NPR Service :1: on remote Server :2:

Text	NPR4016 Cannot start NPR Service :1: on remote Server :2:
------	---

NPR4017: NPR4017 User ID or password missing for login

Text	NPR4017 User ID or password missing for login
------	---

NPR4018: NPR4018 NPR Service :1: is not defined in :2:

Text	NPR4018 NPR Service :1: is not defined in :2:
Explanation	The NPR Service is not defined in the npr.ini file.

NPR4019: NPR4019 NPR Service :1: on :2: is not accessible locally

Text	NPR4019 NPR Service :1: on :2: is not accessible locally
------	--

NPR4020: NPR4020 Value range is :1: to :2:

Text	NPR4020 Value range is :1: to :2:
------	-----------------------------------

NPR4021: NPR4021 Handling services with :1:

Text	NPR4021 Handling services with :1:
------	------------------------------------

NPR4022: NPR4022 Stopping services with :1:

Text	NPR4022 Stopping services with :1:
------	------------------------------------

NPR4023: NPR4023 Stopping all services

Text	NPR4023 Stopping all services
------	-------------------------------

NPR4028: NPR4028 NPR Service :1: is still active (PID :2:) - waiting

Text	NPR4028 NPR Service :1: is still active (PID :2:) - waiting
Action	Please wait, until the NPR Service has recognized and executed the request.

NPR4029: NPR4029 NPR Service :1: on :2: stopped

Text	NPR4029 NPR Service :1: on :2: stopped
------	--

NPR4030: NPR4030 Function initialized

Text	NPR4030 Function initialized
------	------------------------------

NPR4049: NPR4049 Broker Library could not be loaded

Text	NPR4049 Broker Library could not be loaded
------	--

NPR4050: NPR4050 Broker Library loaded: :1:

Text	NPR4050 Broker Library loaded: :1:
------	------------------------------------

NPR4051: NPR4051 Broker Id is too long for API version :1: - maximum is :2:

Text	NPR4051 Broker Id is too long for API version :1: - maximum is :2:
------	--

NPR4061: NPR4061 Broker return length :1: less than expected :2:

Text	NPR4061 Broker return length :1: less than expected :2:
------	---

NPR4091: NPR4091 Service section [:1:] not found in :2:

Text	NPR4091 Service section [:1:] not found in :2:
Explanation	The service section could not be found in the npr.ini file.

Entire System Server Messages for Linux NPR4100-NPR4199**NPR4101: NPR4101 NPRMGR Start**

Text	NPR4101 NPRMGR Start
------	----------------------

NPR4102: NPR4102 NPRMGR End - exit code :1:

Text	NPR4102 NPRMGR End - exit code :1:
------	------------------------------------

NPR4103: NPR4103 NPRMGR Command: :1:

Text	NPR4103 NPRMGR Command: :1:
Explanation	The message shows the NPRMGR command to be executed.

NPR4109: NPR4109 NPRMGR terminating due to error

Text	NPR4109 NPRMGR terminating due to error
------	---

NPR4112: NPR4112 Stop Command set for NPR Service :1;, PID :2;, using IPC Key :3:

Text	NPR4112 Stop Command set for NPR Service :1;, PID :2;, using IPC Key :3:
------	--

NPR4121: NPR4121 Performing Command: :1:

Text	NPR4121 Performing Command: :1:
------	---------------------------------

Entire System Server Messages for Linux NPR9951-NPR9999

NPR9999: NPR9999 :1:

Text	NPR9999 :1:
Explanation	This message code is being used for various message texts.