

ADASIP* (Adabas VSE SVC) System Messages

Overview of Messages

ADASIP00	ADASIP01	ADASIP02	ADASIP03	ADASIP04	ADASIP05
ADASIP06	ADASIP08	ADASIP09	ADASIP10	ADASIP11	ADASIP12
ADASIP13	ADASIP14	ADASIP15	ADASIP16	ADASIP17	ADASIP18
ADASIP19	ADASIP20	ADASIP21	ADASIP22	ADASIP23	ADASIP24
ADASIP26	ADASIP27	ADASIP28	ADASIP29	ADASIP30	ADASIP31
ADASIP32	ADASIP33	ADASIP36	ADASIP37	ADASIP38	ADASIP39
ADASIP40	ADASIP41	ADASIP50	ADASIP60	ADASIP61	ADASIP62
ADASIP63	ADASIP64	ADASIP65	ADASIP66	ADASIP67	ADASIP68
ADASIP69	ADASIP70	ADASIP71	ADASIP72	ADASIP73	ADASIP74
ADASIP75	ADASIP76	ADASIP77	ADASIP78	ADASIP79	ADASIP80
ADASIP81	ADASIP85	ADASIP86	ADASIP87	ADASIP88	

ADASIP00 **Adabas Vav.ar VSE SIP started**
SIP is running under z/VSE Vvv.vr.vm
(yyyy-mm-dd. SM=sm-level , ZAP=zap-level)
SIP IS LOADING ADABAS SVC LEVEL sv.sr.sm
ADASIP IS LOADING ADABAS SVC AMODE=a-mode

Explanation The ADASIP program has started. The following substitutions appear in the message:

Substitution	Description
<i>av.ar</i>	version and release of Adabas.
<i>vv.vr.vm</i>	version, release, and modification level of z/VSE
<i>yyyy-mm-dd</i>	date of ADASIP module assembly
<i>sm-level</i>	system maintenance (SM) level of the ADASIP module
<i>zap-level</i>	Zap level of the ADASIP module
<i>sv.sr.sm</i>	version, release, and modification level of the Adabas SVC
<i>a-mode</i>	the AMODE setting of the Adabas SVC

ADASIP01 **SUBSID macro error**

Explanation ADASIP received a nonzero return code from the operating system.

Action: The VSE operating system release level is too low for installing Adabas. Refer to the Adabas Installation documentation for the minimum allowed VSE levels.

ADASIP02 Unsupported VSE release based upon SUBSID

Explanation An ADASIP validation check indicates an unsupported operating system level.

Action: The VSE operating system release level is too low for installing Adabas. Refer to the Adabas Installation documentation for the minimum allowed VSE levels.

ADASIP03 No SYSPARM value specified for SVC

Explanation ADASIP could not find a SYSPARM input, and a ZAP has not be applied to the specified SVC.

Action: Either provide the SVC with SYSPARM or apply a ZAP to the specified SVC with ADASIP.

ADASIP04 Default value used for the SVC

Explanation No SYSPARM SVC has been used. ADASIP defaults to using the SVC that has a ZAP applied.

ADASIP05 Non-numeric data found in SYSPARM field

Explanation Either SYSPARM or the default ADASIP SVC contains a nonnumeric value.

Action: Correct the specified SYSPARM value, or set the default SVC value to 30.

ADASIP06 Invalid range specified for the SVC 31-256

Explanation ADASIP found an SVC outside the allowed range in SYSPARM or the ADASIP default SVC.

Action: Set the SVC to an unused SVC value within the allowed range. SVC ranges and recommended values are described in the Adabas Installation documentation .

ADASIP08 ADASVC_{vv} was not found in the SVA

Explanation While performing a VSE load, ADASIP found that the specified level ADASVC was not in the SVA.

Action: Issue the SET SDL for ADASVC_{vv}. It may be necessary to relink the Adabas SVC with SVA using the PHASE statement if the Adabas SVC is not found in the Adabas library.

ADASIP09 No match on ID - incorrect ADASVC loaded

Explanation ADASIP found an incorrect SVC version while attempting a load operation.

Action: Relink ADASVC_{vv} with the correct SVC module.

ADASIP10 Unknown keyword in PARM field

Explanation ADASIP found an incorrect keyword in the PARM field.

Action: Correct the keyword parameter and rerun the job.

ADASIP11 Non-numeric data specified for NRIDTES

Explanation The ADASIP NRIDTES= keyword parameter specified non-numeric data.

Action: Correct the NRIDTES= data, then resubmit ADASIP.

ADASIP12 No overriding NRIDTES specified

Explanation The default NRIDTES was used. No error has occurred.

ADASIP13 SVC table entry was found to be invalid

Explanation The SVC number provided by SYSPARM is either not valid, or does not represent either the old or new version of the VSE Adabas SVC. This error can occur if the UPSI statement's "C" parameter specified "0".

Action: Respecify the UPSI statement, or specify another unused SVC value. Rerun ADASIP.

ADASIP14 GETVIS failure for IDT in SVA

Explanation The GETVIS of the IDT passed a nonzero return code back to ADASIP, meaning the GETVIS size was insufficient.

Action: Increase the SVA GETVIS size, re-IPL the operating system, and rerun ADASIP.

ADASIP15 Router unable to initialize IDT

Explanation ADASIP received a nonzero return code from the 56 call to the SVC.

Action: Contact your Software AG technical support representative.

ADASIP16 WARNING -- IDT table already exists

Explanation ADASIP detected that an IDT table for this SVC already exists.

Action: No action is required for this warning message.

ADASIP17 Incorrect SVC suffix after comma in SYSPARM

Explanation An attempt was made to run this program more than once for the current IPL. A second IDT for the program is not required.

Action: Correct the SYSPARM specification for the two-byte SVC suffix, and rerun the job.

ADASIP18 Non-numeric data specified for DMPDBID

Explanation The ADASIP DMPDBID keyword parameter contains nonnumeric data.

Action: Correct the DMPDBID specification, and rerun the job.

ADASIP19 DBID cannot be found in IDTE

Explanation The ADASIP program could not find an entry for the DMPDBID database in the IDT area.

Action: Either correct the DMPDBID specification or start the specified database, then run ADASIP to perform a "snap" dump of the command queue.

ADASIP20 The IDT and SVC have been dumped to SYSLST

Explanation A request to ADASIP to dump the IDT and then SVC via UPSI 80. No error has occurred.

ADASIP21 No IDT table was found for specified SVC

Explanation ADASIP found that the SVC has no address for the IDT.

Action: Specify the correct SVC, or initialize with ADASIP first.

ADASIP22 The SVC has already been installed

Explanation ADASIP found that the same program is being run again.

Action: The SVC is not installed and no IDT table is needed. To reinstall the same SVC, you must first perform a SET SDL.

ADASIP23	The SVC table cannot be listed under DOS/MVT
Explanation	The option to display the SVC table is specified under VSE.
ADASIP24	The IDT has been pagefixed by user option
Explanation	UPSI (X'20') was selected to pagefix the IDT in the system GETVIS area.
ADASIP26	Could not load the ADAOPD table
Explanation	ADASIP was unable to load phase ADAOPD.
Action:	Ensure that ADAOPD is available for loading and rerun the job.
ADASIP27	ADASVCxx must be AMODE=31, RMODE=24
Explanation	ADASIP detected that the Adabas SVC has invalid link-edit attributes.
Action:	Relink the Adabas SVC with the correct attributes and rerun the job.
ADASIP28	ADASIP is AMODE=31
Explanation	ADASIP detected that it is AMODE=31.
Action:	Relink ADASIP AMODE=24.
ADASIP29	PRODID macro failure
Explanation	ADASIP received a nonzero response code from the PRODID DEFINE macro.
Action:	Investigate the cause of the error. Correct it and rerun the job.
ADASIP30	ADASVCvv svc installed (Date yyymmdd)
Explanation	ADASIP has installed SVC number <i>svc</i> successfully.
ADASIP31	<i>address</i>=SVC address
Explanation	The SVC has been loaded at the indicated address.

ADASIP32 *address=IDT address*

Explanation The ID table has been allocated at the indicated address.

ADASIP33 **Invalid value specified for REPLACE parameter**

Explanation An invalid value was specified on the REPLACE parameter.

Action: Specify YES, Y, NO or N for the REPLACE parameter and rerun the job.

ADASIP36 *address=extended IIBS address*

Explanation The extended IIBs have been loaded at the indicated address.

ADASIP37 *address=IDT Extension address*

Explanation The IDT extension has been allocated at the indicated address.

Action: No action is required for this informational message.

ADASIP38 *address=SVC Work Area address*

Explanation The SVC work area has been allocated at the indicated address.

Action: No action is required for this informational message.

ADASIP39 **Error -- Targets still active on SVC nnn**

Explanation ADASIP detected that there are still active targets on the SVC listed in the message (nnn) and is unable to continue processing.

Action: No action is required for this informational message.

ADASIP40 **VSE SVC *svc* is status AM=*a-mode* RM=*r-mode* AR=*reg-mode* SVCT=*svc-tab-addr* MODT=*svc-mod-addr***

Explanation This message occurs when the option to list the SVC table is selected, and specifies the following values:

<i>svc</i>	the VSE SVC number
<i>status</i>	"USED" or "UNUSED"
<i>a-mode</i>	AMODE of this SVC, if used (24 or ANY)
<i>r-mode</i>	RMODE of this SVC, if used (24 or ANY)
<i>reg-mode</i>	access register mode of this SVC, if used (Y=yes, N=no)
<i>svc-tab-addr</i>	address of the SVC table entry for this SVC
<i>svc-mod-addr</i>	address of the SVC mode table entry for this SVC, if present

Action: None required. This message is for your information only. Do not use SVC50, even though it is indicated as "unused".

ADASIP41 **VSE SVC table audit completed**

Explanation ADASIP has completed listing the VSE SVC table.

ADASIP50 **The command queue has been dumped to SYSLST**

Explanation ADASIP has completed listing the command queue for the specified database.

ADASIP60 **Only 1 CPU can be active during ADASIP**

Action Use "SYSDEF TD,STOP=ALL" to stop all but one CPU so that ADASIP can run. Then restart your CPUs again.

ADASIP61 **Rerun ADASIP after using TDSERV to stop CPUs**

Explanation Occurs in conjunction with ADASIP60.

ADASIP62 **GETVIS failed for ADASTUB module**

Explanation Not enough SVA storage to load ADASTUB.

Action Consult with your system programmer.

ADASIP63	ADASTUB module loaded at <i>address</i>
Explanation	Information message indicating module load address.
ADASIP64	No match on ID - incorrect ADASTUB loaded
Explanation	ADASTUB phase is incorrect.
Action	Consult with your system programmer, or contact Software AG.
ADASIP65	ADASTUB SVC table not found
Explanation	ADASTUB phase is incorrect.
Action	Consult with your system programmer, or contact Software AG.
ADASIP66	ADASTUB SVC table is full
Explanation	You have more than 10 SVCs active on this VSE machine.
Action	Contact Software AG for information about increasing the table size.
ADASIP67	PAGEFIX for ADASIP failed
Action	Increase the SETPFIX value and rerun.
ADASIP68	PAGEFREE for ADASIP failed
Action	Consult with your system programmer.
ADASIP69	TURBO dispatcher stub active
Explanation	Adabas Turbo support is now active on this VSE machine.
ADASIP70	VSE supervisor hook install failed
Explanation	Either this version of the VSE 2 supervisor is not supported, or the vendor installation logic for the first-level interrupt handler is incorrect.
Action	Call Software AG; have message ADASIP72 available.

ADASIP71 Load of module ADASTUB failed

Explanation The ADASTUB module was not found in the LIBDEF SEARCH chain.

ADASIP72 Code is : *code*

Explanation Occurs after message ADASIP70.

ADASIP73 ADANCHOR incorrect or not found in SVA

Explanation The ADANCHOR module was not found in the SVA; no SET SDL has been done.

ADASIP74 Info: Stub activated by previous ADASIP

Explanation Adabas Turbo STUB has been installed by a previous ADASIP.

ADASIP75 ADANCHOR and ADASTUB not dumped - not active

Explanation When attempting to dump Adabas control blocks with ADASIP, the modules were not dumped because Adabas Turbo support is not active.

ADASIP76 Adabas turbo stub not activated due to error

Explanation An error occurred during the installation of the Adabas Turbo stub.

ADASIP77 This Adabas SVC will run in non-turbo mode

Explanation An error occurred during the installation of the Adabas Turbo stub. This SVC will run in non-Turbo mode from now on.

ADASIP78 VSE turbo dispatcher *nn*

Explanation Version of VSE Turbo Dispatcher.

ADASIP79 Should we stop the CPUs? (yes/no)

Explanation This message appears following ADASIP60 if more than one CPU is active during ADASIP processing.

Action Replying "no" terminates the job. Replying "yes" causes CPUs to be temporarily deactivated while ADASIP runs. ADASIP will reactivate any deactivated CPUs before terminating.

ADASIP80 SVCnnn Target ID *id* is active in partition *pp*

Explanation ADASIP does not allow an SVC to be reinstalled if there are active targets using the SVC, unless parameter REPLACE=YES is specified. If ADASIP parameter REPLACE=YES was specified, ADASIP replaces the current SVC regardless of any active targets.

An attempt to reinstall an SVC by rerunning ADASIP when there are active targets using the SVC results in warning messages ADASIP80 and ADASIP81 being issued. If the reply to ADASIP81 is "no", ADASIP terminates processing. If the reply to ADASIP is "yes", ADASIP will check again for active targets. If active targets are found, messages ADASIP80 and ADASIP81 will appear again. To proceed with ADASIP processing, active targets must be terminated before replying "yes" to message ADASIP81.

Note:

ADASIP will only flag a target as active if the job which activated the target is still running.

Action No action is required for this warning message.

ADASIP81 Should we continue processing? (yes/no)

Explanation An attempt was made to reinstall an SVC while there are active targets using the SVC. Unless the ADASIP parameter REPLACE=YES is specified, ADASIP does not allow an SVC to be reinstalled if there are active targets using the SVC. This prompt allows you to continue or stop processing.

Action Enter "yes" to continue or "no" to terminate processing.

**ADASIP85 SVA-24 storage allocated: *nnnnn*K
SVA-31 storage allocated: *nnnnn*K**

Explanation ADASIP has allocated *nnnnn*K of SVA storage below (SVA-24) or above (SVA-31) the 16 MB line.

Action No action is required for this informational message.

ADASIP86 **Reuse previous ADASTUB loaded at *address*? (yes/no)**
SVA-31 storage allocated: *nnnnnK*

Explanation ADASIP detected that ADASTUB has already been loaded.

A SET SDL for ADANCHOR should only be issued once per IPL. However, if ADASIP is rerun, and a SET SDL for ADANCHOR is issued a second time in error, it should be possible to preserve the existing Adabas communications environment by answering "yes" to message ADASIP86.

Action Reply "yes" to reuse the ADASTUB or "no" to load a new copy of ADASTUB. The recommended reply is "yes". Do not reply "no" to this message unless directed to do so by your Software AG technical support representative.

ADASIP87 **SYSLST unavailable**

Explanation ADASIP is not able to print messages on SYSLST, as this is unavailable. Console messages only will be issued. ADASIP continues processing.,

Action No action is required for this informational message.

ADASIP88 **Invalid parameter combination**

Explanation ADASIP detected an invalid combination of PARM parameters or UPSI bytes.

Action Correct the parameters or UPSI bytes and rerun the job.