

# Display Unused Storage

Option "U" displays a table of unused storage within the database:

```

16:30:53          ***** A D A B A S  BASIC SERVICES *****          2006-07-20
DBID 105          - Display Unused Storage -          PDRU002

      I Device I      Total Number of      I Extent      in Blk. I
      I Type  I      Blocks      / Cyls.  I from      -      until  I
-----I-----I-----I-----I-----I-----I-----I-----I
DATA I 8391 I      10862      144 I      130509 -      141370 I
-----I-----I-----I-----I-----I-----I-----I-----I
ASSO I 8391 I      8406      46 I      36583 -      44988 I
    
```

Separately for the Associator and Data Storage extents, the table shows the device type where the unused blocks are located, the number of unused storage blocks and cylinders, and the range of unused block numbers.

The equivalent direct command is

```

DISPLAY UNUSED
    
```