

ART* - Event Replicator Target Adapter Messages

Overview of Messages

ART0102I	ART0103E	ART0104I	ART0105I	ART0106I	ART0107I
ART0108E	ART0109E	ART0110E	ART0111E	ART0112I	ART0113I
ART0114I	ART0115E	ART0116I	ART0117I	ART0118I	ART0119E
ART0120E	ART0121E	ART0122I	ART0123E	ART0303I	ART0304I
ART0305I	ART0307I	ART0308I	ART0309I	ART0310I	ART0311I
ART0314I	ART0315I	ART0316I	ART0317I	ART0318I	ART0319I
ART0320E	ART0321E	ART0401I	ART0402I	ART0403I	ART0404I
ART0405I	ART0406I	ART0407I	ART0408I	ART0501I	ART0502I
ART0503I	ART0504I	ART0505I	ART0506I	ART0507E	ART0508E
ART0509E	ART0510E	ART0511E	ART0512E	ART0513E	ART0514E
ART0515I	ART0516I	ART0517E	ART0518E	ART0519E	ART0520E
ART0521E	ART0601I	ART0602E	ART0603I	ART0604E	ART0605E
ART0606E	ART0607E	ART0608E	ART0609E	ART0610E	ART0611E
ART0612E	ART0613I	ART0614I	ART0615E	ART0616E	ART0617E
ART0701I	ART0702I	ART0703I	ART0704I	ART0705E	ART0706E
ART0707E	ART0708E	ART0801I	ART0802I	ART0803I	ART0901E
ART0902I	ART1001E	ART1002E	ART1005W	ART1101I	ART1102I
ART1103E	ART1104I	ART1105I	ART1106I	ART1107I	ART1108E
ART1201I	ART1203W	ART1204E	ART1205E	ART1206E	ART1207E
ART1208I	ART1209I	ART1210I	ART1211E	ART1212E	ART1213E
ART1214W	ART1215E	ART1216E	ART1217F	ART1218F	ART1219E
ART1220E	ART1221E	ART1222E	ART1223E	ART1224E	ART1225E
ART1226E	ART1227E	ART1229E	ART1230E	ART1232E	ART1233I
ART1234I	ART1235W	ART1236E	ART1237W	ART1238I	ART1239I
ART1240E	ART1241W	ART1302I	ART1303E	ART1304E	ART1305E
ART1307E	ART1308E	ART1309E	ART1310I	ART1311I	ART1312I
ART1313I	ART1315I	ART1316E	ART1318I	ART1319E	ART1320E
ART1321E	ART1322E	ART1323E	ART1324E	ART1325E	ART1326I
ART1327E	ART1328E	ART1329E	ART1330E	ART1331E	ART1332E
ART1333E	ART1334E	ART1335E	ART1336E	ART1337E	ART1401I
ART1402E	ART1501I	ART1502I	ART1503I	ART1504I	ART1601I
ART1602I	ART1603I	ART1604I	ART1701W	ART1702W	ART1703W
ART1801E	ART1802E	ART1803E	ART1804I	ART1805I	ART1806E
ART1807E	ART1808E	ART1809E	ART1810E	ART2001E	ART2002E
ART2003E	ART2004E				

ART0102I **An Event Replicator Target Adapter engine is started and waiting for work**

Explanation An Event Replicator Target Adapter has successfully started and is waiting for work.

Action No action is required for this informational message.

ART0103E Unable to load resource bundle; Message**Explanation** This is an internal error.**Action** Contact your Software AG technical support representative for assistance.**ART0104I Version information *version*****Explanation** The version of the Event Replicator Target Adapter that is running is given in the message (*version*).**Action** No action is required for this informational message.**ART0105I Engine shutdown requested****Explanation** A request has been made to shut down the Event Replicator Target Adapter.**Action** No action is required for this informational message.**ART0106I Main processing loop shutdown requested****Explanation** A request has been made to shut down the main processing loop of the Event Replicator Target Adapter.**Action** No action is required for this informational message.**ART0107I Operation message: *input-msg*****Explanation** An operation message (*input-msg*) is listed in the text of this message.**Action** No action is required for this informational message.**ART0108E Invalid or unprocessed message received: *msg*****Explanation** An invalid or unprocessed message was received. The invalid message (*msg*) is provided in the text of this message.**Action** Review any previous messages to determine the primary cause of the problem. If the problem persists, contact your Software AG technical support representative for assistance.

ART0109E Cannot connect to target

Explanation An attempt to connect to a defined target failed.

Action Evaluate the target definition to determine the cause of the problem. If you cannot determine the cause of the problem, contact your Software AG technical support representative for assistance.

ART0110E Operation status: *status*

Explanation The status of the failed operation (*status*) is provided in the text of this message. This message accompanies other error messages. Possible statuses are "Failed" and "FailedRetry".

Action Review the other messages that accompany this one to determine the cause of the problem. If you cannot determine the cause of the problem, contact your Software AG technical support representative for assistance.

ART0111E Incorrect message: *msg*

Explanation The message in error (*msg*) is provided in the text of this message, which accompanies other error messages.

Action Review the other messages that accompany this one to determine the cause of the problem. If you cannot determine the cause of the problem, contact your Software AG technical support representative for assistance.

ART0112I Database retry count is 0

Explanation The database retry count setting has reached the value of zero (0). No further database retries are attempted and the source is closed.

Action Restart the database and reopen the source.

ART0113I Waiting *secs* seconds before database retry *number* of *total*

Explanation The Event Replicator Target Adapter is waiting the number of seconds listed in the message (*secs*) before attempting to reconnect to the source database. The retry attempt number (*number*) and the total number of retry attempts defined for the source (*total*) are also given in the message.

Action No action is required for this informational message.

ART0114I Attempting database retry *number* of *total*

Explanation The Event Replicator Target Adapter is attempting to reconnect to a source database. The retry attempt number (*number*) and the total number of retry attempts defined for the source (*total*) are given in the message.

Action No action is required for this informational message.

ART0115E XSLT or XML document is null

Explanation The style sheet (XSLT) or XML document to be used in Event Replicator Target Adapter processing is null or cannot be found. This is an internal error.

Action Contact your Software AG technical support representative for assistance.

ART0116I Committing invalid or unprocessed message

Explanation The invalid message was committed because the **Commit Unprocessed Message** option was set to true. Processing continues.

Action No action is required for this informational message.

ART0117I IVP message received and processed

Explanation The installation verification procedure (IVP) message was received and processed successfully.

Action No action is required for this informational message.

ART0118I Received *operation* request

Explanation The number of requests received is listed in the message (*count*).

Action No action is required for this informational message.

ART0119E Received unknown message *msg*

Explanation An unknown message was received.

Action Contact your Software AG technical support representative for assistance.

ART0120E **Cannot convert input message from***sourcecode* **page** *num1* **to** *num2*

Explanation The input message listed in the message text could not be converted from one code page (*num1*) to another (*num2*).

Action Contact your Software AG technical support representative for assistance.

ART0121E **Current messages**

Explanation This message accompanies message ARTO108E.

Action Review all the messages to determine the cause of the problem. If the problem persists, contact your Software AG technical support representative for assistance.

ART0122I **Problems writing file; directory must exist:** *dirname*

Explanation A file could not be written because the directory listed in the message did not exist.

Action Create the directory and restart the Event Replicator Target Adapter.

ART0123E **Unprocessed data** *count* **bytes in buffer** *buf*

Explanation An internal error has occurred.

Action Contact your Software AG technical support representative for assistance.

ART0303I **Initial-state process started for:** *isname*

Explanation The Event Replicator Target Adapter has started processing an initial-state request. The name of the initial-state definition (*isname*) is listed in the message.

Action No action is required for this informational message.

ART0304I **Initial-state process completed for:** *isname*

Explanation The Event Replicator Target Adapter has completed processing an initial-state request. The name of the initial-state definition (*isname*) is listed in the message.

Action No action is required for this informational message.

ART0305I Initial-state erroneous request rejected

Explanation An invalid initial-state request was rejected. It was not processed.

Action No action is required for this informational message. However, you might want to review the invalid initial-state request to determine why it was not processed.

ART0307I Normal Event Replicator Server session started message received from: *reptor-id*

Explanation A normal Event Replicator Server session has started and a message has been received from it. The Event Replicator Server ID is listed in the message (*reptor-id*).

Action No action is required for this informational message.

ART0308I Event Replicator Server restart after abnormal end

Explanation The Event Replicator Server has restarted after it ended abnormally.

Action No action is required for this informational message although you might want to review the error messages provided by the Event Replicator Server to determine why it ended abnormally.

ART0309I Normal Event Replicator Server session termination message received from: *reptor-id*

Explanation A normal Event Replicator Server session has terminated. The Event Replicator Server ID is listed in the message (*reptor-id*).

Action No action is required for this informational message.

ART0310I Replication deactivated

Explanation Replication has been deactivated (stopped).

Action No action is required for this informational message.

ART0311I Replication reactivated

Explanation Replication has been reactivated (started).

Action No action is required for this informational message.

ART0314I Replay process (ADARPL) started

Explanation The ADARPL utility has started to resend replicated data from the database protection log (PLOG) to the target RDBMS. For more information, read about the ADARPL utility in your Event Replicator for Adabas documentation.

Action No action is required for this informational message.

ART0315I Replay process (ADARPL) ended

Explanation The ADARPL utility has completed resending replicated data from the database protection log (PLOG) to the target RDBMS. For more information, read about the ADARPL utility in your Event Replicator for Adabas documentation.

Action No action is required for this informational message.

ART0316I Event Replicator Server replication definitions refreshed

Explanation The Event Replicator Server replication definitions have been refreshed via an RPLREFRESH command.

Action No action is required for this informational message.

ART0317I ADALOD UPDATE started

Explanation A run of the ADALOD UPDATE utility function has started.

Action No action is required for this informational message.

ART0318I ADALOD UPDATE ended

Explanation A run of the ADALOD UPDATE utility function has ended.

Action No action is required for this informational message.

ART0319I ADALOD LOAD ended. Source: *src* Target: *targ*

Explanation A run of the ADALOD LOAD utility function has ended.

Action No action is required for this informational message.

ART0320E **Unknown status message** *message*

Explanation An unknown status message was encountered during Event Replicator Target Adapter processing. The status message is given in the message text.

Action Contact your Software AG technical support representative for assistance.

ART0321E **Unknown URBS operation** *operation*

Explanation An unknown URBS operation was attempted. The type of operation attempted is listed in the message text.

Action Contact your Software AG technical support representative for assistance.

ART0401I **Testing database connections**

Explanation The Event Replicator Target Adapter is testing its database connections.

Action No action is required for this informational message.

ART0402I **Database information at startup:**

Explanation This message is the introductory message for a series of other informational messages about the databases to which the Event Replicator Target Adapter has connections.

Action No action is required for this informational message.

ART0403I **Connector protocol:** *protocol-type* **port:** *port*

Explanation This message lists the protocol type and port number used by the Event Replicator Target Adapter Tomcat engine.

Action No action is required for this informational message.

ART0404I **Using connector port:** *conn-port* **port:** *port*

Explanation This message lists the default HTTP port number that will be used.

Action No action is required for this informational message.

ART0405I Adabas Replicator servlet shutdown started**Explanation** The Event Replicator Server is shutting down.**Action** No action is required for this informational message.**ART0406I Adabas Replicator servlet shutdown complete****Explanation** The Event Replicator Server shutdown is complete.**Action** No action is required for this informational message.**ART0407I Testing connection to database resource *id*****Explanation** A test is being performed that connects to the database resource listed in the message (*id*).**Action** No action is required for this informational message.**ART0408I Database testing complete****Explanation** Tests on the database have completed.**Action** No action is required for this informational message.**ART0501I EntireX Broker information *info*****Explanation** This message displays information about a webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter.**Action** No action is required for this informational message.**ART0502I EntireX Broker source shutdown requested****Explanation** A request is being processed to close a webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter.**Action** No action is required for this informational message.

ART0503I **EntireX Broker source shutdown requested; processing: *state* userstop: *xxxx***

Explanation A webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter is being closed. The current state of the source is displayed in the message.

Action No action is required for this informational message.

ART0504I **EntireX Broker source close complete**

Explanation A webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter has been closed.

Action No action is required for this informational message.

ART0505I **EntireX Broker UOW rolled back ID: *id***

Explanation The webMethods EntireX unit of work ID was rolled back. This is an internal process.

Action No action is required for this informational message.

ART0506I **EntireX Broker prefetch size reached: *size***

Explanation The defined prefetch size for the webMethods EntireX source has been reached. The defined prefetch size is given in the message (*size*).

Action No action is required for this informational message. However, you might consider increasing the defined prefetch size. Note that increasing the prefetch size will increase the memory requirements.

ART0507E **EntireX Broker send error class: *class* code: *code* message: *msg***

Explanation An error has occurred during an attempt to send data to a webMethods EntireX source. The error class (*class*), message code (*code*) and message text (*msg*) are given in the message.

Action Refer to your webMethods EntireX documentation for additional information.

ART0508E **EntireX Broker error class: *class* code: *code* message: *msg***

Explanation An error has occurred during an attempt to use a webMethods EntireX source. The error class (*class*), message code (*code*) and message text (*msg*) are given in the message.

Action Refer to your webMethods EntireX documentation for additional information.

ART0509E EntireX Broker exception: *info*

Explanation An exception occurred during an attempt to use a webMethods EntireX source. The exception information (*info*) is given in the message.

Action Contact your Software AG technical support representative for assistance.

ART0510E EntireX Broker receive error class: *class* code: *code* message: *msg*

Explanation An error has occurred during an attempt to receive data from an webMethods EntireX source. The error class (*class*), message code (*code*) and message text (*msg*) are given in the message.

Action Refer to your webMethods EntireX documentation for additional information.

ART0511E EntireX Broker logon error ID: *class* service: *service* message: *msgtxt*

Explanation An error has occurred during an attempt to log into an webMethods EntireX source. The error class (*class*), service name (*service*), and message code (*msgtxt*) are given in the message.

Action Verify that the correct logon information (user ID, token, and password) is provided in the webMethods EntireX source definition. Correct it as necessary and try again.

ART0512E EntireX Broker error on: *id* cause: *exx-cause*

Explanation An error occurred during an attempt to use the webMethods EntireX source whose ID is listed in the message (*id*). The cause of the error is also listed in the message (*exx-cause*).

Action Contact your Software AG technical support representative for assistance.

ART0513E EntireX Broker commit error message: *err-msg*

Explanation An error occurred during an attempt to use a webMethods EntireX source definition. The webMethods EntireX error message (*err-msg*) is listed in the message.

Action Contact your Software AG technical support representative for assistance.

ART0514E EntireX Broker cannot open Broker trace log file: *fn*

Explanation An error occurred during an attempt to open the webMethods EntireX trace log file. The file name of the log file is given in the message (*fn*).

Action Verify that the correct file name is specified for the the webMethods EntireX trace log file in the webMethods EntireX definitions. If it is not, correct the name and try again. If the problem persists, contact your Software AG support representative for assistance.

ART0515I EntireX Broker trace level: *lvl* trace file: *fn*

Explanation This message identifies the trace level (*lvl*) and file name (*fn*) used by the Event Replicator Target Adapter for webMethods EntireX sources.

Action No action is required for this informational message.

ART0516I EntireX Broker receive complete: time: *count* Ms length: *length* UowStatus: *status*

Explanation A webMethods EntireX source received data from replication. The length of time (in microseconds) for the receive operation (*count*), the length of the data received (*length*), and the unit of work status of the receive operation (*status*) are given in the message. Values for the unit of work status are "First", "Middle" or "Last".

Action No action is required for this informational message.

ART0517E EntireX Broker commit error class: *class* code: *code* uowid: *uowid*

Explanation An error occurred during a commit attempt for the webMethods EntireX source. The error class (*class*), EntireX message code (*code*) and EntireX UOWID (*uowid*) are listed in the message.

Action Contact your Software AG technical support representative for assistance.

ART0518E EntireX Broker rollback error class: *class* code: *code* message: *mst*

Explanation An error occurred during a rollback attempt for the webMethods EntireX source. The error class (*class*), EntireX message code (*code*) and EntireX message text (*msg*) are listed in the message.

Action Contact your Software AG technical support representative for assistance.

ART0519E **EntireX Broker deregister error host: *host-id* service: *service* message: *msg***

Explanation An error occurred during an attempt to deregister a webMethods EntireX source. The EntireX ID (*host-id*), service (*service*) and message text (*msg*) are listed in the message.

Action Contact your Software AG technical support representative for assistance.

ART0520E **EntireX Broker user ID required**

Explanation A valid webMethods EntireX user ID is required but was not supplied.

Action Supply a valid webMethods EntireX user ID and try again.

ART0521E **EntireX Broker token required**

Explanation A valid webMethods EntireX token is required but was not supplied.

Action Supply a valid webMethods EntireX token and try again.

ART0601I **Save file *fn* with data: *dddd***

Explanation An attempt to save the file listed in the message (*fn*) with the data listed in the message (*dddd*) was successful.

Action No action is required for this informational message.

ART0602E **Read resource failed for: *resource-id* status code: *code***

Explanation An attempt to read from the resource listed in the message (*resource-id*) failed. The status code of the attempt is given in the message (*code*).

Action Contact your Software AG technical support representative for assistance.

ART0603I **Retrying resource read for: *resource-id***

Explanation An attempt is being made to read from the resource listed in the message (*resource-id*).

Action No action is required for this informational message.

ART0604E WebDAV error: *err-code*

Explanation A WebDAV error occurred during Event Replicator Target Adapter processing.

Action Verify that the web service target URL is correct and try again. If the problem persists, contact your Software AG technical support representative.

ART0605E WebDAV repository is not accessible *err-code*

Explanation The WebDAV repository cannot be accessed.

Action Verify that the web service target URL is correct and try again. If the problem persists, contact your Software AG technical support representative.

ART0606E Invalid WebDAV cache size *valuesize*

Explanation An invalid WebDAV cache size has been specified. The value was not numeric.

Action Supply a valid numeric cache size and try again.

ART0607E Cannot find generic XSLT file *filename*

Explanation The XSLT file listed in the message (*filename*) could not be found.

Action If the problem persists, contact your Software AG technical support representative.

ART0608E Cannot find XSLT file *filename*

Explanation The XSLT file listed in the message (*filename*) could not be found.

Action If the problem persists, contact your Software AG technical support representative.

ART0609E Create table XML message is null or base table name is null

Explanation An internal error has occurred.

Action If the problem persists, contact your Software AG technical support representative.

ART0610E Cannot convert create table schema to string

Explanation An internal error has occurred.

Action If the problem persists, contact your Software AG technical support representative.

ART0611E Cannot save create table schema *name* into WebDAV

Explanation An attempt to save the schema named in the message (*name*) to the WebDAV repository failed.

Action If the problem persists, contact your Software AG technical support representative.

ART0612E Problem with managing WebDAV file *filename*

Explanation The WebDAV file named in the message (*filename*) could not be managed.

Action If the problem persists, contact your Software AG technical support representative.

ART0613I Collection may not exist *colname*

Explanation The collection named in the message (*colname*) may not exist in the WebDAV repository. The collection is created.

Action No action is required for this informational message.

ART0614I Retrying resource write for *res*

Explanation An attempt is in progress to retry the resource write for the resource named in the message (*res*).

Action No action is required for this informational message.

ART0615E Write resource file *fn* failed *err-code*

Explanation An attempt to write the resource file named in the message (*fn*) failed.

Action If the problem persists, contact your Software AG technical support representative.

ART0616E WebDAV status code *code* status message *msg*

Explanation A WebDAV internal error has occurred.

Action If the problem persists, contact your Software AG technical support representative.

ART0617E Make collection *colname* failed status *stat*

Explanation An attempt to make the collection named in the message (*colname*) failed. The status of the attempt is also given in the message (*stat*).

Action If the problem persists, contact your Software AG technical support representative.

ART0701I Source shutdown complete

Explanation An attempt to shut down a source completed successfully.

Action No action is required for this informational message.

ART0702I Source waiting for restart after user stop or rollback

Explanation The source is waiting to be restarted after it was manually stopped or after a rollback occurred.

Action No action is required for this informational message. Restart the source when you are ready.

ART0703I Retries = 0; source waiting for manual restart

Explanation The value of the `Retry Count` parameter in the source definition has been reached. The source is waiting for a manual restart.

Action No action is required for this informational message. Manually restart the source when you are ready.

ART0704I Wait for retry; count: *count*

Explanation The source is waiting between retry attempts. The retry attempt count is given in the message (*count*).

Action No action is required for this informational message.

ART0705E No commit/rollback listener

Explanation An internal error has occurred.

Action Contact your Software AG technical support representative for assistance.

ART0706E Source message is null on commit**Explanation** An internal error has occurred.**Action** Contact your Software AG technical support representative for assistance.**ART0707E Unsupported source type *type*****Explanation** An internal error has occurred.**Action** Contact your Software AG technical support representative for assistance.**ART0708E Cannot open source capture file *fn*****Explanation** The file cannot be opened. Verify that the directory name exists.**Action** If the problem persists, contact your Software AG technical support representative.**ART0801I Runtime metrics****Explanation** This message is the heading message for a series of runtime metric messages.**Action** No action is required for this informational message.**ART0802I Resource key: *rkey*****Explanation** A resource key is listed in the message (*rkey*).**Action** No action is required for this informational message.**ART0803I Metrics key: *mkey*****Explanation** A metrics key is listed in the message (*mkey*).**Action** No action is required for this informational message.**ART0901E Process request failed****Explanation** An Event Replicator Target Adapter process request failed. The source is shut down.**Action** Review any accompanying error messages to determine the cause of the problem. If the problem persists, contact your Software AG technical support representative.

ART0902I Database active result: *result*

Explanation The result of a test to see whether the database is active or not is listed in the message (*result*).

Action No action is required for this informational message.

ART1001E Exception cause: *cause*

Explanation An Event Replicator Target Adapter process request failed. The cause of the failure is given in the message (*cause*).

Action Contact your Software AG technical support representative for assistance.

ART1002E Exception stack: *stack*

Explanation An Event Replicator Target Adapter process request failed. The exception stack for the failure is given in the message (*stack*).

Action Contact your Software AG technical support representative for assistance.

ART1005W Unable to transform document

Explanation The Event Replicator Target Adapter was unable to transform a document.

Action No action is required for this warning message. Determine the reason for which the Event Replicator Target Adapter cannot transform the document and alter the conditions as necessary. Then try again.

ART1101I File source configured for input directory: *dirname*

Explanation A file source definition has been configured for the input directory listed in the message (*dirname*).

Action No action is required for this informational message.

ART1102I File source ready to receive data from: *dirname*

Explanation A file source definition is ready to receive data from the directory listed in the message (*dirname*).

Action No action is required for this informational message.

ART1103E File source unable to get list of files

Explanation A file source could not get a list of the files from the source.

Action Determine why a list of files could not be obtained. Resolve the error and try again. If the problem persists, contact your Software AG support representative for assistance.

ART1104I File source closing

Explanation A file source is closing.

Action No action is required for this informational message.

ART1105I File source returning file: FILE:*dirnamefn***

Explanation The file source definition is returning the file source as part of the file source shutdown execution. The directory (*dirname*) and filename (*fn*) are given in the message.

Action No action is required for this informational message.

ART1106I File source shutdown requested

Explanation Shutdown of a file source was requested.

Action No action is required for this informational message.

ART1107I File source rollback called

Explanation Rollback of the updates from a file source was called.

Action No action is required for this informational message.

ART1108E File source file does not exist *fn*

Explanation The file source file named in the message (*fn*) does not exist. This is an internal message.

Action Contact your Software AG technical support representative for assistance.

ART1201I Rollback following SQL commands

Explanation A rollback occurred based on SQL commands.

Action No action is required for this informational message.

ART1203W **File name not provided for operation: *op* FNR: *fnum* ISN: *isnum***

Explanation A file name was not provided for the operation listed in the message (*op*). The file (*fnum*) and ISN (*isnum*) numbers are also listed in the message.

Action No action is required for this informational message.

ART1204E **Test connection failed: *conn-name***

Explanation A test connection to the connection listed in the message (*conn-name*) failed.

Action Restart the database if it is down.

ART1205E **Cannot get a connection from the data source**

Explanation An attempt to connect to a data source failed.

Action Review the data source definition and try again. If the problem persists, contact your Software AG technical support representative for assistance.

ART1206E **Cannot get metadata**

Explanation An attempt to connect to a data source failed.

Action Review the data source definition and try again. If the problem persists, contact your Software AG technical support representative for assistance.

ART1207E **Exception obtaining table metadata: *tblname***

Explanation An exception occurred while the Event Replicator Target Adapter was attempting to obtain metadata from a table. The name of the table is given in the message (*tblname*).

Action Contact your Software AG technical support representative for assistance.

ART1208I **Process is continuing after the previous error**

Explanation Event Replicator Target Adapter processing is continuing in spite of a previously reported error condition.

Action No action is required for this informational message.

ART1209I Unable to locate table: *tablename*

Explanation The Event Replicator Target Adapter could not locate the table listed in the message (*tablename*).

Action No action is required for this informational message. If you really do need the Event Replicator Target Adapter to locate this table, determine why it cannot be located and try again. If the problem persists, contact your Software AG technical support representative.

ART1210I Create index command built: *cmd*

Explanation An internal command to create the index to a table was successfully built.

Action No action is required for this informational message.

ART1211E Cannot get connection to data source *name*

Explanation An attempt to connect to the data source named in the message (*name*) failed.

Action Verify that the database definitions are correct and that the database is active.

ART1212E Cannot retrieve database metrics

Explanation An attempt to retrieve metrics for the database failed.

Action Contact your Software AG technical support representative for assistance.

ART1213E Internal error of Sybase ASE

Explanation An internal error occurred in Sybase ASE

Action Contact your Software AG technical support representative for assistance.

ART1214W Unknown data type *type* for column *colname* in metadata

Explanation An attempt was made to specify the unknown data type listed in the message (*type*) in the column listed in the message (*colname*).

Action Contact your Software AG technical support representative for assistance.

ART1215E **pkTableName *pkname* does not match with table name *tblname***

Explanation A mismatch has occurred between the table and the primary key. The table name (*tblname*) and the primary key (*pkname*) are given in the message.

Action Contact your Software AG technical support representative for assistance.

ART1216E **Cannot find previous column information**

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1217F **Initial context is null**

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1218F **Context lookup is null**

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1219E **Unsupported driver class name for JDBC/database *dbname***

Explanation An unsupported driver class name was specified for the JDBC database listed in the message (*dbname*).

Action Contact your Software AG technical support representative for assistance.

ART1220E **Error obtaining connection *err-code***

Explanation A connection to the database could not be made.

Action Verify that the database definitions are correct and that the database is active.

ART1221E **Table *tblname* has duplicate column name *colname***

Explanation The table named in the message (*tblname*) has two columns with the same name (*colname*).

Action Change one of the column names and try again.

ART1222E Cannot create statement**Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1223E Cannot connect to database *dbname*****Explanation** An attempt to connect to the database named in the message (*dbname*) failed.**Action** Verify that the database definitions are correct and that the database is active.**ART1224E Cannot execute batch****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1225E Cannot turn off database autocommit****Explanation** An attempt to turn off the autocommit feature of the database failed.**Action** Contact your Software AG technical support representative for assistance.**ART1226E Cannot create executing SQL statement****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1227E Process continuing because dbErrorContinue is TRUE****Explanation** The target database **Error Continue** option was set to "true" (selected or turned on), so the SQL error is ignored and processing continues.**Action** No action is required for this message.**ART1229E Unable to load/construct DB support class for *classname*****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.

ART1230E Update to insert mode is on but full image value is missing

Explanation An attempt to insert an update failed because the full image of the record is missing from the database.

Action Use Option=32 in the Event Replicator Server destination definition. For more information, refer to your Event Replicator for Adabas destination documentation.

ART1232E Cannot insert column

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1233I SQL command failed *cmd*

Explanation The SQL command listed in the message (*cmd*) failed.

Action Review other accompanying error messages to determine the cause of the problem. If the problem persists, contact your Software AG technical support representative for assistance.

ART1234I SQL command reason *rsncode*

Explanation The previous SQL command failed with the reason code (*rsncode*) given in the message.

Action Review the documentation for your RDBMS to determine the cause of the problem.

ART1235W Sync DDL value *val* is not one of the following values, ignore, warn, apply, error. Reset to ignore.

Explanation The value for the **Adabas-RDBMS Synchronization Level** option is invalid. It has been reset to "ignore".

Action In the target database options, change the setting of the **Adabas-RDBMS Synchronization Level** option to something other than "ignore" if you want.

ART1236E **Cannot alter column *detailed-info***

Explanation The Event Replicator Target Adapter could not alter the column described by the detailed information listed in the message (*detailed-info*) during its attempt to synchronize the RDBMS table with the Adabas file.

Action Make sure the target database supports this kind of type conversion and that this column is not a primary key and doesn't have foreign key. If the problem persists, contact your Software AG technical support representative for assistance.

ART1237W **Data type mismatch on column *detailed-info***

Explanation During an attempt to synchronize the RDBMS table with the Adabas file, the Event Replicator Target Adapter determined that a data type mismatch had occurred for the column described by the detailed information listed in the message (*detailed-info*).

Action Issue the same message as the previous one. The Event Replicator Target Adapter will continue to run because the **Adabas-RDBMS Synchronization Level** value is set to "warn". If the problem persists, contact your Software AG technical support representative for assistance.

ART1238I **Alter column *detailed-info***

Explanation The column described by the detailed information listed in the message (*detailed-info*) was altered in the RDBMS during Event Replicator Target Adapter synchronization between the RDBMS table and the Adabas file.

Action No action is required for this informational message.

ART1239I **Add column *detailed-info***

Explanation The column described by the detailed information listed in the message (*detailed-info*) was added to the RDBMS during Event Replicator Target Adapter synchronization between the RDBMS table and the Adabas file.

Action No action is required for this informational message.

ART1240E **Cannot add column *detailed-info***

Explanation The Event Replicator Target Adapter could not add the column described by the detailed information listed in the message (*detailed-info*) to the RDBMS during its attempt to synchronize the RDBMS table with the Adabas file.

Action Make sure the target database supports adding columns. If the problem persists, contact your Software AG technical support representative for assistance.

ART1241W Target database doesn't have column *detailed-info*

Explanation During an attempt to synchronize the RDBMS table with the Adabas file, the Event Replicator Target Adapter determined that the target RDBMS is missing the column described by the detailed information listed in the message (*detailed-info*).

This message is issued because the **Adabas-RDBMS Synchronization Level** value is set to "warn". In this case, the Event Replicator Target Adapter issues this warning message and continues processing.

Action No action is required for this warning message.

ART1302I Loader complete

Explanation The Event Replicator Target Adapter completed loading replicated data without failing.

Action No action is required for this informational message.

ART1303E Loader fail. Please check the log files *fn*

Explanation An attempt to load replicated data to the database via the Oracle SQL loader failed. The log files (*fn*) that contain more information are listed in the message.

Action Review the log files for more information about the failure. If possible, correct the error and try again. If the problem persists, contact your Software AG technical support representative for assistance.

ART1304E Loader exception

Explanation An exception occurred during the loading process.

Action Contact your Software AG technical support representative for assistance.

ART1305E Create table XML file *fn* does not exist

Explanation A request to create the table in an XML file failed because the XML file could not be found. The filename of the XML file is given in the message (*fn*).

Action Contact your Software AG technical support representative for assistance.

ART1307E Control file *fn* is not generated

Explanation The control file listed in the message (*fn*) was not generated.

Action Contact your Software AG technical support representative for assistance.

ART1308E Loader cannot support streaming mode

Explanation The loader cannot support streaming mode.

Action Modify the target database options used by the database so that the **Use Stream** option is not selected (checked) and try again. For more information, read *Specifying Target Database Processing Option Definitions*.

ART1309E Output file *fn* is not generated

Explanation The output file named in the message (*fn*) was not generated.

Action Contact your Software AG technical support representative for assistance.

ART1310I Current configuration cannot support streaming mode; change to nonstreaming mode

Explanation The current configuration does not support streaming mode. The Event Replicator Target Adapter turns stream mode off and retries the operation.

Action No action is required for this informational message.

ART1311I Current configuration cannot support loader mode; change to nonloader mode

Explanation The current configuration does not support the database in loader mode.

Action No action is required for this informational message.

ART1312I Loader process running

Explanation The database loader process is running.

Action No action is required for this informational message.

ART1313I Loader about to execute following command: *cmd*

Explanation The database loader process is executing the command listed in the message (*cmd*).

Action No action is required for this informational message.

ART1315I Create loader thread

Explanation An attempt by the Event Replicator Target Adapter to create a loader thread is in process.

Action No action is required for this informational message.

ART1316E Called with table: *tblname* column: *colname*

Explanation An error occurred trying to call the table (*tblname*) and column (*colname*) whose names are listed in the message.

Action Contact your Software AG technical support representative for assistance.

ART1318I Initial-state running in loader mode

Explanation The initial-state process is running in loader mode.

Action No action is required for this informational message.

ART1319E Cannot wait for loader process

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1320E Cannot find control file name

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1321E Cannot find log file name

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1322E Cannot find bad file name

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1323E Cannot find discard file name**Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1324E Cannot find out file name****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1325E Create loader process failed****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1326I Test loader process successful****Explanation** The test loader process completed successfully.**Action** No action is required for this informational message.**ART1327E Test loader process failed, exit code *code*****Explanation** The test loader process failed with the exit code listed in the message (*code*).**Action** Contact your Software AG technical support representative for assistance.**ART1328E Cannot create XsltWorker****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART1329E Cannot set up environment variables of file *fn*****Explanation** An attempt to set the environment variables for the file named in the message (*fn*) failed.**Action** Contact your Software AG technical support representative for assistance.

ART1330E Cannot support current database type

Explanation Support is not provided for the database type.

Action Change the database type to one that is supported by the Event Replicator Target Adapter. If necessary, contact your Software AG technical support representative for assistance.

ART1331E Worker is null

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1332E Cannot create loader thread

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1333E Cannot create piped stream

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1334E Loader failed. Current mode is streaming mode, change to nonstreaming mode and retry

Explanation The loader failed.

Action Modify the target database options used by the database so that the **Use Stream** option is not selected (checked) and try again. For more information, read *Specifying Target Database Processing Option Definitions*

ART1335E Cannot write to output stream

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1336E **Parsing error *err* line *lll* column *ccc* PID *pid* CID *cid***

Explanation A parsing error occurred. The error, line number, column number, process ID, and command ID are given in the message.

Action Contact your Software AG technical support representative for assistance.

ART1337E **Unable to send message to the loader**

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1401I **Transform document using XSLT file: *fn* token: *token***

Explanation The Event Replicator Target Adapter is attempting to transform the document using the XSLT file (*fn*) and token (*token*) listed in the message.

Action No action is required for this informational message.

ART1402E **Cannot convert from UTF8 byte array to a string**

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART1501I **Source manager shutdown requested**

Explanation A request was made to shut down the source manager.

Action No action is required for this informational message.

ART1502I **Source manager notified to shut down**

Explanation The source manager has been notified to shut down.

Action No action is required for this informational message.

ART1503I **Waiting for source manager shutdown to complete**

Explanation The Event Replicator Target Adapter is waiting for the source manager to fully shut down.

Action No action is required for this informational message.

ART1504I Source manager is down

Explanation The source manager shutdown has completed.

Action No action is required for this informational message.

ART1601I Engine manager shutdown requested

Explanation A request was made to shut down the engine manager.

Action No action is required for this informational message.

ART1602I Engine manager notified to shut down

Explanation The engine manager has been notified to shut down.

Action No action is required for this informational message.

ART1603I Waiting for engine manager shutdown to complete

Explanation The Event Replicator Target Adapter is waiting for the engine manager to fully shut down.

Action No action is required for this informational message.

ART1604I Engine manager is down

Explanation The engine manager shutdown has completed.

Action No action is required for this informational message.

ART1701W Parameter *parm* value *val* not numeric

Explanation The parameter named in the message (*parm*) specifies a value (*val*) that is not numeric.

Action Supply a numeric value for the parameter and try again.

ART1702W Parameter *parm* value *val* does not end with "S"

Explanation The parameter named in the message (*parm*) specifies a value (*val*) that does not end in an "S".

Action Supply a value for the parameter that ends in an "S" and try again.

ART1703W **Parameter *parm* value *val* is not "true" or "false"**

Explanation The parameter named in the message (*parm*) specifies a value (*val*) that is not "true" or "false."

Action Supply a "true" or "false" value for the parameter and try again.

ART1801E **Cannot open WebSphere MQ trace log file *fn***

Explanation An attempt to open the WebSphere MQ trace file named in the message (*fn*) failed.

Action Check your definition. Verify that the directory defined in your definitions exists.

ART1802E **WebSphere MQ rollback failed *err-code***

Explanation A rollback attempt for WebSphere MQ failed.

Action Review the webSphere MQ documentation to determine the reason for the failure.

ART1803E **WebSphere MQ logon failed host *hostid* port *portnum* error *err***

Explanation An attempt to logon to WebSphere MQ failed. The WebSphere MQ host ID (*hostid*), port number (*portnum*), and the error number (*err*) from the attempt are given in the message.

Action Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

ART1804I **WebSphere MQ logon to host *hostid* successful**

Explanation The attempt to log onto the WebSphere MQ host named in the message (*hostid*) was successful.

Action No action is required for this informational message.

ART1805I **WebSphere MQ receiving messages from queue *qname***

Explanation WebSphere MQ is receiving and processing messages from the queue listed in the message (*qname*).

Action No action is required for this informational message.

ART1806E Attempt to connect to queue manager failed

Explanation An attempt to connect to the WebSphere MQ queue manager failed.

Action Check with your WebSphere MQ administrator to determine why the attempt failed.
Resolve the problem and try again.

ART1807E WebSphere MQ receive failed *err-code*

Explanation A receive request via the WebSphere MQ queue failed.

Action Check with your WebSphere MQ administrator to determine why the attempt failed.
Resolve the problem and try again.

ART1808E WebSphere MQ commit failed *err-code*

Explanation A commit request via the WebSphere MQ queue failed.

Action Check with your WebSphere MQ administrator to determine why the attempt failed.
Resolve the problem and try again.

ART1809E WebSphere MQ send failed *err-code*

Explanation A send request via the WebSphere MQ queue failed.

Action Check with your WebSphere MQ administrator to determine why the attempt failed.
Resolve the problem and try again.

ART1810E WebSphere MQ close failed *err-code*

Explanation A close request via the WebSphere MQ queue failed.

Action Check with your WebSphere MQ administrator to determine why the attempt failed.
Resolve the problem and try again.

ART2001E Required target configuration not found *config* or default

Explanation An internal error occurred.

Action Contact your Software AG technical support representative for assistance.

ART2002E Operation is null**Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART2003E Operation *opname* is not supported****Explanation** An attempt to run the operation named in the message (*opname*) failed because it is not supported.**Action** Try an operation that is supported.**ART2004E Not SOAP element****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.