

# ART\* - Event Replicator Target Adapter Messages

## Overview of Messages

ART0102I	ART0103E	ART0104I	ART0105I	ART0106I	ART0107I
ART0108E	ART0109E	ART0110E	ART0111E	ART0112I	ART0113I
ART0114I	ART0115E	ART0116I	ART0117I	ART0118I	ART0119E
ART0120E	ART0121E	ART0122I	ART0123E	ART0124I	ART0125I
ART0303I	ART0304I	ART0305I	ART0307I	ART0308I	ART0309I
ART0310I	ART0311I	ART0314I	ART0315I	ART0316I	ART0317I
ART0318I	ART0319I	ART0320E	ART0321E	ART0322E	ART0323I
ART0324E	ART0325I	ART0401I	ART0402I	ART0403I	ART0404I
ART0405I	ART0406I	ART0407I	ART0408I	ART0409I	ART0410I
ART0501I	ART0502I	ART0503I	ART0504I	ART0505I	ART0506I
ART0507E	ART0508E	ART0509E	ART0510E	ART0511E	ART0512E
ART0513E	ART0514E	ART0515I	ART0516I	ART0517E	ART0518E
ART0519E	ART0520E	ART0521E	ART0601I	ART0602E	ART0603I
ART0604E	ART0605E	ART0606E	ART0607E	ART0608E	ART0609E
ART0610E	ART0611E	ART0612E	ART0613I	ART0614I	ART0615E
ART0616E	ART0617E	ART0701I	ART0702I	ART0703I	ART0704I
ART0705E	ART0706E	ART0707E	ART0708E	ART0801I	ART0802I
ART0803I	ART0901E	ART0902I	ART0903I	ART1001E	ART1002E
ART1005W	ART1101I	ART1102I	ART1103E	ART1104I	ART1105I
ART1106I	ART1107I	ART1108E	ART1109I	ART1201I	ART1203W
ART1204E	ART1205E	ART1206E	ART1207E	ART1208I	ART1209I
ART1210I	ART1211E	ART1212E	ART1213E	ART1214W	ART1215E
ART1216E	ART1217F	ART1218F	ART1219E	ART1220E	ART1221E
ART1222E	ART1223E	ART1224E	ART1225E	ART1226E	ART1227E
ART1228E	ART1229E	ART1230E	ART1232E	ART1233I	ART1234I
ART1235W	ART1236E	ART1237W	ART1238I	ART1239I	ART1240E
ART1241W	ART1242E	ART1302I	ART1303E	ART1304E	ART1305E
ART1307E	ART1308E	ART1309E	ART1310I	ART1311I	ART1312I
ART1313I	ART1315I	ART1316E	ART1318I	ART1319E	ART1320E
ART1321E	ART1322E	ART1323E	ART1324E	ART1325E	ART1326I
ART1327E	ART1328E	ART1329E	ART1330E	ART1331E	ART1332E
ART1333E	ART1334E	ART1335E	ART1336E	ART1337E	ART1338E
ART1339W	ART1340E	ART1341E	ART1342E	ART1343W	ART1344W
ART1401I	ART1402E	ART1501I	ART1502I	ART1503I	ART1504I
ART1601I	ART1602I	ART1603I	ART1604I	ART1701W	ART1702W
ART1703W	ART1801E	ART1802E	ART1803E	ART1804I	ART1805I
ART1806E	ART1807E	ART1808E	ART1809E	ART1810E	ART2001E
ART2002E	ART2003E	ART2004E	ART3001E	ART3002E	ART3003E
ART3004E	ART3005E	ART3006E			

---

**ART0102I**      **An Event Replicator Target Adapter engine is started and waiting for work**

**Explanation**      An Event Replicator Target Adapter has successfully started and is waiting for work.

**Action**              No action is required for this informational message.

**ART0103E**      **Unable to load resource bundle; message**

**Explanation**      This is an internal error.

**Action**              Contact your Software AG technical support representative for assistance.

**ART0104I**      **Version information *version***

**Explanation**      The version of the Event Replicator Target Adapter that is running is given in the message (*version*).

**Action**              No action is required for this informational message.

**ART0105I**      **Engine shutdown requested**

**Explanation**      A request has been made to shut down the Event Replicator Target Adapter.

**Action**              No action is required for this informational message.

**ART0106I**      **Main processing loop shutdown requested**

**Explanation**      A request has been made to shut down the main processing loop of the Event Replicator Target Adapter.

**Action**              No action is required for this informational message.

**ART0107I**      **Operation message: *input-msg***

**Explanation**      An operation message (*input-msg*) is listed in the text of this message.

**Action**              No action is required for this informational message.

**ART0108E Invalid or unprocessed message received: *msg***

**Explanation** An invalid or unprocessed message was received. The invalid message (*msg*) is provided in the text of this message.

**Action** Review any previous messages to determine the primary cause of the problem. If the problem persists, contact your Software AG technical support representative for assistance.

**ART0109E Cannot connect to target**

**Explanation** An attempt to connect to a defined target failed.

**Action** Evaluate the target definition to determine the cause of the problem. If you cannot determine the cause of the problem, contact your Software AG technical support representative for assistance.

**ART0110E Operation status: *status***

**Explanation** The status of the failed operation (*status*) is provided in the text of this message. This message accompanies other error messages. Possible statuses are "Failed" and "FailedRetry".

**Action** Review the other messages that accompany this one to determine the cause of the problem. If you cannot determine the cause of the problem, contact your Software AG technical support representative for assistance.

**ART0111E Incorrect message: *msg***

**Explanation** The message in error (*msg*) is provided in the text of this message, which accompanies other error messages.

**Action** Review the other messages that accompany this one to determine the cause of the problem. If you cannot determine the cause of the problem, contact your Software AG technical support representative for assistance.

**ART0112I Database retry count is 0**

**Explanation** The database retry count setting has reached the value of zero (0). No further database retries are attempted and the source is closed.

**Action** Restart the database and reopen the source.

**ART0113I**     **Waiting *secs* seconds before database retry *number* of *total***

**Explanation**     The Event Replicator Target Adapter is waiting the number of seconds listed in the message (*secs*) before attempting to reconnect to the source database. The retry attempt number (*number*) and the total number of retry attempts defined for the source (*total*) are also given in the message.

**Action**             No action is required for this informational message.

**ART0114I**     **Attempting database retry *number* of *total***

**Explanation**     The Event Replicator Target Adapter is attempting to reconnect to a source database. The retry attempt number (*number*) and the total number of retry attempts defined for the source (*total*) are given in the message.

**Action**             No action is required for this informational message.

**ART0115E**     **XSLT or XML document is null**

**Explanation**     The style sheet (XSLT) or XML document to be used in Event Replicator Target Adapter processing is null or cannot be found. This is an internal error.

**Action**             Contact your Software AG technical support representative for assistance.

**ART0116I**     **Committing invalid or unprocessed message**

**Explanation**     The invalid message was committed because the **Commit Unprocessed Message** option was set to true. Processing continues.

**Action**             No action is required for this informational message.

**ART0117I**     **IVP message received and processed**

**Explanation**     The installation verification procedure (IVP) message was received and processed successfully.

**Action**             No action is required for this informational message.

**ART0118I**             **Received *count* request**

**Explanation**             The number of requests received is listed in the message (*count*).

**Action**             No action is required for this informational message.

**ART0119E**      **Received unknown message *msg*****Explanation**      An unknown message was received.**Action**              Contact your Software AG technical support representative for assistance.**ART0120E**      **Cannot convert input message from *source* code page *num1* to *num2*****Explanation**      The input message listed in the message text could not be converted from one code page (*num1*) to another (*num2*).**Action**              Contact your Software AG technical support representative for assistance.**ART0121E**      **Current messages****Explanation**      This message accompanies message ARTO108E.**Action**              Review all the messages to determine the cause of the problem. If the problem persists, contact your Software AG technical support representative for assistance.**ART0122I**      **Problems writing file; directory must exist: *dirname*****Explanation**      A file could not be written because the directory listed in the message did not exist.**Action**              Create the directory and restart the Event Replicator Target Adapter.**ART0123E**      **Unprocessed data *count* bytes in buffer *buf*****Explanation**      An internal error has occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART0124I**      **Successful database reconnect for *target* target****Explanation**      An attempt to reconnect to the database target was successful.**Action**              No action required for this informational message**ART0125I**      **Software AG License check *license*****Explanation**      A Software AG license check occurred for the license shown in the message.**Action**              No action required for this informational message

**ART0303I Initial-state process started for: *isname***

**Explanation** The Event Replicator Target Adapter has started processing an initial-state request. The name of the initial-state definition (*isname*) is listed in the message.

**Action** No action is required for this informational message.

**ART0304I Initial-state process completed for: *isname***

**Explanation** The Event Replicator Target Adapter has completed processing an initial-state request. The name of the initial-state definition (*isname*) is listed in the message.

**Action** No action is required for this informational message.

**ART0305I Initial-state erroneous request rejected**

**Explanation** An invalid initial-state request was rejected. It was not processed.

**Action** No action is required for this informational message. However, you might want to review the invalid initial-state request to determine why it was not processed.

**ART0307I Normal Event Replicator Server session started message received from: *reptor-id***

**Explanation** A normal Event Replicator Server session has started and a message has been received from it. The Event Replicator Server ID is listed in the message (*reptor-id*).

**Action** No action is required for this informational message.

**ART0308I Event Replicator Server restart after abnormal end**

**Explanation** The Event Replicator Server has restarted after it ended abnormally.

**Action** No action is required for this informational message although you might want to review the error messages provided by the Event Replicator Server to determine why it ended abnormally.

**ART0309I Normal Event Replicator Server session termination message received from: *reptor-id***

**Explanation** A normal Event Replicator Server session has terminated. The Event Replicator Server ID is listed in the message (*reptor-id*).

**Action** No action is required for this informational message.

**ART0310I          Replication deactivated****Explanation**          Replication has been deactivated (stopped).**Action**                  No action is required for this informational message.**ART0311I          Replication reactivated****Explanation**          Replication has been reactivated (started).**Action**                  No action is required for this informational message.**ART0314I          Replay process (ADARPL) started****Explanation**          The ADARPL utility has started to resend replicated data from the database protection log (PLOG) to the target RDBMS. For more information, read about the ADARPL utility in your Event Replicator for Adabas documentation.**Action**                  No action is required for this informational message.**ART0315I          Replay process (ADARPL) ended****Explanation**          The ADARPL utility has completed resending replicated data from the database protection log (PLOG) to the target RDBMS. For more information, read about the ADARPL utility in your Event Replicator for Adabas documentation.**Action**                  No action is required for this informational message.**ART0316I          Event Replicator Server replication definitions refreshed****Explanation**          The Event Replicator Server replication definitions have been refreshed via an RPLREFRESH command.**Action**                  No action is required for this informational message.**ART0317I          ADALOD UPDATE started****Explanation**          A run of the ADALOD UPDATE utility function has started.**Action**                  No action is required for this informational message.

**ART0318I      ADALOD UPDATE ended**

**Explanation**      A run of the ADALOD UPDATE utility function has ended.

**Action**              No action is required for this informational message.

**ART0319I      ADALOD LOAD ended. Source: *src* Target: *target***

**Explanation**      A run of the ADALOD LOAD utility function has ended.

**Action**              No action is required for this informational message.

**ART0320E      Unknown status message *message***

**Explanation**      An unknown status message was encountered during Event Replicator Target Adapter processing. The status message is given in the message text.

**Action**              Contact your Software AG technical support representative for assistance.

**ART0321E      Unknown URBS operation *operation***

**Explanation**      An unknown URBS operation was attempted. The type of operation attempted is listed in the message text.

**Action**              Contact your Software AG technical support representative for assistance.

**ART0322E      Invalid DBID *dbid* or file number *fn***

**Explanation**      An invalid database ID or file number was encountered during processing.

**Action**              Contact your Software AG technical support representative for assistance.

**ART0323I      Receiving LODS message: Source: *src* Target: *target***

**Explanation**      An LODS message is being received. The data source and target are listed in the message.

**Action**              No action is required for this informational message.

**ART0324E      Receiving unknown message**

**Explanation**      An unknown message was received during processing.

**Action**              Contact your Software AG technical support representative for assistance.



**ART0325I      Receiving AUT1 message (Adabas utility execution)**

**Explanation**    An AUT1 message produced by the execution of an Adabas utility is being received.

**Action**            No action is required for this informational message.

**ART0401I      Testing database connections**

**Explanation**    The Event Replicator Target Adapter is testing its database connections.

**Action**            No action is required for this informational message.

**ART0402I      Database information at startup:**

**Explanation**    This message is the introductory message for a series of other informational messages about the databases to which the Event Replicator Target Adapter has connections.

**Action**            No action is required for this informational message.

**ART0403I      Connector protocol: *protocol-type* port: *port***

**Explanation**    This message lists the protocol type and port number used by the Event Replicator Target Adapter Tomcat engine.

**Action**            No action is required for this informational message.

**ART0404I      Using connector port: *conn-port* port: *port***

**Explanation**    This message lists the default HTTP port number that will be used.

**Action**            No action is required for this informational message.

**ART0405I      Adabas Replicator servlet shutdown started**

**Explanation**    The Event Replicator Server is shutting down.

**Action**            No action is required for this informational message.

**ART0406I      Adabas Replicator servlet shutdown complete**

**Explanation**    The Event Replicator Server shutdown is complete.

**Action**            No action is required for this informational message.

**ART0407I     Testing connection to database resource *id***

**Explanation**     A test is being performed that connects to the database resource listed in the message (*id*).

**Action**             No action is required for this informational message.

**ART0408I             Database testing complete**

**Explanation**             Tests on the database have completed.

**Action**                 No action is required for this informational message.

**ART0409I     JMS information at startup:**

**Explanation**     This message is the introductory message for a series of other informational messages about the JMS to which the Event Replicator Target Adapter has connections.

**Action**             No action is required for this informational message.

**ART0410I             JMS testing complete**

**Explanation**             Tests on the JMS have completed.

**Action**                 No action is required for this informational message.

**ART0501I     EntireX Broker information *info***

**Explanation**     This message displays information about a webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter.

**Action**             No action is required for this informational message.

**ART0502I     EntireX Broker source shutdown requested**

**Explanation**     A request is being processed to close a webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter.

**Action**             No action is required for this informational message.

**ART0503I**    **EntireX Broker source shutdown requested; processing: *state* userstop: *xxxx***

**Explanation**    A webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter is being closed. The current state of the source is displayed in the message.

**Action**    No action is required for this informational message.

**ART0504I**    **EntireX Broker source close complete**

**Explanation**    A webMethods EntireX source used to convey replicated Adabas data to the Event Replicator Target Adapter has been closed.

**Action**    No action is required for this informational message.

**ART0505I**    **EntireX Broker UOW rolled back ID: *id***

**Explanation**    The webMethods EntireX unit of work ID was rolled back. This is an internal process.

**Action**    No action is required for this informational message.

**ART0506I**    **EntireX Broker prefetch size reached: *size***

**Explanation**    The defined prefetch size for the webMethods EntireX source has been reached. The defined prefetch size is given in the message (*size*).

**Action**    No action is required for this informational message. However, you might consider increasing the defined prefetch size. Note that increasing the prefetch size will increase the memory requirements.

**ART0507E**    **EntireX Broker send error class: *class* code: *code* message: *msg***

**Explanation**    An error has occurred during an attempt to send data to a webMethods EntireX source. The error class (*class*), message code (*code*) and message text (*msg*) are given in the message.

**Action**    Refer to your webMethods EntireX documentation for additional information.

**ART0508E**    **EntireX Broker error class: *class* code: *code* message: *msg***

**Explanation**    An error has occurred during an attempt to use a webMethods EntireX source. The error class (*class*), message code (*code*) and message text (*msg*) are given in the message.

**Action**    Refer to your webMethods EntireX documentation for additional information.

**ART0509E EntireX Broker exception: *info***

**Explanation** An exception occurred during an attempt to use a webMethods EntireX source. The exception information (*info*) is given in the message.

**Action** Contact your Software AG technical support representative for assistance.

**ART0510E EntireX Broker receive error class: *class* code: *code* message: *msg***

**Explanation** An error has occurred during an attempt to receive data from an webMethods EntireX source. The error class (*class*), message code (*code*) and message text (*msg*) are given in the message.

**Action** Refer to your webMethods EntireX documentation for additional information.

**ART0511E EntireX Broker logon error ID: *class* service: *service* message: *msgtxt***

**Explanation** An error has occurred during an attempt to log into an webMethods EntireX source. The error class (*class*), service name (*service*), and message code (*msgtxt*) are given in the message.

**Action** Verify that the correct logon information (user ID, token, and password) is provided in the webMethods EntireX source definition. Correct it as necessary and try again.

**ART0512E EntireX Broker error on: *id* cause: *exx-cause***

**Explanation** An error occurred during an attempt to use the webMethods EntireX source whose ID is listed in the message (*id*). The cause of the error is also listed in the message (*exx-cause*).

**Action** Contact your Software AG technical support representative for assistance.

**ART0513E EntireX Broker commit error message: *err-msg***

**Explanation** An error occurred during an attempt to use a webMethods EntireX source definition. The webMethods EntireX error message (*err-msg*) is listed in the message.

**Action** Contact your Software AG technical support representative for assistance.

**ART0514E    EntireX Broker cannot open Broker trace log file: *fn***

**Explanation**    An error occurred during an attempt to open the webMethods EntireX trace log file. The file name of the log file is given in the message (*fn*).

**Action**            Verify that the correct file name is specified for the webMethods EntireX trace log file in the webMethods EntireX definitions. If it is not, correct the name and try again. If the problem persists, contact your Software AG support representative for assistance.

**ART0515I    EntireX Broker trace level: *lvl* trace file: *fn***

**Explanation**    This message identifies the trace level (*lvl*) and file name (*fn*) used by the Event Replicator Target Adapter for webMethods EntireX sources.

**Action**            No action is required for this informational message.

**ART0516I    EntireX Broker receive complete: time: *count* Ms length: *length* UowStatus: *status***

**Explanation**    A webMethods EntireX source received data from replication. The length of time (in microseconds) for the receive operation (*count*), the length of the data received (*length*), and the unit of work status of the receive operation (*status*) are given in the message. Values for the unit of work status are "First", "Middle" or "Last".

**Action**            No action is required for this informational message.

**ART0517E    EntireX Broker commit error class: *class* code: *code* uowid: *uowid* message: *msg***

**Explanation**    An error occurred during a commit attempt for the webMethods EntireX source. The error class (*class*), EntireX message code (*code*), EntireX UOWID (*uowid*) and EntireX message text (*msg*) are listed in the message.

**Action**            Contact your Software AG technical support representative for assistance.

**ART0518E    EntireX Broker rollback error class: *class* code: *code* message: *msg***

**Explanation**    An error occurred during a rollback attempt for the webMethods EntireX source. The error class (*class*), EntireX message code (*code*) and EntireX message text (*msg*) are listed in the message.

**Action**            Contact your Software AG technical support representative for assistance.

**ART0519E    EntireX Broker deregister error host: *host-id* service: *service* message: *msg***

**Explanation**    An error occurred during an attempt to deregister a webMethods EntireX source. The EntireX ID (*host-id*), service (*service*) and message text (*msg*) are listed in the message.

**Action**            Contact your Software AG technical support representative for assistance.

**ART0520E    EntireX Broker user ID required**

**Explanation**    A valid webMethods EntireX user ID is required but was not supplied.

**Action**            Supply a valid webMethods EntireX user ID and try again.

**ART0521E    EntireX Broker token required**

**Explanation**    A valid webMethods EntireX token is required but was not supplied.

**Action**            Supply a valid webMethods EntireX token and try again.

**ART0601I    Save file *fn* with data: *dddd***

**Explanation**    An attempt to save the file listed in the message (*fn*) with the data listed in the message (*dddd*) was successful.

**Action**            No action is required for this informational message.

**ART0602E    Read resource failed for: *resource-id* status code: *code***

**Explanation**    An attempt to read from the resource listed in the message (*resource-id*) failed. The status code of the attempt is given in the message (*code*).

**Action**            Contact your Software AG technical support representative for assistance.

**ART0603I    Retrying resource read for: *resource-id***

**Explanation**    An attempt is being made to read from the resource listed in the message (*resource-id*).

**Action**            No action is required for this informational message.

**ART0604E    WebDAV error: *err-code***

**Explanation**    A WebDAV error occurred during Event Replicator Target Adapter processing.

**Action**        Verify that the web service target URL is correct and try again. If the problem persists, contact your Software AG technical support representative.

**ART0605E    WebDAV repository is not accessible *err-code***

**Explanation**    The WebDAV repository cannot be accessed.

**Action**        Verify that the web service target URL is correct and try again. If the problem persists, contact your Software AG technical support representative.

**ART0606E    Invalid WebDAV cache size value *size***

**Explanation**    An invalid WebDAV cache size has been specified. The value was not numeric.

**Action**        Supply a valid numeric cache size and try again.

**ART0607E    Cannot find generic XSLT file *filename***

**Explanation**    The XSLT file listed in the message (*filename*) could not be found.

**Action**        If the problem persists, contact your Software AG technical support representative.

**ART0608E    Cannot find XSLT file *filename***

**Explanation**    The XSLT file listed in the message (*filename*) could not be found.

**Action**        If the problem persists, contact your Software AG technical support representative.

**ART0609E    Create table XML message is null or base table name is null**

**Explanation**    An internal error has occurred.

**Action**        If the problem persists, contact your Software AG technical support representative.

**ART0610E    Cannot convert create table schema to string**

**Explanation**    An internal error has occurred.

**Action**        If the problem persists, contact your Software AG technical support representative.

**ART0611E    Cannot save create table schema *name* into WebDAV**

**Explanation**    An attempt to save the schema named in the message (*name*) to the WebDAV repository failed.

**Action**         If the problem persists, contact your Software AG technical support representative.

**ART0612E    Problem with managing WebDAV file *filename***

**Explanation**    The WebDAV file named in the message (*filename*) could not be managed.

**Action**         If the problem persists, contact your Software AG technical support representative.

**ART0613I    Collection may not exist *colname***

**Explanation**    The collection named in the message (*colname*) may not exist in the WebDAV repository. The collection is created.

**Action**         No action is required for this informational message.

**ART0614I    Retrying resource write for *res***

**Explanation**    An attempt is in progress to retry the resource write for the resource named in the message (*res*).

**Action**         No action is required for this informational message.

**ART0615E    Write resource file *fn* failed *err-code***

**Explanation**    An attempt to write the resource file named in the message (*fn*) failed.

**Action**         If the problem persists, contact your Software AG technical support representative.

**ART0616E    WebDAV status code *code* status message *msg***

**Explanation**    A WebDAV internal error has occurred.

**Action**         If the problem persists, contact your Software AG technical support representative.



**ART0617E    Make collection *colname* failed status *stat***

**Explanation**    An attempt to make the collection named in the message (*colname*) failed. The status of the attempt is also given in the message (*stat*).

**Action**            If the problem persists, contact your Software AG technical support representative.

**ART0701I            Source shutdown complete**

**Explanation**            An attempt to shut down a source completed successfully.

**Action**                No action is required for this informational message.

**ART0702I    Source waiting for restart after user stop or rollback**

**Explanation**    The source is waiting to be restarted after it was manually stopped or after a rollback occurred.

**Action**            No action is required for this informational message. Restart the source when you are ready.

**ART0703I    Retries = 0; source waiting for manual restart**

**Explanation**    The value of the `Retry Count` parameter in the source definition has been reached. The source is waiting for a manual restart.

**Action**            No action is required for this informational message. Manually restart the source when you are ready.

**ART0704I    Wait for retry; count: *count***

**Explanation**    The source is waiting between retry attempts. The retry attempt count is given in the message (*count*).

**Action**            No action is required for this informational message.

**ART0705E    No commit/rollback listener**

**Explanation**            An internal error has occurred.

**Action**                Contact your Software AG technical support representative for assistance.

**ART0706E      Source message is null on commit****Explanation**      An internal error has occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART0707E      Unsupported source type *type*****Explanation**      An internal error has occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART0708E      Cannot open source capture file *fn*****Explanation**      The file cannot be opened. Verify that the directory name exists.**Action**              If the problem persists, contact your Software AG technical support representative.**ART0801I      Runtime metrics****Explanation**      This message is the heading message for a series of runtime metric messages.**Action**              No action is required for this informational message.**ART0802I      Resource key: *rkey*****Explanation**      A resource key is listed in the message (*rkey*).**Action**              No action is required for this informational message.**ART0803I      Metrics key: *mkey*****Explanation**      A metrics key is listed in the message (*mkey*).**Action**              No action is required for this informational message.**ART0901E      Process request failed****Explanation**      An Event Replicator Target Adapter process request failed. The source is shut down.**Action**              Review any accompanying error messages to determine the cause of the problem. If the problem persists, contact your Software AG technical support representative.

**ART0902I Database active result: *result***

**Explanation** The result of a test to see whether the database is active or not is listed in the message (*result*).

**Action** No action is required for this informational message.

**ART0903I Retrying Database Transaction**

**Explanation** An attempt is in progress to retry the database transaction.

**Action** No action is required for this informational message.

**ART1001E Exception cause: *cause***

**Explanation** An Event Replicator Target Adapter process request failed. The cause of the failure is given in the message (*cause*).

**Action** Contact your Software AG technical support representative for assistance.

**ART1002E Exception stack: *stack***

**Explanation** An Event Replicator Target Adapter process request failed. The exception stack for the failure is given in the message (*stack*).

**Action** Contact your Software AG technical support representative for assistance.

**ART1005W Unable to transform document**

**Explanation** The Event Replicator Target Adapter was unable to transform a document.

**Action** No action is required for this warning message. Determine the reason for which the Event Replicator Target Adapter cannot transform the document and alter the conditions as necessary. Then try again.

**ART1101I File source configured for input directory: *dirname***

**Explanation** A file source definition has been configured for the input directory listed in the message (*dirname*).

**Action** No action is required for this informational message.

**ART1102I     File source ready to receive data from: *dirname***

**Explanation**    A file source definition is ready to receive data from the directory listed in the message (*dirname*).

**Action**            No action is required for this informational message.

**ART1103E     File source unable to get list of files**

**Explanation**    A file source could not get a list of the files from the source.

**Action**            Determine why a list of files could not be obtained. Resolve the error and try again. If the problem persists, contact your Software AG support representative for assistance.

**ART1104I             File source closing**

**Explanation**    A file source is closing.

**Action**            No action is required for this informational message.

**ART1105I     File source returning file: FILE: *dirname-->fn***

**Explanation**    The file source definition is returning the file source as part of the file source shutdown execution. The directory (*dirname*) and filename(*fn*) are given in the message.

**Action**            No action is required for this informational message.

**ART1106I             File source shutdown requested**

**Explanation**    Shutdown of a file source was requested.

**Action**            No action is required for this informational message.

**ART1107I             File source rollback called**

**Explanation**    Rollback of the updates from a file source was called.

**Action**            No action is required for this informational message.

**ART1108E**    **File source file does not exist *fn***

**Explanation**    The file source file named in the message (*fn*) does not exist. This is an internal message.

**Action**            Contact your Software AG technical support representative for assistance.

**ART1109I**    **File source processing time for: *dirname-->fn* is *num* Milliseconds**

**Explanation**    The processing time is given in the message for the file identified in the message.

**Action**            No action is required for this informational message.

**ART1201I**            **Rollback following SQL commands**

**Explanation**            A rollback occurred based on SQL commands.

**Action**            No action is required for this informational message.

**ART1203W**    **File name not provided for operation: *op* FNR: *fnum* ISN: *isnum***

**Explanation**    A file name was not provided for the operation listed in the message (*op*). The file (*fnum*) and ISN (*isnum*) numbers are also listed in the message.

**Action**            No action is required for this informational message.

**ART1204E**    **Test connection failed: *conn-name***

**Explanation**    A test connection to the connection listed in the message (*conn-name*) failed.

**Action**            Restart the database if it is down.

**ART1205E**    **Cannot get a connection from the data source**

**Explanation**    An attempt to connect to a data source failed.

**Action**            Review the data source definition and try again. If the problem persists, contact your Software AG technical support representative for assistance.

**ART1206E    Cannot get metadata**

**Explanation**    An attempt to connect to a data source failed.

**Action**            Review the data source definition and try again. If the problem persists, contact your Software AG technical support representative for assistance.

**ART1207E    Exception obtaining table metadata: *tablename***

**Explanation**    An exception occurred while the Event Replicator Target Adapter was attempting to obtain metadata from a table. The name of the table is given in the message (*tblname*).

**Action**            Contact your Software AG technical support representative for assistance.

**ART1208I    Process is continuing after the previous error**

**Explanation**    Event Replicator Target Adapter processing is continuing in spite of a previously reported error condition.

**Action**            No action is required for this informational message.

**ART1209I    Unable to locate table: *tablename***

**Explanation**    The Event Replicator Target Adapter could not locate the table listed in the message (*tablename*).

**Action**            No action is required for this informational message. If you really do need the Event Replicator Target Adapter to locate this table, determine why it cannot be located and try again. If the problem persists, contact your Software AG technical support representative.

**ART1210I    Create index command built: *cmd***

**Explanation**    An internal command to create the index to a table was successfully built.

**Action**            No action is required for this informational message.

**ART1211E    Cannot get connection to data source *name***

**Explanation**    An attempt to connect to the data source named in the message (*name*) failed.

**Action**            Verify that the database definitions are correct and that the database is active.

**ART1212E      Cannot retrieve database metadata****Explanation**      An attempt to retrieve metadata for the database failed.**Action**              Contact your Software AG technical support representative for assistance.**ART1213E      Internal error of Sybase ASE****Explanation**      An internal error occurred in Sybase ASE**Action**              Contact your Software AG technical support representative for assistance.**ART1214W      Unknown data type *type* for column *colname* in metadata****Explanation**      An attempt was made to specify the unknown data type listed in the message (*type*) in the column listed in the message (*colname*).**Action**              Contact your Software AG technical support representative for assistance.**ART1215E      pkTableName *pkname* does not match with table name *tblname*****Explanation**      A mismatch has occurred between the table and the primary key. The table name (*tblname*) and the primary key (*pkname*) are given in the message.**Action**              Contact your Software AG technical support representative for assistance.**ART1216E      Cannot find previous column information****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1217F      Initial context is null****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1218F      Context lookup is null****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.

**ART1219E    Unsupported driver class name for JDBC/database *dbname***

**Explanation**    An unsupported driver class name was specified for the JDBC database listed in the message (*dbname*).

**Action**            Contact your Software AG technical support representative for assistance.

**ART1220E    Error obtaining connection *err-code***

**Explanation**    A connection to the database could not be made.

**Action**            Verify that the database definitions are correct and that the database is active.

**ART1221E    Table *tblname* has duplicate column name *colname***

**Explanation**    The table named in the message (*tblname*) has two columns with the same name (*colname*).

**Action**            Change one of the column names and try again.

**ART1222E    Cannot create statement**

**Explanation**    An internal error occurred.

**Action**            Contact your Software AG technical support representative for assistance.

**ART1223E    Cannot connect to database *dbname***

**Explanation**    An attempt to connect to the database named in the message (*dbname*) failed.

**Action**            Verify that the database definitions are correct and that the database is active.

**ART1224E    Cannot execute batch**

**Explanation**    An internal error occurred.

**Action**            Contact your Software AG technical support representative for assistance.

**ART1225E    Cannot turn off database autocommit**

**Explanation**    An attempt to turn off the autocommit feature of the database failed.

**Action**            Contact your Software AG technical support representative for assistance.



**ART1226E      Cannot create executing SQL statement****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1227E      Process continuing because dbErrorContinue is TRUE****Explanation**      The target database **Error Continue** option was set to "true" (selected or turned on), so the SQL error is ignored and processing continues.**Action**              No action is required for this message.**ART1228E      Executing....<processing information>****Explanation**      An SQL command either failed or executed successfully. The SQL command and details about its processing are given in the message (<processing information>).

If an error occurred, and you have not selected the **Error Continue** option for the target database, the Event Replicator Target Adapter will stop running. For more information, read *Specifying Target Database Processing Option Definitions*.

**Action**              If the command failed, resolve the error described in the message. If necessary, contact your Software AG technical support representative for assistance.**ART1229E      Unable to load/construct DB support class for classname****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1230E      Update to insert mode is on but full image value is missing****Explanation**      An attempt to insert an update failed because the full image of the record is missing from the database.**Action**              Use Option=32 in the Event Replicator Server destination definition. For more information, refer to your Event Replicator for Adabas destination documentation.**ART1232E      Cannot insert column****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.

**ART1233I SQL command failed *cmd***

**Explanation** The SQL command listed in the message (*cmd*) failed.

**Action** Review other accompanying error messages to determine the cause of the problem. If the problem persists, contact your Software AG technical support representative for assistance.

**ART1234I SQL command reason *rsncode***

**Explanation** The previous SQL command failed with the reason code (*rsncode*) given in the message.

**Action** Review the documentation for your RDBMS to determine the cause of the problem.

**ART1235W Sync DDL value *val* is not one of the following values, ignore, warn, apply, error. Reset to ignore.**

**Explanation** The value for the **Adabas-RDBMS Synchronization Level** option is invalid. It has been reset to "ignore".

**Action** In the target database options, change the setting of the **Adabas-RDBMS Synchronization Level** option to something other than "ignore" if you want.

**ART1236E Cannot alter column *detailed-info***

**Explanation** The Event Replicator Target Adapter could not alter the column described by the detailed information listed in the message (*detailed-info*) during its attempt to synchronize the RDBMS table with the Adabas file.

**Action** Make sure the target database supports this kind of type conversion and that this column is not a primary key and doesn't have foreign key. If the problem persists, contact your Software AG technical support representative for assistance.

**ART1237W Data type or length mismatch on column *detailed-info***

**Explanation** During an attempt to synchronize the RDBMS table with the Adabas file, the Event Replicator Target Adapter determined that a data type or length mismatch had occurred for the column described by the detailed information listed in the message (*detailed-info*).

**Action** Issue the same message as the previous one. The Event Replicator Target Adapter will continue to run because the **Adabas-RDBMS Synchronization Level** value is set to "warn". If the problem persists, contact your Software AG technical support representative for assistance.

**ART1238I**    **Alter column *detailed-info***

**Explanation**    The column described by the detailed information listed in the message (*detailed-info*) was altered in the RDBMS during Event Replicator Target Adapter synchronization between the RDBMS table and the Adabas file.

**Action**         No action is required for this informational message.

**ART1239I**    **Add column *detailed-info***

**Explanation**    The column described by the detailed information listed in the message (*detailed-info*) was added to the RDBMS during Event Replicator Target Adapter synchronization between the RDBMS table and the Adabas file.

**Action**         No action is required for this informational message.

**ART1240E**    **Cannot add column *detailed-info***

**Explanation**    The Event Replicator Target Adapter could not add the column described by the detailed information listed in the message (*detailed-info*) to the RDBMS during its attempt to synchronize the RDBMS table with the Adabas file.

**Action**         Make sure the target database supports adding columns. If the problem persists, contact your Software AG technical support representative for assistance.

**ART1241W**    **Target database doesn't have column *detailed-info***

**Explanation**    During an attempt to synchronize the RDBMS table with the Adabas file, the Event Replicator Target Adapter determined that the target RDBMS is missing the column described by the detailed information listed in the message (*detailed-info*).

This message is issued because the **Adabas-RDBMS Synchronization Level** value is set to "warn". In this case, the Event Replicator Target Adapter issues this warning message and continues processing.

**Action**         No action is required for this warning message.

**ART1242E**    **Cannot find *\_INDEX* as suffix of the PE table *tablename* primary key *key***

**Explanation**    An internal error occurred.

**Action**         Contact your Software AG technical support representative for assistance.

**ART1302I Loader complete for loader**

**Explanation** The Event Replicator Target Adapter completed loading replicated data for the Oracle SQL Loader listed in the message without failing.

**Action** No action is required for this informational message.

**ART1303E Loader fail. Please check the log files *fn***

**Explanation** An attempt to load replicated data to the database via the Oracle SQL loader failed. The log files (*fn*) that contain more information are listed in the message.

**Action** Review the log files for more information about the failure. If possible, correct the error and try again. If the problem persists, contact your Software AG technical support representative for assistance.

**ART1304E Loader exception**

**Explanation** An exception occurred during the loading process.

**Action** Contact your Software AG technical support representative for assistance.

**ART1305E Create table XML file *fn* does not exist**

**Explanation** A request to create the table in an XML file failed because the XML file could not be found. The filename of the XML file is given in the message (*fn*).

**Action** Contact your Software AG technical support representative for assistance.

**ART1307E Control file *fn* is not generated**

**Explanation** The control file listed in the message (*fn*) was not generated.

**Action** Contact your Software AG technical support representative for assistance.

**ART1308E Loader cannot support streaming mode**

**Explanation** The loader cannot support streaming mode.

**Action** Modify the target database options used by the database so that the **Use Stream** option is not selected (checked) and try again. For more information, read *Specifying Target Database Processing Option Definitions*.

**ART1309E      Output file *fn* is not generated**

**Explanation**      The output file named in the message (*fn*) was not generated.

**Action**              Contact your Software AG technical support representative for assistance.

**ART1310I      Current configuration cannot support streaming mode; change to nonstreaming mode**

**Explanation**      The current configuration does not support streaming mode. The Event Replicator Target Adapter turns stream mode off and retries the operation.

**Action**              No action is required for this informational message.

**ART1311I      Current configuration cannot support loader mode; change to nonloader mode**

**Explanation**      The current configuration does not support the database in loader mode.

**Action**              No action is required for this informational message.

**ART1312I      Loader process running for *loader***

**Explanation**      The database loader process is running for the Oracle SQL Loader listed in the message.

**Action**              No action is required for this informational message.

**ART1313I      Loader about to execute following command: *cmd***

**Explanation**      The database loader process is executing the command listed in the message (*cmd*).

**Action**              No action is required for this informational message.

**ART1315I      Create loader thread**

**Explanation**      An attempt by the Event Replicator Target Adapter to create a loader thread is in process.

**Action**              No action is required for this informational message.

**ART1316E**      **Called with table: *tblname* column: *colname***

**Explanation**      An error occurred trying to call the table (*tblname*) and column (*colname*) whose names are listed in the message.

**Action**              Contact your Software AG technical support representative for assistance.

**ART1318I**              **Initial-state running in loader mode**

**Explanation**              The initial-state process is running in loader mode.

**Action**                  No action is required for this informational message.

**ART1319E**              **Cannot wait for loader process**

**Explanation**              An internal error occurred.

**Action**                  Contact your Software AG technical support representative for assistance.

**ART1320E**              **Cannot find control file name**

**Explanation**              An internal error occurred.

**Action**                  Contact your Software AG technical support representative for assistance.

**ART1321E**              **Cannot find log file name**

**Explanation**              An internal error occurred.

**Action**                  Contact your Software AG technical support representative for assistance.

**ART1322E**              **Cannot find bad file name**

**Explanation**              An internal error occurred.

**Action**                  Contact your Software AG technical support representative for assistance.

**ART1323E**              **Cannot find discard file name**

**Explanation**              An internal error occurred.

**Action**                  Contact your Software AG technical support representative for assistance.

**ART1324E      Cannot find out file name****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1325E      Create loader process failed****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1326I      Test loader process successful****Explanation**      The test loader process completed successfully.**Action**              No action is required for this informational message.**ART1327E      Test loader process failed, exit code *code*****Explanation**      The test loader process failed with the exit code listed in the message (*code*).**Action**              Contact your Software AG technical support representative for assistance.**ART1328E      Cannot create XsltWorker****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1329E      Cannot set up environment variables of file *fn*****Explanation**      An attempt to set the environment variables for the file named in the message (*fn*) failed.**Action**              Contact your Software AG technical support representative for assistance.**ART1330E      Cannot support current database type****Explanation**      Support is not provided for the database type.**Action**              Change the database type to one that is supported by the Event Replicator Target Adapter. If necessary, contact your Software AG technical support representative for assistance.

**ART1331E      Worker is null****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1332E      Cannot create loader thread****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1333E      Cannot create piped stream****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1334E      Loader failed. Current mode is streaming mode, change to nonstreaming mode and retry****Explanation**      The loader failed.**Action**              Modify the target database options used by the database so that the **Use Stream** option is not selected (checked) and try again. For more information, read *Specifying Target Database Processing Option Definitions***ART1335E      Cannot write to output stream****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1336E      Parsing error *err* line *lll* column *ccc* PID *pid* CID *cid*****Explanation**      A parsing error occurred. The error, line number, column number, process ID, and command ID are given in the message.**Action**              Contact your Software AG technical support representative for assistance.



**ART1337E      Unable to send message to the loader****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1338E      Cannot find base file name****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1339W      Current database cannot support streaming mode, reset to nonstreaming mode****Explanation**      The current database does not support streaming mode. The Event Replicator Target Adapter has turned streaming mode off.**Action**              No action is required for this warning message.**ART1340E      The child thread may end unexpectedly****Explanation**      An internal error occurred.**Action**              Contact your Software AG technical support representative for assistance.**ART1341E      Cannot find WebDAV****Explanation**      The WebDAV file cannot be found.**Action**              Contact your Software AG technical support representative for assistance.**ART1342E      Batch file *fn* does not exist****Explanation**      The batch file named in the message does not exist.**Action**              Contact your Software AG technical support representative for assistance.

**ART1343W**    **The service name of the loader in the Target Database Options of a Teradata MLoad, *name*, has more than *num* characters. Using *xxxx* as the *tdpid* for this MLoad**

**Explanation**    The service name of the loader during Teradata MLoad processing is too long. The Event Replicator Target Adapter is using the name *xxxx* for the *tdpid* of the MLoad processing.

**Action**    No action is required for this warning message.

**ART1344W**    **The service name of the loader in the Target Database Options of a Teradata MLoad has not been informed. Attempting to use *xxxx* as the *tdpid* for ths MLoad**

**Explanation**    The service name of the loader during Teradata MLoad processing has not been provided. The Event Replicator Target Adapter is trying to use the name *xxxx* for the *tdpid* of the MLoad processing.

**Action**    No action is required for this warning message.

**ART1401I**    **Transform document using XSLT file: *fn* token: *token***

**Explanation**    The Event Replicator Target Adapter is attempting to transform the document using the XSLT file (*fn*) and token (*token*) listed in the message.

**Action**    No action is required for this informational message.

**ART1402E**    **Cannot convert from UTF8 byte array to a string**

**Explanation**    An internal error occurred.

**Action**    Contact your Software AG technical support representative for assistance.

**ART1501I**    **Source manager shutdown requested**

**Explanation**    A request was made to shut down the source manager.

**Action**    No action is required for this informational message.

**ART1502I**    **Source manager notified to shut down**

**Explanation**    The source manager has been notified to shut down.

**Action**    No action is required for this informational message.

**ART1503I      Waiting for source manager shutdown to complete**

**Explanation**    The Event Replicator Target Adapter is waiting for the source manager to fully shut down.

**Action**            No action is required for this informational message.

**ART1504I              Source manager is down**

**Explanation**            The source manager shutdown has completed.

**Action**                No action is required for this informational message.

**ART1601I              Engine manager shutdown requested**

**Explanation**            A request was made to shut down the engine manager.

**Action**                No action is required for this informational message.

**ART1602I              Engine manager notified to shut down**

**Explanation**            The engine manager has been notified to shut down.

**Action**                No action is required for this informational message.

**ART1603I      Waiting for engine manager shutdown to complete**

**Explanation**    The Event Replicator Target Adapter is waiting for the engine manager to fully shut down.

**Action**            No action is required for this informational message.

**ART1604I              Engine manager is down**

**Explanation**            The engine manager shutdown has completed.

**Action**                No action is required for this informational message.

**ART1701W      Parameter *parm* value *val* not numeric**

**Explanation**    The parameter named in the message (*parm*) specifies a value (*val*) that is not numeric.

**Action**            Supply a numeric value for the parameter and try again.

**ART1702W** Parameter *parm* value *val* does not end with "S"

**Explanation** The parameter named in the message (*parm*) specifies a value (*val*) that does not end in an "S".

**Action** Supply a value for the parameter that ends in an "S" and try again.

**ART1703W** Parameter *parm* value *val* is not "true" or "false"

**Explanation** The parameter named in the message (*parm*) specifies a value (*val*) that is not "true" or "false."

**Action** Supply a "true" or "false" value for the parameter and try again.

**ART1801E** Cannot open WebSphere MQ trace log file *fn*

**Explanation** An attempt to open the WebSphere MQ trace file named in the message (*fn*) failed.

**Action** Check your definition. Verify that the directory defined in your definitions exists.

**ART1802E** WebSphere MQ rollback failed *err-code*

**Explanation** A rollback attempt for WebSphere MQ failed.

**Action** Review the webSphere MQ documentation to determine the reason for the failure.

**ART1803E** WebSphere MQ logon failed host *hostid* port *portnum* error *err*

**Explanation** An attempt to logon to WebSphere MQ failed. The WebSphere MQ host ID (*hostid*), port number (*portnum*), and the error number (*err*) from the attempt are given in the message.

**Action** Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

**ART1804I** WebSphere MQ logon to host *hostid* successful

**Explanation** The attempt to log onto the WebSphere MQ host named in the message (*hostid*) was successful.

**Action** No action is required for this informational message.

**ART1805I    WebSphere MQ receiving messages from queue *qname***

**Explanation**    WebSphere MQ is receiving and processing messages from the queue listed in the message (*qname*).

**Action**            No action is required for this informational message.

**ART1806E    WebSphere MQ request failed**

**Explanation**    A WebSphere MQ request failed.

**Action**            Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

**ART1807E    WebSphere MQ receive failed *err-code***

**Explanation**    A receive request via the WebSphere MQ queue failed.

**Action**            Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

**ART1808E    WebSphere MQ commit failed *err-code***

**Explanation**    A commit request via the WebSphere MQ queue failed.

**Action**            Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

**ART1809E    WebSphere MQ send failed *err-code***

**Explanation**    A send request via the WebSphere MQ queue failed.

**Action**            Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

**ART1810E    WebSphere MQ close failed *err-code***

**Explanation**    A close request via the WebSphere MQ queue failed.

**Action**            Check with your WebSphere MQ administrator to determine why the attempt failed. Resolve the problem and try again.

**ART2001E Required target configuration not found *config* or default****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART2002E Operation is null****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART2003E Operation *opname* is not supported****Explanation** An attempt to run the operation named in the message (*opname*) failed because it is not supported.**Action** Try an operation that is supported.**ART2004E Not SOAP element****Explanation** An internal error occurred.**Action** Contact your Software AG technical support representative for assistance.**ART3001E Wrong factory type for *msgtype*. Type is *factype*.****Explanation** An attempt to use the wrong JMS factory type for the type of messaging specified. The message type (*msgtype*) and factory type (*factype*) are given in the message. Replicate the data to a JMS topic if you want to use publish-subscribe messaging; replicate the data to a JMS queue if you want to use point-to-point messaging.**Action** Verify the JMS target definition is specified correctly in the Event Replicator Target Adapter Administration tool. Contact your Software AG technical support representative for assistance.**ART3002E Factory *factory* not found in the naming system.****Explanation** An attempt to access the JMS topic or queue connection factory in the system was not successful.**Action** Verify the JMS target definition is specified correctly in the Event Replicator Target Adapter Administration tool. Contact your Software AG technical support representative for assistance.

**ART3003E**    **Error occurred while accessing factory *factory* in the naming system *system*.**

**Explanation**    An error occurred attempting to access the JMS topic or queue connection factory named in the message in the system named in the message.

**Action**    Verify the JMS target definition is specified correctly in the Event Replicator Target Adapter Administration tool. Contact your Software AG technical support representative for assistance.

**ART3004E**    **Wrong destination type for *jmsname*. Type is *factype*.**

**Explanation**    An attempt to use the wrong type of destination was made when replicating data to JMS queues or topics. The JMS destination topic or queue name (*jmsname*) and the factory type (*factype*) are given in the message. Specify the destination as a JMS topic (as defined to webMethods Broker) if you want to use publish-subscribe messaging; specify the destination as a JMS queue (as defined to webMethods Broker) if you want to use point-to-point messaging.

**Action**    Verify the JMS target definition is specified correctly in the Event Replicator Target Adapter Administration tool. Contact your Software AG technical support representative for assistance.

**ART3005E**    **Destination *dest* not found in the JNDI provider**

**Explanation**    An internal error occurred. The destination specified in the JMS target definition was not found in the JNDI provider specified in the JMS target definition. The destination name is given in the message.

**Action**    Verify the JMS target definition is specified correctly in the Event Replicator Target Adapter Administration tool. Contact your Software AG technical support representative for assistance.

**ART3006E**    **Error while accessing destination *dest***

**Explanation**    An internal error occurred. An error occurred during an attempt to access the destination specified in the JMS target definition.

**Action**    Verify the JMS target definition is specified correctly in the Event Replicator Target Adapter Administration tool. Contact your Software AG technical support representative for assistance.