

# Natural System Error Messages 5801-5850

## NAT5801: Job not found.

Text	ESY5801 Job not found.
Expl.	The requested job was not found.
Actn.	No action is required.

## NAT5802: GETMAIN for CSA area failed.

Text	ESY5802 GETMAIN for CSA area failed.
Expl.	An attempt was made to access main storage, and GETMAIN for the CSA area failed.
Actn.	Notify the system programmer.

## NAT5803: Cannot access data.

Text	ESY5803 Cannot access data.
Expl.	An attempt was made to access main storage, and the data specified cannot be accessed.
Actn.	No action is required.

## NAT5804: Request to access data has timed out.

Text	ESY5804 Request to access data has timed out.
Expl.	Main storage was accessed, and SRB was scheduled to run in an address space. SRB must be completed within 10 seconds.
Actn.	No action is required.

## NAT5805: Invalid TCB address.

Text	ESY5805 Invalid TCB address.
Expl.	An invalid TCB-ADDRESS was specified.
Actn.	Specify valid TCB-ADDRESS.

## NAT5806: Permanent I/O error on catalog.

Text	ESY5806 Permanent I/O error on catalog.
Expl.	A permanent I/O error occurred while accessing the catalog.
Actn.	This may be a hardware error. Contact data center personell.

**NAT5807: Invalid track address.**

Text	ESY5807 Invalid track address.
Expl.	An invalid track address was specified.
Actn.	Specify valid track address.

**NAT5809: Subsystem not active.**

Text	ESY5809 Subsystem not active.
Expl.	The related subsystem has not been started properly. Therefore, the requested function is not available in this run of ESY. Following views return this error code on BS2000/OSD: - views SPOOL-QUEUE, SPOOL-FILES, WRITE-SPOOL if SPOOL=NONE is defined; - views SEND-MESSAGE, CONSOLE if CONSOLE task is not running; - views CONSOLE, EVENTING if EVENTING task is not running.
Actn.	Contact your administrator to get the subsystem started for the next ESY run.

**NAT5810: Error detected in catalog, processing terminated.**

Text	ESY5810 Error detected in catalog, processing terminated.
Expl.	An error in the catalog structure was detected.
Actn.	Notify the system programmer.

**NAT5811: Specified level is an empty index.**

Text	ESY5811 Specified level is an empty index.
Expl.	The level specified is an empty index.
Actn.	No action is required.

**NAT5820: Unknown command.**

Text	ESY5820 Unknown command.
Expl.	A command which is not known to NATURAL PROCESS was entered.
Actn.	Check spelling, syntax of command. Check to see whether command is a NATURAL command.

**NAT5821: Job no longer active.**

Text	ESY5821 Job no longer active.
Expl.	An attempt was made to access a job which is no longer active.
Actn.	No action required.

**NAT5822: Logical error on JES3 spool.**

Text	ESY5822 Logical error on JES3 spool.
Expl.	A logical error occurred while reading the JES3 spool data set.
Actn.	Try again. If error persists, it may indicate a bad control block on the JES3 spool (which may be caused by a hardware error).

**NAT5823: Requested job in input queue.**

Text	ESY5823 Requested job in input queue.
Expl.	An attempt was made to access output data of a job which is in the input queue.
Actn.	Wait until job is processed.

**NAT5824: I/O error on JES3 spool.**

Text	ESY5824 I/O error on JES3 spool.
Expl.	A READ operation to JES3 spool failed to complete normally.
Actn.	Probably a hardware failure. A JES3 warmstart (with analysis) should be considered.

**NAT5825: JES3 command data set is full.**

Text	ESY5825 JES3 command data set is full.
Expl.	A WRITE operation to the JES3 command data set failed because the data set is full.
Actn.	Wait until space becomes available.

**NAT5826: I/O error on JES3 command data set failed.**

Text	ESY5826 I/O error on JES3 command data set.
Expl.	A WRITE attempt to the JES3 command data set failed.
Actn.	This is probably a hardware error. If error persists, it may be advisable to relocate the JES3 command data set.

**NAT5830: JES interface is not active.**

Text	ESY5830 JES interface is not active.
Expl.	The JES interface is not active.
Actn.	Check the JES parameter in the NATURAL PROCESS system parameter module.

**NAT5831: Error during queue initialization.**

Text	ESY5831 Error during queue initialization.
Expl.	An error occurred while reading JES control blocks.
Actn.	This is probably a hardware error. Contact data center personell.

**NAT5832: Error during queue open.**

Text	ESY5832 Error during queue open.
Expl.	An error occurred during open of JES spool data set.
Actn.	Check with the system programmer.

**NAT5833: You are not allowed to alter this job.**

Text	ESY5833 You are not allowed to alter this job.
Expl.	An attempt was made to alter a job. The user is not authorized to alter the specified job. This error message is issued by the security system with which NATURAL PROCESS interfaces.
Actn.	No action is required.

**NAT5834: Command failed, MGCRE RC = :1:.**

Text	ESY5834 Command failed, MGCRE RC = ....
Expl.	A request failed to issue an internal JES or system command.
Actn.	Check with the system programmer. Contact Software AG technical support.

**NAT5840: VTAM operator ACB is not open.**

Text	ESY5840 VTAM operator ACB is not open.
Expl.	The VTAM operator ACB was not opened successfully during initialization.
Actn.	Either active VTAM support has not been requested by the system parameters, or an open error occurred during initialization. The job-log contains further information.

**NAT5841: Error in SENDCMD - RTNCD=:1: FDBK2=:2:.**

Text	ESY5841 Error in SENDCMD - RTNCD=... FDBK2=....
Expl.	A VTAM error occurred while sending a command. Note: A more detailed message is returned when field ERROR-TEXT is specified.
Actn.	Check the command requested. The RTNCD and FDBK2 values are defined in the appropriate VTAM documentation.

**NAT5842: Invalid VTAM command.**

Text	ESY5842 Invalid VTAM command.
Expl.	An invalid VTAM command was requested.
Actn.	No action is required.

**NAT5843: Printer is not available.****NAT5844: Buffer is waiting to be printed.****NAT5845: Printer is active for user :1:.**

Text	ESY5845 Printer is active for user ....
Expl.	Another user is working with the printer.
Actn.	Wait until printer is not busy anymore.

**NAT5846: Use function STATUS to get results.****NAT5847: Print mode ASIS error.****NAT5849: Print failed. Fct=:1: FD=:2: S=:3:.**

Text	ESY5849 Print failed. Fct=... FD=... S=....
Expl.	The print request failed. For further details check the variable data of FUNCTION, FEEDBACK and STATUS. You may find the explanation of these fields in the VTAM documentation.
Actn.	Please contact your systems programmer.

**NAT5850: Error :1: when processing VTOC.**