

Defining Users

The User function enables the system administrator to grant user access to Entire Output Management by creating and modifying user IDs with their passwords and authorization profiles.

Users are defined in Entire Output Management for the following purposes:

- security
- distribution lists
- logging

Every user in Entire Output Management is associated with a user definition, which consists of:

- a user record - this contains details about the user such as user ID, name, phone number, job title, etc.
- a user profile - this contains a list of functions the user is authorized to perform and some defaults.

This section describes the functions available for user maintenance:

- User Maintenance
 - Adding a User Record
 - Adding a User Profile
 - Displaying User Activity Log
 - Display User Cross-Reference Information
 - Copying a User Definition
 - Deleting a User Definition
 - Display User Definition Log Information
 - Modifying a User Record
 - Modifying a User Profile
-

User Maintenance

 **To invoke user uaintenance:**

1. Enter 2 in the command line of the System Administration Menu.

The User Maintenance screen appears:

```

09:52:08          **** Entire Output Management ****          29/02/2008
User ID DC              - User Maintenance -

Cmd User ID  Name                                     Phone
-----
__  AD      Dent, Arthur                               4405
__  AQ      Quatermain, Allan                          5678
__  DC      Copperfield, David                        1362
__  HF      Finn, Huckleberry                            1372
__  JE      Eyre, Jane                                       1366
__  OT      Twist, Oliver                                       1367
__  RC      Crusoe, Robinson                                  1234
__  TS      Sawyer, Thomas                                       1785
__
__
__
__
__
__
All
Command => _____
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help  Add   Exit  Flip          -      +                               Menu
    
```

This screen lists all users defined in Entire Output Management. They are displayed in alphabetical order of user IDs.

For each user, the ID, name and telephone number are displayed.

To display only user IDs that start with a given prefix, you can use an asterisk (*) to enter selection criteria in the field above the user IDs.

- From this screen, you invoke the individual user maintenance functions by pressing a PF key or by marking a user with a line command in the Cmd field.

Special PF Keys

Key	Name	Function
PF2	Add	Define a new user.

Line Commands

Command	Function
CO	Copy the user definition (user record and user profile).
DE	Delete the user definition.
DI	Display the user definition.
FO	Maintain the user's folder.
LO	Display log information for user definition.
MO	Modify the user record.
UL	Display log records of user activity.
UP	Modify the user profile.
XR	Cross-reference: display all objects related to the user.

Adding a User Record

The user record contains details about the user such as user ID, name, phone number, job title, etc.

To add a new user record:

1. Press PF2 (Add) on the User Maintenance screen.

The Define User screen is displayed.

2. On this screen, you enter a user ID and name to create the user record. You can also enter further information for the user.

Special PF Keys

Key	Name	Function
PF9	Profl	Display the user profile.

Fields

Field	Explanation
User ID	Enter the user ID. The user ID uniquely identifies a user in Entire Output Management and is used for security and for report distribution. The user ID must be identified to the security package in your installation, if you have one, for example: RACF, TOP-SECRET, unless the profile field ESY User is set to N.
First Name / Last Name	Enter the user's first name and last name.
All other specifications are optional:	
Address/City/Country/Postal Code	The user's address.
Title	The user's title (for example: President, Materials Manager, Dr., Ms., Mr.).
Dept No	The number of the department where the user works.
Dept Name	The name of the department where the user works.
Location	The location of the user's office.
Organization	The name of the organization for which the user works.
Work Phone	The international dialing code, phone number and extension for the user's telephone at work.
Home Phone	The international dialing code and phone number for the user's telephone at home.

Adding a User Profile

The user profile contains a list of functions the user is authorized to perform.

 **To add a new user profile:**

1. Press PF9 (Profl) on the Define User screen.

The following screen appears:

```

12:48:44          **** ENTIRE OUTPUT MANAGEMENT ****          2008-11-29
User ID XYZ          - User Profile Definition -

User ID .. CTY
Name ..... Tyree, Clinton

User Type      (A/G/O/P) A   Confirm          (Y/N) N   Editor Prefix  (Y/N) Y
Language Code  (1/2) 1     Auto-Commit     (E/I) E   Editor PF-Keys (Y/N) Y
ESY User       (Y/N) Y

Report         (D/M/P) P   Active Reports (D/M/P) P   Archive        (Y/N) Y
Bundle         (D/M/P) P       sort by         (D/N) N   Revive         (Y/N) Y
Distrib. List  (D/M/P) P   Active Bundles (D/M/P) P   Flush Bundle   (Y/N) Y
Printer        (D/M/P) P   Printouts       (D/M/P) P

Phys. Printer  (D/M/P) P   Archive Admin. (Y/N) Y   Monitor Startup (Y/N) Y
Calendar       (D/M/P) P   System Defaults (D/M) M   Monitor Shutdwn (Y/N) Y
User           (D/M/P) P   Restrict Abun. (Y/N) _   Abun list format(1/2) _
                                   Displ.long names (Y/N) _   Display Mon-Log (Y/N) Y

Command => _____
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help           Exit Flip Do      Undo                               Menu

```

This screen lists the functions permitted to the user. Next to each function, the possible values are shown in parentheses.

Fields

Field	Explanation
User ID	ID of user whose profile is being defined.
Name	The user's name as entered on the Define User screen.
User Type (A/G/O/P)	<p>Possible values:</p> <ul style="list-style-type: none"> ● A - Administrator: The user can see the entire printout queue. ● G - General user: The user will only see the printouts he/she has explicit access to. ● O - Operator: The user can see the entire printout queue. In addition to the same rights as a general user, he/she may manage objects in the printout queue without having explicit authorization for them. ● P - Printer-associated user: The user has access to all printouts of all printers he/she has access to. For this user, only the printout queue of the respective printer(s) will be shown.
Language Code (1/2)	Specify the language code for the user interface: 1 = English, 2 = German.
ESY User	Is the user ID defined in the external security system? Enter "Y" (yes) or "N" (no). (See also the field description for Use Owner ID).
Confirm (Y/N)	<p>Enter "Y" to open a window requesting confirmation of deletion.</p> <p>Enter "N" to suppress the window.</p>
Auto-Commit (E/I)	<p>Enter "E" (explicit) to open a window requesting confirmation of modifications.</p> <p>Enter "I" (implicit) to commit modifications automatically.</p>
Editor Prefix	<p>Enter "Y" to display the six columns with line numbers on the left-hand side of the Editor screen when browsing active reports.</p> <p>Enter "N" to suppress the display.</p>
Editor PF Keys	<p>Enter "Y" to display the PF-key assignments at the bottom of the Editor screen when browsing active reports.</p> <p>Enter "N" to suppress the display.</p>

Field	Explanation
Report	The user may perform the following functions on objects of this type:
Bundle	
Distribution List	
Printer	
Physical Printer	
Calendar	
User	
Active Reports	
Active Bundles	
Printouts	
- sort by	
Archive	Y = The user is allowed to perform the corresponding function. N = The user is not allowed to perform the corresponding function.
Revive	
Flush Bundle	
Archive Administration	
Monitor Startup	
Monitor Shutdown	
Display Monitor	
System Defaults (D/M)	D = The user may display the system defaults; M = The user may modify the system defaults.
Restrict Abun (Y/N)	Y = prevent users from listing all active bundles; N = allow users to list all active bundles; users can display and add reports only into active bundles for which they are authorized; these bundles are highlighted in the Active Bundle list.
Abun List Format (1/2)	This option controls the behaviour of active bundle list wildcard selection: 1 = the user is presented with a list of matching active bundle names from which he/she may select one; active bundles with the selected name are then listed; 2 = all matching active bundle names are listed.
Display Long names (Y/N)	Y = Long report and bundle names consisting of up to 25 characters (see System Defaults) are displayed; N = Long names are not displayed. If long-name display is not supported by the system, this field is automatically set to "N" and cannot be overwritten.

Displaying User Activity Log

▶ To display log information about a user's activities:

1. Enter UL in the command line preceding the appropriate user.

A screen is displayed listing all activities performed by the user. For each activity, the following information is displayed:

Field	Explanation
Date	The date of the activity performed.
Time	The time of the activity performed.
Object	The entity on which the user performed the activity.
Message	The activity performed.

Display User Cross-Reference Information

▶ To display cross-reference information about a user:

1. Enter XR in the command line preceding the appropriate user.

The XREF of User window for the selected user is displayed. It shows the entities related to the user ID, grouped by categories. If a category contains entities related to the user ID, you can mark that category in the M column with any character.

2. Mark the category for which cross reference information is to be displayed.

A window is displayed, listing all entities of the selected type to which the user is linked.

Copying a User Definition

▶ To copy a user:

1. On the User Maintenance screen, enter CO in the command line preceding the user you want to copy.

The Copy User Definition window opens.

2. Type the name of the target user in the input field provided.

A message confirms that the user has been copied.

Deleting a User Definition

▶ To delete a user:

1. On the User Maintenance screen, enter `DE` in the command line preceding the user you want to delete.

If `CONFIRM` is set to `ON`, a window opens which asks you to confirm deletion by typing the user ID again.

2. Type the user ID in the input field provided.

A message confirms the deletion.

Display User Definition Log Information

To display user definition log information:

1. On the User Maintenance screen, enter `LO` in the command line preceding the user definition for which you want to display log information.

The Log Display screen appears for the user definition selected.

2. You can display more information about a log entry by entering the `IN` line command in the command line preceding the entry.

Modifying a User Record

To modify a user record:

1. On the User Maintenance screen, enter `MO` in the command line preceding the user you want to modify.

The Define User screen appears for the user you have selected.

2. You can modify the data displayed by overwriting them. Then you press `ENTER` to save your modifications.

A message confirms the modification.

Modifying a User Profile

To modify a user profile:

1. On the User Maintenance screen, enter `UP` in the command line preceding the user you want to modify.

The user profile of the user is displayed.

2. You can modify the data displayed by overwriting them. Then you press `ENTER` to save your modifications.

A message confirms the modification.