

Entire Connection

Error Messages

Version 9.3.4

September 2026

This document applies to Entire Connection Version 9.3.4 and all subsequent releases.

Specifications contained herein are subject to change and these changes will be reported in subsequent release notes or new editions.

Copyright © 1984-2026 Software GmbH, Darmstadt, Germany and/or its subsidiaries and/or its affiliates and/or their licensors.

The name Software AG and all Software GmbH product names are either trademarks or registered trademarks of Software GmbH and/or its subsidiaries and/or its affiliates and/or their licensors. Other company and product names mentioned herein may be trademarks of their respective owners.

Detailed information on trademarks and patents owned by Software GmbH and/or its subsidiaries is located at <https://softwareag.com/licenses>.

Use of this software is subject to adherence to Software GmbH's licensing conditions and terms. These terms are part of the product documentation, located at <https://softwareag.com/licenses> and/or in the root installation directory of the licensed product(s).

This software may include portions of third-party products. For third-party copyright notices, license terms, additional rights or restrictions, please refer to "License Texts, Copyright Notices and Disclaimers of Third-Party Products". For certain specific third-party license restrictions, please refer to section E of the Legal Notices available under "License Terms and Conditions for Use of Software GmbH Products / Copyright and Trademark Notices of Software GmbH Products". These documents are part of the product documentation, located at <https://softwareag.com/licenses> and/or in the root installation directory of the licensed product(s).

Use, reproduction, transfer, publication or disclosure is prohibited except as specifically provided for in your License Agreement with Software GmbH.

Document ID: PCC-MESSAGES-934-20260915

Table of Contents

1 About this Documentation	1
Document Conventions	2
Online Information and Support	2
Data Protection	3
2 Error Messages	5

1

About this Documentation

■ Document Conventions	2
■ Online Information and Support	2
■ Data Protection	3

Document Conventions

Convention	Description
Bold	Identifies elements on a screen.
Monospace font	Identifies service names and locations in the format <i>folder.subfolder.service</i> , APIs, Java classes, methods, properties.
<i>Italic</i>	Identifies: Variables for which you must supply values specific to your own situation or environment. New terms the first time they occur in the text. References to other documentation sources.
Monospace font	Identifies: Text you must type in. Messages displayed by the system. Program code.
{ }	Indicates a set of choices from which you must choose one. Type only the information inside the curly braces. Do not type the { } symbols.
	Separates two mutually exclusive choices in a syntax line. Type one of these choices. Do not type the symbol.
[]	Indicates one or more options. Type only the information inside the square brackets. Do not type the [] symbols.
...	Indicates that you can type multiple options of the same type. Type only the information. Do not type the ellipsis (...).

Online Information and Support

Product Documentation

You can find the product documentation on our documentation website at <https://documentation.softwareag.com>.

Product Training

You can find helpful product training material on our Learning Portal at <https://learn.software-ag.com>.

Tech Community

You can collaborate with Software GmbH experts on our Tech Community website at <https://tech-community.softwareag.com>. From here you can, for example:

- Browse through our vast knowledge base.
- Ask questions and find answers in our discussion forums.
- Get the latest Software GmbH news and announcements.
- Explore our communities.
- Go to our public GitHub and Docker repositories at <https://github.com/softwareag> and <https://hub.docker.com/publishers/softwareag> and discover additional Software GmbH resources.

Product Support

Support for Software GmbH products is provided to licensed customers via our Empower Portal at <https://empower.softwareag.com>. Many services on this portal require that you have an account. If you do not yet have one, you can request it at <https://empower.softwareag.com/register>. Once you have an account, you can, for example:

- Download products, updates and fixes.
- Search the Knowledge Center for technical information and tips.
- Subscribe to early warnings and critical alerts.
- Open and update support incidents.
- Add product feature requests.

Data Protection

Software AG products provide functionality with respect to processing of personal data according to the EU General Data Protection Regulation (GDPR). Where applicable, appropriate steps are documented in the respective administration documentation.

2 Error Messages

0-010 SAGExt version incorrect.

Text	SAGExt version incorrect.
Explanation	The SAGExt.DLL does not have the correct version. Entire Connection cannot be started.
Action	Repair your Entire Connection installation.

0-011 OLE initialization failed.

Text	OLE initialization failed.
Explanation	OLE initialization failed. Entire Connection cannot be started.
Action	Check your Windows system. Make sure that the OLE libraries have the correct version.

0-012 Error on startup.

Text	Error on startup.
Explanation	Error on startup. Entire Connection cannot be started.
Action	Repair your Entire Connection installation.

0-013 Initialization failed.

Text	Initialization failed.
Explanation	The Entire Connection initialization failed. The parameters you passed are not valid.
Action	Correct the startup parameters and restart Entire Connection.

0-014 Error starting Entire Connection.

Text	Error starting Entire Connection.
Explanation	An unrecoverable error occurred while starting Entire Connection.
Action	Check your Entire Connection installation and configuration, and retry.

0-015 Initialization failed.

Text	Initialization failed.
Explanation	An unrecoverable error occurred while initializing Entire Connection.
Action	Check your Entire Connection installation and configuration, and retry.

0-020 User properties record does not exist.

Text	User properties record does not exist.
Explanation	You selected "Use Windows user name for logon" and "Create user properties automatically" in the "System Preferences and Settings" dialog box. The user properties record for Windows <i>user-name</i> does not exist.
Action	Select "Yes" if you want to create the user properties with the default values. Contact your Entire Connection administrator if you are not sure what to do.

0-021 Unknown user name or password.

Text	Unknown user name or password.
Explanation	Logon to Entire Connection failed. The user name or password entered is unknown to Entire Connection.
Action	Check and correct the user name and the password.

0-022 Already logged on with this user name.

Text	Already logged on with this user name.
Explanation	You are already logged on with <i>user-name</i> to another Entire Connection terminal you started on the PC. You cannot run multiple Entire Connection terminals with different users logged on at the same time.
Action	Check the startup parameters and the setting of "Use Windows user name for logon" in the "System Preferences and Settings" dialog box.

0-023 Error with user-defined menu.

Text	Error with user-defined menu.
Explanation	An error was detected in the definition of the user-defined menu. The menu you selected could not be displayed.
Action	Check the definitions of the menu in the Entire Connection Configuration Manager.

0-030 No tasks and procedure files found.

Text	No tasks and procedure files found.
Explanation	No tasks and no procedure files were found. There may be a problem with the share file or the procedure folder setting.
Action	Check the defined tasks and the procedure folder setting in the Entire Connection Configuration Manager.

0-031 Error occurred in starting command, task or procedure file.

Text	Error occurred in starting command, task or procedure file.
Explanation	The command, task or procedure file you wanted to execute could not be started.
Action	Check your Entire Connection installation and configuration, and retry.

0-032 Canceling procedure has been rejected.

Text	Canceling procedure has been rejected.
Explanation	Canceling procedure has been rejected. The Entire Connection system is instable.
Action	Check your Windows system for unusual high memory usage. Restart Entire Connection.

0-033 Running procedure file has been rejected.

Text	Running procedure file has been rejected.
Explanation	Running the procedure file has been rejected. The Entire Connection system is instable.
Action	Check your Windows system for unusual high memory usage. Restart Entire Connection.

0-034 Procedure debugger has nothing to run.

Text	Procedure debugger has nothing to run.
Explanation	You are in the procedure debugger but there are no procedure files or no more procedure commands to execute.
Action	Check and correct.

0-040 Error opening session.

Text	Error opening session.
Explanation	Failed to open session.
Action	Check the session properties of the session you tried to open.

0-041 Maximum number of concurrent open terminal windows has exceeded.

Text	Maximum number of concurrent open terminal windows has exceeded.
Explanation	The number of open terminal windows is limited in your user properties. The maximum number of concurrent open terminal windows has exceeded. No new terminal window could be opened.
Action	Close terminal windows that you do not need. Contact your Entire Connection system administrator if you need more concurrent open sessions.

0-042 No sessions are currently defined.

Text	No sessions are currently defined.
Explanation	Failed to open session. No sessions are currently defined.
Action	Check your share file and create session properties for the hosts you want to use.

0-050 The Configuration Manager was not found.

Text	The Configuration Manager was not found.
Explanation	Starting the Entire Connection Configuration Manager from the terminal window failed. The executable for the Configuration Manager (Pccadmin.exe) was not found.
Action	Repair your Entire Connection installation.

0-051 The Configuration Manager cannot be started.

Text	The Configuration Manager cannot be started.
Explanation	The Configuration Manager cannot be started. There was an error with error-code <i>error-code</i> when starting the Entire Connection Configuration Manager.
Action	Check your Entire Connection installation and configuration, and retry.

0-052 The Host Printer Manager was not found.

Text	The Host Printer Manager was not found.
Explanation	Starting the Entire Connection Host Printer Manager failed. The executable for the Host Printer Manager (PccPLUMn.exe) was not found.
Action	Repair your Entire Connection installation.

0-053 The Host Printer Manager cannot be started.

Text	The Host Printer Manager cannot be started.
Explanation	The Host Printer Manager cannot be started. There was an error with error-code <i>error-code</i> when starting the Entire Connection Host Printer Manager.
Action	Check your Entire Connection installation and configuration, and retry.

0-060 Error reading unattended workstation data.

Text	Error reading unattended workstation data.
Explanation	An error occurred while reading the scheduling data for the unattended workstation. Cannot enter unattended mode.
Action	Check your scheduling data for the unattended workstation. Check your hard disk. Restore your share file from a backup and retry.

0-061 Error writing the unattended workstation scheduling data.

Text	Error writing the unattended workstation scheduling data.
Explanation	An error occurred while writing the unattended workstation scheduling data to the share file.
Action	Check your hard disk. Restore your share file from a backup and retry.

0-110 Missing ending quote in startup parameter.

Text	Missing ending quote in startup parameter.
Explanation	The startup parameter <i>token</i> has a beginning quote (" or '), but no ending quote (" or '). If you use quotes for string arguments, they must be paired. You have to use quotes for strings containing blanks.
Action	Check and correct.

0-111 Error parsing startup parameters.

Text	Error parsing startup parameters.
Explanation	An error occurred while parsing the startup parameters.
Action	Check and correct.

0-113 Startup parameters too long.

Text	Startup parameters too long.
Explanation	You entered too many characters for the startup parameters - the maximum length for all startup parameters is 192 characters.
Action	Check and correct.

0-114 Internal error: No share file name passed.

Text	Internal error: No share file name passed.
Explanation	No share file name was passed to the loader routine. Internal error. Can only happen in the development environment.
Action	No action required.

0-140 Error opening share file.

Text	Error opening share file.
Explanation	Opening the share file <i>name</i> returned an error with error-code <i>error-code</i> . The error-code is the return code of the Open File function of Windows. Entire Connection cannot be started.
Action	Check your hard disk. Restore your share file from a backup and retry.

0-142 SYSTEM properties record not found.

Text	SYSTEM properties record not found.
Explanation	The SYSTEM properties record was not found in share file <i>name</i> . Entire Connection cannot be started.
Action	Check your hard disk. Restore your share file from a backup and retry.

0-144 Error reading share file.

Text	Error reading share file.
Explanation	An error occurred while reading the share file <i>name</i> . Entire Connection cannot be started.
Action	Check your hard disk. Restore your share file from a backup and retry.

0-145 Wrong share file version.

Text	Wrong share file version.
Explanation	The share file <i>name</i> is not compatible with the current version of Entire Connection. Entire Connection cannot be started.
Action	Check and correct.

0-146 File is not an Entire Connection share file.

Text	File is not an Entire Connection share file.
Explanation	The share file <i>name</i> is not an Entire Connection share file.
Action	Check and correct.

0-150 WORD table missing.

Text	WORD table missing.
Explanation	There is an error in the share file - the WORD table is missing. Entire Connection cannot be started.
Action	Restore your share file from a backup and retry.

0-153 Terminal function code table missing.

Text	Terminal function code table missing.
Explanation	There is an error in the share file - the terminal function code table <i>name</i> is missing. Entire Connection cannot be started.
Action	Restore your share file from a backup and retry.

0-160 Error opening table input file.

Text	Error opening table input file.
Explanation	An error occurred while opening the table input file <i>name</i> . This error can only occur in the development environment.
Action	No action required.

0-161 Missing table name.

Text	Missing table name.
Explanation	The table name is missing in line <i>number</i> of the table input file <i>name</i> . This error can only occur in the development environment.
Action	No action required.

0-162 Too many entries for the table.

Text	Too many entries for the table.
Explanation	There is an error in the table input file <i>name</i> in line <i>number</i> - too many entries for the table. Only 16 entries per table are allowed. This error can only occur in the development environment.
Action	No action required.

0-163 Token number error.

Text	Token number error.
Explanation	There is an error in the table input file <i>name</i> in line <i>number</i> - incorrect number of tokens. There must be 18 hexadecimal tokens. This error can only occur in the development environment.
Action	No action required.

0-164 Out of sequence.

Text	Out of sequence.
Explanation	There is an error in the translation table input file <i>name</i> in line <i>number</i> - out of sequence.
Action	Check and correct.

0-165 First token not equal to last token.

Text	First token not equal to last token.
Explanation	There is an error in the translation table input file <i>name</i> in line <i>number</i> - the first token is not equal to the last token.
Action	Check and correct.

0-166 Table incomplete.

Text	Table incomplete.
Explanation	There is an error in the translation table input file <i>name</i> in line <i>number</i> - the table is incomplete. Rows 0 - F are required.
Action	Check and correct.

0-167 Too many translation tables.

Text	Too many translation tables.
Explanation	There is an error in the translation table input file <i>name</i> in line <i>number</i> - too many translation tables defined.
Action	Check and correct.

0-170 Error in input line.

Text	Error in input line.
Explanation	There is an error in the physical keyboard table input file <i>name</i> in line <i>number</i> .
Action	Check and correct.

0-172 Missing lines in table NUMPAD.

Text	Missing lines in table NUMPAD.
Explanation	There is an error in the physical keyboard table input file - lines missing in table NUMPAD.
Action	Check and correct.

0-173 Missing lines in table KEYTABLE.

Text	Missing lines in table KEYTABLE.
Explanation	There is an error in the physical keyboard table input file - lines missing in table KEYTABLE.
Action	Check and correct.

0-175 Too many lines in table KEYTABLE.

Text	Too many lines in table KEYTABLE.
Explanation	There is an error in the physical keyboard table input file - too many lines in table KEYTABLE.
Action	Check and correct.

0-176 Invalid table name.

Text	Invalid table name.
Explanation	The table name <i>name</i> specified in the terminal function code table input file is not valid for this kind of table. Valid names are BS2, HLLAPI, N3270, VTXXX and VT_aaa, where aaa can be 1 to 28 characters long.
Action	Check and correct.

0-177 No table name specified.

Text	No table name specified.
Explanation	There is an error in the terminal function code table input file <i>name</i> - no table name specified.
Action	Check and correct.

0-999 Syntax error in command.

Text	Syntax error in command.
Explanation	There is a syntax error in the element <i>token</i> of the command in line <i>line</i> . This general message is used if a specific error message has not yet been implemented. It should only happen in the development environment.
Action	Report the error to your local our support.

1-006 Communication method not yet supported.

Text	Communication method not yet supported.
Explanation	The communication method specified in the session properties is not yet supported. This can only happen in a development test environment.
Action	No action required.

1-007 Session not defined in the share file.

Text	Session not defined in the share file.
Explanation	An error occurred while reading the session data from the share file.
Action	Reorganize the share file with the Configuration Manager (go to the Tools menu and choose Reorganize Share File). If the error is still there, create the session again or use a backup copy of your share file.

1-008 Data transfer has aborted.

Text	Data transfer has aborted.
Explanation	The Natural data transfer with Entire Connection has aborted. The previous error messages contain more details about the cause.
Action	If the data transfer has aborted because of an error, save the error trace file XFER_ERR.TRC from the log and trace directory, and report the error to your local our support including the error trace file.

1-009 The interface to the print service could not be opened.

Text	The interface to the print service could not be opened.
Explanation	The associated printer session was not created. Printing to the associated printer session failed.
Action	Close the display session and open it again. If the error persists, report the error to your local our support.

1-010 Communication method not supported by terminal server.

Text	Communication method not supported by terminal server.
Explanation	The communication method specified in the session you tried to open is not supported by the terminal server. Because of technical restrictions, the communication methods "HLLAPI" and "Serial VTxxx" cannot be used on a terminal server.
Action	Use a local installation if you want to use these communication methods.

1-012 Communication method no longer supported.

Text	Communication method no longer supported.
Explanation	The communication method specified in the session you tried to open is no longer supported.
Action	Check the Entire Connection documentation, chapter Installation, Supported Communication Methods for alternative communication methods.

1-400 Error text not found.

Text	Error text not found.
Explanation	The error text for the error number n could not be found. This should only happen during development.
Action	Report the error to your local our support.

2-101 File access error.

Text	File access error.
Explanation	An error occurred while accessing the file <i>file</i> . The operating system error-code was <i>n</i> .
Action	Check the operating system error-code for details. You find a list of the operating system error-codes in your operating system documentation.

3-001 Internal error.

Text	Internal error.
Explanation	Internal error while parsing the BS2000 9750 data stream. This can only happen in a development test environment.
Action	No action required.

3-002 Internal error.

Text	Internal error.
Explanation	Internal error in the command parser routine <i>cp_subst</i> .
Action	If the error persists, report the error to your local our support.

3-004 Internal error.

Text	Internal error.
Explanation	Internal error in the routine <i>cp_setke</i> .
Action	If the error persists, report the error to your local our support.

3-005 Dynamic variables cannot be set.

Text	Dynamic variables cannot be set.
Explanation	You cannot set a value for a dynamic variable. Dynamic variables start with an asterisk (*).
Action	See chapter Terminal Emulation, Procedure Files, Variables in Procedure Files in the Entire Connection documentation.

3-006 Internal error.

Text	Internal error.
Explanation	Internal error in the routine <i>cp_value</i> .
Action	If the error persists, report the error to your local our support.

3-007 Cannot not open audit log file.

Text	Cannot not open audit log file.
Explanation	The audit log file <i>file-name</i> could not be created or opened. Possible reasons are a wrong setting for the user's log and trace directory or disk problems.
Action	Check the setting of the user's log and trace directory in the Configuration Manager, User Properties, Procedure dialog.

3-008 Internal error - unknown command in pcode.

Text	Internal error - unknown command in pcode.
Explanation	Internal error in the routine cp_rout.
Action	If the error persists, report the error to your local our support.

3-010 Task does not exist.

Text	Task does not exist.
Explanation	The task <i>task-name</i> was scheduled for execution but does not or no longer exist in the share file.
Action	Check the task definitions with the Entire Connection Configuration Manager.

3-012 Internal error.

Text	Internal error.
Explanation	Internal error in the routine js_exec.
Action	If the error persists, report the error to your local our support.

3-013 Internal error.

Text	Internal error.
Explanation	Internal error in the routine js_exec.
Action	If the error persists, report the error to your local our support.

3-014 DOS task cannot be executed.

Text	DOS task cannot be executed.
Explanation	The task <i>task-name</i> cannot be executed. In your user properties, DOS tasks are marked to be not allowed for you. The property to disallow DOS tasks is no longer supported since version 4 of Entire Connection. This error can only occur if you merged a version 3 share file containing tasks which use this property.
Action	Delete and then re-create the user properties with the current version of the Entire Connection Configuration Manager.

3-020 Error starting task.

Text	Error starting task.
Explanation	An operating system error occurred when trying to start the Entire Connection task <i>task-name</i> with the program <i>program-name</i>
Action	Check the task definition.

3-040 Task does not exist.

Text	Task does not exist.
Explanation	The task <i>task-name</i> does not exist in the share file.
Action	Check the task name used and also the task definitions in the share file.

3-042 Missing ending quotes in literal string.

Text	Missing ending quotes in literal string.
Explanation	The string <i>string</i> in token <i>n</i> does not have ending quotes. Procedure file input arguments must have paired quotes.
Action	Correct error.

3-052 Unknown dynamic variable.

Text	Unknown dynamic variable.
Explanation	An unknown dynamic variable is used in the command. This should only happen in the development environment.
Action	Report the error to your local our support.

4-001 LocalLock failed.

Text	LocalLock failed.
Explanation	A memory request to the Windows operating system failed. The current Entire Connection operation failed.
Action	Stop Entire Connection, close other Windows applications, and then try again.

5-000 No more tables available.

Text	No more tables available.
Explanation	The internal table manager of Entire Connection ran out of space. This should only happen in the development environment.
Action	Stop Entire Connection and retry. If the error persists, report the error to your local our support.

10-000 Unknown command or task.

Text	Unknown command or task.
Explanation	The command or task <i>name</i> in line <i>n</i> is unknown in Entire Connection.
Action	Specify a valid command. See the Entire Connection documentation for information on the commands.

10-001 Operation could not be completed.

Text	Operation could not be completed.
Explanation	You cannot modify session related variables from the command line.
Action	No action required.

10-002 No command specified.

Text	No command specified.
Explanation	A command containing only blanks was entered.
Action	Specify a valid command.

10-010 Invalid file number in command.

Text	Invalid file number in command.
Explanation	Invalid file number for command <i>cmd</i> in line <i>n</i> Valid file numbers are 1,2,3 or 4. See the Entire Connection documentation for information on the commands OPEN, CLOSE, READ and WRITE.
Action	Correct the command.

10-011 OPEN requires a file name.

Text	OPEN requires a file name.
Explanation	The OPEN command in line <i>n</i> requires a file name. See the Entire Connection documentation for information on the command OPEN.
Action	Correct error.

10-012 READ command requires global or local parameter variables.

Text	READ command requires global or local parameter variables.
Explanation	The READ command requires global or global parameter variables. You may use +PARM0 - +PARM9 and/or #PARM0 - #PARM9. See the Entire Connection documentation for information on the command READ.
Action	Correct error.

10-022 Local variable may not be set at this time.

Text	Local variable may not be set at this time.
Explanation	A local procedure variable cannot be specified in the command line (using the SET command). Local variables can only be used in procedure files. See the Entire Connection documentation for information on the commands.
Action	Correct error.

10-024 You cannot use a SET key command within a SET key command.

Text	You cannot use a SET key command within a SET key command.
Explanation	You may not use a SET PCKEY/TEKEY command within a SET PCKEY/TEKEY command.
Action	Correct error.

10-025 Too many parameters for the command.

Text	Too many parameters for the command.
Explanation	Too many parameters are given for the command <i>cmd</i> . For example, only 10 parameters are allowed for the command EXECUTE.
Action	Correct error.

10-030 Wrong screen range in *SCREEN variable.

Text	Wrong screen range in *SCREEN variable.
Explanation	The screen range given for the *SCREEN variable is less than the length of the compare string. For information on how to use the *SCREEN variable, see the documentation for the Entire Connection command IF.
Action	Correct error.

10-031 Literal string does not have ending quotes.

Text	Literal string does not have ending quotes.
Explanation	Literal string does not have ending quotes. Quoted strings must be paired.
Action	Correct error.

10-032 NULL string not valid.

Text	NULL string not valid.
Explanation	An empty string (NULL string) is not valid in compare commands such as IF or WAITFOR.
Action	Correct error.

10-040 Command TYPE not allowed.

Text	Command TYPE not allowed.
Explanation	The TYPE command is not allowed in this statement.
Action	Remove the TYPE command from the statement.

10-050 Invalid use of local variable.

Text	Invalid use of local variable.
Explanation	Invalid use of local variable. You cannot use a local variable with the commands CLOSE, INPUT, OPEN-I, OPEN-O, READ, SET PCFILE, WAITM and WRITE.
Action	Correct error.

10-051 Unsupported key type in SET key_var statement.

Text	Unsupported key type in SET key_var statement.
Explanation	The key type used in the SET key_var statement is no longer supported. Valid key type for key_var is TEKEY.
Action	Correct error.

10-054 TEKEY may not be set at this time.

Text	TEKEY may not be set at this time.
Explanation	You cannot set a TEKEY at this time.
Action	Use the "Terminal Emulation Key Scheme" dialog box of the Entire Connection Configuration Manager.

10-056 VTKEY may not be set at this time.

Text	VTKEY may not be set at this time.
Explanation	You cannot set a VTKEY at this time.
Action	Modify the appropriate .key table file in the tables folder of your installation. Then use the "Terminal function code" dialog of the Entire Connection Configuration Manager to import the table.

10-057 3278KEY may not be set at this time.

Text	3278KEY may not be set at this time.
Explanation	You cannot set a 3278KEY at this time.
Action	Modify the appropriate .key table file in the tables folder of your installation. Then use the "Terminal function code" dialog of the Entire Connection Configuration Manager to import the table.

10-062 Only one *SCREEN variable allowed.

Text	Only one *SCREEN variable allowed.
Explanation	Only one *SCREEN variable may be used in the command.
Action	Correct error.

10-071 Invalid PCFILE number in SET PCFILE command.

Text	Invalid PCFILE number in SET PCFILE command.
Explanation	The file number specified in the SET PCFILE command is not valid. The file number must be an integer value in the range 1 - 32.
Action	Correct error.

10-077 Invalid combination of parameters in SET PCFILE command.

Text	Invalid combination of parameters in SET PCFILE command.
Explanation	The parameters UP and REPORT cannot be combined in the SET PCFILE command.
Action	Correct error.

10-083 *SCREEN variable cannot be used from the command line.

Text	*SCREEN variable cannot be used from the command line.
Explanation	The variable *SCREEN cannot be used from the command line. *SCREEN can be used from a procedure file.
Action	Correct error.

10-084 Too many tokens after *SCREEN variable.

Text	Too many tokens after *SCREEN variable.
Explanation	No more tokens are allowed after *SCREEN format. For information on how to use the *SCREEN variable, see the Entire Connection documentation for information on the command IF.
Action	Correct error.

10-087 Invalid value for MINUTE parameter.

Text	Invalid value for MINUTE parameter.
Explanation	The value for the MINUTE parameter must be an integer value.
Action	Correct error.

10-109 Number or variable expected.

Text	Number or variable expected.
Explanation	A number or variable was expected. You must use an integer or a variable that contains an integer.
Action	Correct error.

10-110 PARITY keyword or variable expected.

Text	PARITY keyword or variable expected.
Explanation	A PARITY keyword or variable was expected. You must use a PARITY keyword or a variable that contains an integer.
Action	Correct error.

10-111 BINARY keyword or variable expected.

Text	BINARY keyword or variable expected.
Explanation	A BINARY keyword or variable expected. You must use a BINARY keyword or a variable here.
Action	Correct error.

10-113 String or variable expected.

Text	String or variable expected.
Explanation	A string or variable expected was expected at the position <i>n</i> . You may use a quoted string or a variable.
Action	Correct error.

10-116 Command expected.

Text	Command expected.
Explanation	A command was expected at the position <i>n</i> . You can use any Entire Connection command except IF, IFNOT, WAITFOR.
Action	Correct error.

10-117 Command expected.

Text	Command expected.
Explanation	A command was expected at the position <i>n</i> . You can use any Entire Connection command here.
Action	Correct error.

10-118 Command not valid here.

Text	Command not valid here.
Explanation	Command <i>cmd</i> not valid here. This command cannot be used from the command line.
Action	Correct error.

10-119 Syntax error.

Text	Syntax error.
Explanation	Syntax error in token <i>n</i> . No matching command or variable found.
Action	Correct error.

10-120 System variable, global variable or local variable expected.

Text	System variable, global variable or local variable expected.
Explanation	The token at position <i>n</i> should be a system variable, a global variable or a local variable.
Action	Correct error.

10-128 A label expected.

Text	A label expected.
Explanation	The token at position <i>n</i> should be a label.
Action	Correct error.

10-129 Invalid label.

Text	Invalid label.
Explanation	The label at position <i>n</i> is not valid. A label can't be greater then 12 characters.
Action	Correct error.

10-130 Command expected.

Text	Command expected.
Explanation	The token at position <i>n</i> should be a command.
Action	Correct error.

10-131 TEKEY keyword expected.

Text	TEKEY keyword expected.
Explanation	The TEKEY keyword is expected as token <i>n</i> .
Action	Correct error.

10-132 Variables not allowed here.

Text	Variables not allowed here.
Explanation	The token 3 in a SET TEKEY command must be a keyword for a key of the physical keyboard, for example, F1.
Action	Correct error.

10-133 Keyword for key of physical keyboard expected.

Text	Keyword for key of physical keyboard expected.
Explanation	The token 3 in a SET PCKEY command must be a keyword for a key of the physical keyboard, for example, F1.
Action	Correct error.

10-135 VT100 key expected.

Text	VT100 key expected.
Explanation	The token 3 in a SET VTKEY command must be the keyword for a VT100 key. Used in SET VTKEY commands in the terminal function code tables.
Action	Contact your local our support for assistance to correct error.

10-139 XCLOCK/KEYRESET keyword or TYPE keyword expected.

Text	XCLOCK/KEYRESET keyword or TYPE keyword expected.
Explanation	An XCLOCK/KEYRESET keyword or TYPE keyword was expected but not found. Used in SET 3278KEY and SET VTKEY commands in the terminal function code tables.
Action	Contact your local our support for assistance to correct error.

10-141 Keyword for terminal emulation key expected.

Text	Keyword for terminal emulation key expected.
Explanation	A keyword for a terminal emulation key was expected but not found. Used in SET 3278KEY and SET VTKEY commands in the terminal function code tables.
Action	Contact your local our support for assistance to correct error.

10-142 Keyword for PC key expected.

Text	Keyword for PC key expected.
Explanation	A keyword for a PC key was expected but not found. Used in SET 3278KEY and SET VTKEY commands in the terminal function code tables.
Action	Contact your local our support for assistance to correct error.

10-143 Literal or keyword for a VT100 key expected.

Text	Literal or keyword for a VT100 key expected.
Explanation	A literal or a keyword for a VT100 key was expected but not found. Used in SET VTKEY commands in the terminal function code tables.
Action	Contact your local our support for assistance to correct error.

10-144 Token not a keyword for a VT100 key.

Text	Token not a keyword for a VT100 key.
Explanation	A keyword for a VT100 key was expected but not found. Used in SET VTKEY commands in the terminal function code tables.
Action	Contact your local our support for assistance to correct error.

10-145 Token not a literal, global variable, system variable or PC key.

Text	Token not a literal, global variable, system variable or PC key.
Explanation	A literal, global variable, system variable, or PC key was expected but not found. Used in internal tables in SET key commands.
Action	Contact your local our support for assistance to correct error.

10-146 Token not a literal, global variable, system variable, or terminal emulation key.

Text	Token not a literal, global variable, system variable, or terminal emulation key.
Explanation	A literal, global variable, system variable, or terminal emulation key was expected but not found. Used in internal tables in SET key commands.
Action	Contact your local our support for assistance to correct error.

10-150 Global or local counter variable expected.

Text	Global or local counter variable expected.
Explanation	A global or local counter variable is expected with a DECR and INCR command. See the Entire Connection documentation for information on the commands DECR and INCR.
Action	Correct error.

10-151 Global or local variable expected.

Text	Global or local variable expected.
Explanation	A global or local variable is expected with the RESETVAR command. See the Entire Connection documentation for information on the command RESETVAR.
Action	Correct error.

10-152 Keyword GLOBALS or LOCALS expected.

Text	Keyword GLOBALS or LOCALS expected.
Explanation	The keyword GLOBALS or LOCALS is expected with the SHIFT command. See the Entire Connection documentation for information on the command SHIFT.
Action	Correct error.

10-153 Binary system variable expected.

Text	Binary system variable expected.
Explanation	A binary system variable is expected with the TOGGLE command. See the Entire Connection documentation for information on the command TOGGLE.
Action	Correct error.

10-160 *SCREEN format syntax error.

Text	*SCREEN format syntax error.
Explanation	*SCREEN format syntax error. A row, but no column is specified.
Action	Correct error.

10-163 Literal or variable expected.

Text	Literal or variable expected.
Explanation	A literal or variable is expected after token <i>n</i> .
Action	Correct error.

10-164 Operator expected.

Text	Operator expected.
Explanation	An operator is expected after token <i>n</i> .
Action	Correct error.

10-165 Operator expected.

Text	Operator expected.
Explanation	An operator is expected before token <i>n</i> .
Action	Correct error.

10-166 Operator or command expected.

Text	Operator or command expected.
Explanation	An operator or command is expected after token <i>n</i> .
Action	Correct error.

10-167 Literal or variable expected.

Text	Literal or variable expected.
Explanation	A literal or variable is expected before token <i>n</i> .
Action	Correct error.

10-168 Operator or command expected.

Text	Operator or command expected.
Explanation	An operator or command is expected as token <i>n</i> .
Action	Correct error.

10-169 Operator not allowed with the IFNOT command.

Text	Operator not allowed with the IFNOT command.
Explanation	An operator is not allowed with the IFNOT command. See the Entire Connection documentation for information on the command IFNOT.
Action	Correct error.

10-170 PCFILE number expected after SET PCFILE.

Text	PCFILE number expected after SET PCFILE.
Explanation	A PCFILE number is expected after SET PCFILE. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-172 DOWN or UP expected as next token.

Text	DOWN or UP expected as next token.
Explanation	The keyword DOWN or UP is expected after SET PCFILE <i>fnr</i> . See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-173 DOWN or UP expected as next token.

Text	DOWN or UP expected as next token.
Explanation	The keyword DOWN or UP is expected after SET PCFILE <i>fnr</i> . See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-174 DATA or REPORT expected as next token.

Text	DATA or REPORT expected as next token.
Explanation	The keyword DATA or REPORT is expected as next token in the SET PCFILE command. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-175 DATA or REPORT expected as next token.

Text	DATA or REPORT expected as next token.
Explanation	The keyword DATA or REPORT is expected as next token in the SET PCFILE command. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-176 DATA or REPORT expected as next token.

Text	DATA or REPORT expected as next token.
Explanation	The keyword DATA or REPORT is expected as next token in the SET PCFILE command. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-178 File name expected as next token.

Text	File name expected as next token.
Explanation	A PC file name is expected as next token in the SET PCFILE command. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-179 Invalid token in SET PCFILE command.

Text	Invalid token in SET PCFILE command.
Explanation	An additional token was specified in the SET PCFILE command. No tokens are allowed behind the PCFILE parameter. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-180 *SCREEN format required.

Text	*SCREEN format required.
Explanation	To use the *SCREEN variable in a SET command, the full *SCREEN format must be specified; for example <code>*SCREEN row col len</code> .
Action	Correct error.

10-181 *SCREEN format syntax error.

Text	*SCREEN format syntax error.
Explanation	The *SCREEN format is <code>*SCREEN row col len</code> . You can use an integer value, a local variable or a global variable for <code>row</code> , <code>col</code> and <code>len</code> .
Action	Correct error.

10-182 Too many tokens in SET PCFILE command.

Text	Too many tokens in SET PCFILE command.
Explanation	An additional token was specified in the SET PCFILE command. No tokens are allowed behind the PCFILE parameter. See the Entire Connection documentation for information on the command SET PCFILE.
Action	Correct error.

10-190 Global or local variable expected.

Text	Global or local variable expected.
Explanation	A global or local variable is expected as parameter 1 in the INPUT command. See the Entire Connection documentation for information on the command INPUT.
Action	Correct error.

10-191 Integer for length expected.

Text	Integer for length expected.
Explanation	An integer length value is expected as parameter 2 in the INPUT command. See the Entire Connection documentation for information on the command INPUT.
Action	Correct error.

10-193 Parameter 3 or 4 in INPUT command not a literal or variable.

Text	Parameter 3 or 4 in INPUT command not a literal or variable.
Explanation	A literal or variable is expected as parameter 3 and 4 in the INPUT command. See the Entire Connection documentation for information on the command INPUT.
Action	Correct error.

10-194 Too many parameters in INPUT command.

Text	Too many parameters in INPUT command.
Explanation	There are too many parameters in the INPUT command. See the Entire Connection documentation for information on the command INPUT.
Action	Correct error.

10-311 Too many operands.

Text	Too many operands.
Explanation	There are too many operands in the command. Check the syntax for the command used. See the Entire Connection documentation for information on the commands.
Action	Correct error.

10-312 Incomplete syntax.

Text	Incomplete syntax.
Explanation	Parameters or operands are missing. Check the syntax for the command used. See the Entire Connection documentation for information on the commands.
Action	Correct error.

11-003 Invalid BAUDRATE value.

Text	Invalid BAUDRATE value.
Explanation	The value given for the system variable BAUDRATE is not valid. Valid values are 300, 1200, 2400, 4800, 9600, 14400, 19200, 28800, 38400, 57600, 115200.
Action	Correct error.

11-004 Invalid BREAKMS value.

Text	Invalid BREAKMS value.
Explanation	The value given for the system variable BREAKMS is not valid. Valid values are 1 - 1000.
Action	Correct error.

11-005 Invalid COMMPORT value.

Text	Invalid COMMPORT value.
Explanation	The value given for the system variable COMMPORT is not valid. Valid values are 1 - 4.
Action	Correct error.

11-006 Invalid DATABITS value.

Text	Invalid DATABITS value.
Explanation	The value given for the system variable DATABITS is not valid. Valid values are 7 and 8.
Action	Correct error.

11-007 Invalid STOPBITS value.

Text	Invalid STOPBITS value.
Explanation	The value given for the system variable STOPBITS is not valid. Valid values are 1 and 2.
Action	Correct error.

11-008 Invalid UPLDELAY value.

Text	Invalid UPLDELAY value.
Explanation	The value given for the system variable UPLDELAY is not valid. Valid values are 0 - 3200.
Action	Correct error.

11-009 Invalid UPLPSIZE value.

Text	Invalid UPLPSIZE value.
Explanation	The value given for the system variable UPLPSIZE is not valid. Valid values are 1 - 1920. Note: this System variable is deprecated with PCC453.
Action	Correct error.

11-010 Invalid CURSOR value.

Text	Invalid CURSOR value.
Explanation	The value given for the system variable CURSOR is not valid. Valid values are 0 - 4.
Action	Correct error.

11-016 Invalid ECHO value.

Text	Invalid ECHO value.
Explanation	The value given for the system variable ECHO is not valid. Valid values are 0 - 100.
Action	Correct error.

11-017 Invalid RESPONSE value.

Text	Invalid RESPONSE value.
Explanation	The value given for the system variable RESPONSE is not valid. Valid values are 1 - 2440.
Action	Correct error.

11-018 Invalid AUTOLOCK value.

Text	Invalid AUTOLOCK value.
Explanation	The value given for the system variable AUTOLOCK is not valid. Valid values are 0 - 1440.
Action	Correct error.

11-050 Internal error in a local variable.

Text	Internal error in a local variable.
Explanation	There was a problem while processing a local variable.
Action	If the error persists, contact your local our support.

11-051 Integer value is required.

Text	Integer value is required.
Explanation	The variable used in this command must contain an integer value between 0 - 32767.
Action	Check variable usage and correct error.

11-052 Invalid parity value in the variable.

Text	Invalid parity value in the variable.
Explanation	The variable used in this command must contain a valid parity value. Valid values are 1 and 2.
Action	Check variable usage and correct error.

11-053 Binary keyword required after system variable.

Text	Binary keyword required after system variable.
Explanation	The value in the variable used to set the system variable must be a binary keyword such as ON or OFF.
Action	Check variable usage and correct error.

11-082 Invalid *SCREEN format.

Text	Invalid *SCREEN format.
Explanation	The values in the variables for the *SCREEN format are not valid.
Action	Check variable usage and correct error.

12-002 File does not exist.

Text	File does not exist.
Explanation	A "file not found" or "file read" error occurred for file <i>file-name</i> .
Action	Check whether the file exists.

12-003 Procedure aborted by user.

Text	Procedure aborted by user.
Explanation	The procedure was aborted by the user. The command where it was aborted is in line <i>number</i> of the procedure file.
Action	No action required.

12-004 Internal error while parsing the procedure file.

Text	Internal error while parsing the procedure file.
Explanation	An error occurred while parsing the procedure file. The internal memory was exceeded.
Action	If the error persists, contact your local our support.

12-005 Internal nest limit exceeded.

Text	Internal nest limit exceeded.
Explanation	The procedure was terminated because the internal nest limit was exceeded. You are only allowed to nest up to 7 procedure files.
Action	Reduce the number of nested procedure calls.

12-006 Host system not responding.

Text	Host system not responding.
Explanation	The procedure was terminated because the host system did not respond in the configured response time.
Action	Check the host connection. Use the Entire Connection Configuration Manager (Session Properties, Procedure dialog) to check the response time setting for the session.

12-007 Invalid procedure file. Lines too long or binary data found.

Text	Invalid procedure file. Lines too long or binary data found.
Explanation	An error occurred while parsing the procedure file. Binary data were found in a line, or a line which is too long was found. The maximum length of a procedure file line is 192 characters.
Action	Correct error.

12-008 SET TEKEY command cannot be completed.

Text	SET TEKEY command cannot be completed.
Explanation	The SET TEKEY command in the procedure file cannot be completed. You must first open a session.
Action	Open a session and retry.

12-011 Duplicate tag in procedure file.

Text	Duplicate tag in procedure file.
Explanation	There is more than one tag with the same label in the procedure file.
Action	Correct error.

12-012 LOOPCNT exceeded.

Text	LOOPCNT exceeded.
Explanation	The procedure terminated because the configured loop count was exceeded. The loop count is set in the Entire Connection Configuration Manager (User Properties, Procedure dialog).
Action	Correct procedure file or increase loop count value.

12-013 Tag not found.

Text	Tag not found.
Explanation	The tag <i>tag-label</i> was not found in the procedure file.
Action	Correct error.

12-015 DOS task not allowed.

Text	DOS task not allowed.
Explanation	Procedure terminated when trying to execute a DOS task. In your user properties, DOS tasks are marked to be not allowed for you. The property to disallow DOS tasks is no longer supported since version 4 of Entire Connection. This error can only occur if you merged a version 3 share file containing tasks which use this property.
Action	Delete and then re-create the user properties with the current version of the Entire Connection Configuration Manager.

12-016 DOS commands not allowed.

Text	DOS commands not allowed.
Explanation	Procedure terminated when trying to execute a DOS command. In your user properties, DOS commands are marked to be not allowed for you. The property to disallow DOS commands is no longer supported since version 4 of Entire Connection. This error can only occur if you merged a version 3 share file containing tasks which use this property.
Action	Delete and then re-create the user properties with the current version of the Entire Connection Configuration Manager.

12-017 Too many nested PERFORM commands.

Text	Too many nested PERFORM commands.
Explanation	Procedure terminated because there are too many nested PERFORM commands. You may only nest 8 PERFORM commands.
Action	Correct error.

12-018 No active PERFORM command to which to return.

Text	No active PERFORM command to which to return.
Explanation	Procedure terminated because a RETURN was to be executed but there is no active PERFORM command to which to return.
Action	Correct error.

12-019 Cannot schedule more than 32 tasks in a procedure file.

Text	Cannot schedule more than 32 tasks in a procedure file.
Explanation	Procedure terminated because you tried to schedule more than 32 tasks. You can schedule up to 32 tasks in a procedure file.
Action	Correct error.

12-060 Internal buffer overflow error.

Text	Internal buffer overflow error.
Explanation	An internal buffer overflow error occurred in line <i>n</i> . The buffer size was exceeded.
Action	If the error persists, report the error to your local our support.

12-082 Invalid *SCREEN format.

Text	Invalid *SCREEN format.
Explanation	A runtime error occurred in line <i>n</i> because the *SCREEN parameters built from variables are not valid. See the Entire Connection documentation for information on the command IF for usage of the *SCREEN variable.
Action	Correct error.

12-101 Nested TYPE command error.

Text	Nested TYPE command error.
Explanation	A runtime error occurred in a nested TYPE command. After the first TYPE, only TYPE commands are allowed.
Action	Correct error.

12-802 Command REC_BUFF not valid for VT100 communication method.

Text	Command REC_BUFF not valid for VT100 communication method.
Explanation	The command REC_BUFF cannot be used in a VT100 host session.
Action	Correct error.

12-804 Command HOLD not valid for the communication method.

Text	Command HOLD not valid for the communication method.
Explanation	The command HOLD is only valid in a VTxxx session. It is not supported in your current session.
Action	Correct error.

12-805 Command SESSION not valid for the communication method.

Text	Command SESSION not valid for the communication method.
Explanation	The command SESSION is only valid in an HLLAPI session. It is not supported in your current session.
Action	Correct error.

12-806 No more HLLAPI sessions available.

Text	No more HLLAPI sessions available.
Explanation	The command SESSION failed - no more HLLAPI sessions are available.
Action	Correct error.

12-807 Command not allowed in a DOWNLOAD COMMAND SYNC statement.

Text	Command not allowed in a DOWNLOAD COMMAND SYNC statement.
Explanation	Several commands cannot be used in a DOWNLOAD COMMAND SYNC statement sent from Natural. See chapter Terminal Emulation, Data Transfer, DOWNLOAD Statement in the Entire Connection documentation.
Action	Correct error.

12-808 Invalid command in DOWNLOAD COMMAND SYNC statement.

Text	Invalid command in DOWNLOAD COMMAND SYNC statement.
Explanation	A command was sent from Natural in a DOWNLOAD COMMAND SYNC statement while another command or procedure file was still being processed. Only the command SET PCFILE can be used in this situation.
Action	Correct error.

12-930 Invalid value for MINUTE parameter.

Text	Invalid value for MINUTE parameter.
Explanation	A runtime error occurred because the value for the MINUTE parameter taken from a variable was greater than 1440.
Action	Check the procedure file logic and correct the error.

12-931 Message text too long.

Text	Message text too long.
Explanation	The message text given for the WAIT or WAITM command is too long. The message text must be less than 184 characters long.
Action	Correct error.

12-932 Invalid value for MINUTE.

Text	Invalid value for MINUTE.
Explanation	A runtime error occurred because the value for the MINUTE parameter taken from a variable was not valid. The value for the MINUTES parameter must be between 1 and 1440.
Action	Correct error.

12-933 Invalid value detected for date or time.

Text	Invalid value detected for date or time.
Explanation	An invalid value for date or time was detected in the ELAPSETIME command.
Action	Correct error.

12-934 Invalid value detected for date or time.

Text	Invalid value detected for date or time.
Explanation	An invalid value for date or time was detected in the ELAPSETIME or WAITUNTIL command.
Action	Correct error.

12-940 Invalid file number.

Text	Invalid file number.
Explanation	A runtime error occurred because the file number in the SET PCFILE command is not valid. The file number must be an integer value in the range 1 - 32.
Action	Check the procedure file logic and correct the error.

12-941 Invalid file name.

Text	Invalid file name.
Explanation	A runtime error occurred because the file name in the SET PCFILE command is not valid. The file name must not contain keywords such as LPT1 or wildcard characters.
Action	Correct error.

12-942 File name too long.

Text	File name too long.
Explanation	A runtime error occurred because the file name in the SET PCFILE command is too long. Entire Connection file names can only be 268 characters long.
Action	Correct error.

12-943 Invalid file name.

Text	Invalid file name.
Explanation	A runtime error occurred because the file name in the SET PCFILE command is not valid. The special file name ~~RANDOM is only valid for downloads.
Action	Correct error.

12-945 Internal error in SET PCFILE - No more tables.

Text	Internal error in SET PCFILE - No more tables.
Explanation	An internal error occurred when processing the SET PCFILE command - no more tables are available.
Action	If the error persists, report the error to your local our support.

12-946 Data missing in SET PCFILE.

Text	Data missing in SET PCFILE.
Explanation	A runtime error occurred in the SET PCFILE x DOWN CONVERT command - not enough data specified. Required data are stylesheet type and stylesheet name.
Action	Correct error.

12-947 Error in SET PCFILE: PCFILE length exceeded due to usage of environment variable.

Text	Error in SET PCFILE: PCFILE length exceeded due to usage of environment variable.
Explanation	A runtime error occurred in the SET PCFILE command - the PCFILE length was exceeded due to usage of environment variable. By including the value of the environment variable, the maximum file name length of 512 characters was exceeded.
Action	Check if you can circumvent the problem by using a different length path or file name.

12-950 Recursive key definition.

Text	Recursive key definition.
Explanation	A runtime error occurred in the SET TEKEY command. A recursive key definition was detected.
Action	Correct error.

12-951 Integer value required.

Text	Integer value required.
Explanation	A runtime error occurred in the SET command - expected integer value here. Integer values must be between 0 - 32767.
Action	Correct error.

12-952 Invalid use of local variable.

Text	Invalid use of local variable.
Explanation	Local variables cannot be used on the command line. Local variables are only valid when used in a procedure file.
Action	Correct error.

12-960 Invalid length.

Text	Invalid length.
Explanation	A runtime error occurred in the INPUT or READ command. An invalid length was detected. The length in the INPUT command must be between 1 and 72. The length in the READ command must be less than 255.
Action	Correct error.

12-961 Message missing in INPUT command.

Text	Message missing in INPUT command.
Explanation	At least one message must be specified in the INPUT command.
Action	Correct error.

12-970 DOSDIR not started.

Text	DOSDIR not started.
Explanation	A runtime error occurred in the DOSDIR command. You must first start DOSDIR with a file parameter. Only subsequent DOSDIR commands can then be without parameters.
Action	Correct error.

12-971 Invalid option in DOSDIR command.

Text	Invalid option in DOSDIR command.
Explanation	A runtime error occurred in the DOSDIR command - an invalid option was detected. Valid file attribute option values are A, D, H, R, S.
Action	Correct error.

12-972 Invalid PRINTOPTION parameter.

Text	Invalid PRINTOPTION parameter.
Explanation	A runtime error occurred in the SET PRINTOPTION command - an invalid parameter was detected. See the Entire Connection documentation for all valid parameters of the PRINTOPTION system variable.
Action	Correct error.

12-973 No current directory available for POPDIR.

Text	No current directory available for POPDIR.
Explanation	A runtime error occurred in the POPDIR command. You must use the PUSHDIR command before you can use the POPDIR command.
Action	Correct error.

12-974 Invalid PUSHDIR command.

Text	Invalid PUSHDIR command.
Explanation	A runtime error occurred in the PUSHDIR command. You are not allowed to save more than 8 directories with the PUSHDIR command.
Action	Correct error.

12-975 DOSDIR not started - not allowed to PUSHDIR.

Text	DOSDIR not started - not allowed to PUSHDIR.
Explanation	A runtime error occurred in the PUSHDIR command. You must use the DOSDIR command before you can use the PUSHDIR command.
Action	Correct error.

12-980 Invalid file number.

Text	Invalid file number.
Explanation	A runtime error occurred in the OPEN, READ or WRITE command - invalid file number detected. The file number in the OPEN, READ or WRITE command must be 1, 2, 3 or 4.
Action	Correct error.

12-983 Invalid file name in OPEN command.

Text	Invalid file name in OPEN command.
Explanation	A runtime error occurred in the OPEN command - invalid file name detected. AUX and CON are not valid file names.
Action	Correct error.

12-984 File number in use.

Text	File number in use.
Explanation	A runtime error occurred in the OPEN command - there is an open file for the file number. You forgot to close the file before trying to use the file number again.
Action	Correct error.

12-985 File already open.

Text	File already open.
Explanation	A runtime error occurred in the OPEN command - a file with the name <i>name</i> is already open. You may not open two files with the same name.
Action	Correct error.

12-986 File not opened for output.

Text	File not opened for output.
Explanation	A runtime error occurred in the WRITE command - file not opened for output. The file has been opened for input - writes are not allowed.
Action	Correct error.

12-987 File not opened for input.

Text	File not opened for input.
Explanation	A runtime error occurred in the READ command - file not opened for input. This file has been opened for output - reads are not allowed.
Action	Correct error.

12-988 File number not opened.

Text	File number not opened.
Explanation	A runtime error occurred in the READ, WRITE or CLOSE command - file not opened. Before you can READ, WRITE or CLOSE a file, it must first be opened.
Action	Correct error.

12-989 Error in WRITE command.

Text	Error in WRITE command.
Explanation	A runtime error occurred in the WRITE command - error while writing to disk.
Action	Check whether the disk is full and whether you have privileges to write to the specified location.

12-990 Error in READ command.

Text	Error in READ command.
Explanation	A runtime error occurred in the READ command - error while reading from disk.
Action	Check whether you have privileges to read from the specified location. Check your hard disk.

12-991 Error in OPEN command.

Text	Error in OPEN command.
Explanation	A runtime error occurred in the OPEN command - the file could not be opened.
Action	Check whether you have privileges for the specified location. Check your hard disk.

12-992 Error in CLOSE command.

Text	Error in CLOSE command.
Explanation	A runtime error occurred in the CLOSE command - the file could not be closed.
Action	Check your hard disk.

12-994 TE task or EMULATE failed.

Text	TE task or EMULATE failed.
Explanation	A runtime error occurred in the EMULATE command or in the TE task - no default session specified. You must specify a default session in the user properties.
Action	Use the Entire Connection Configuration Manager to specify a default session in your user properties.

12-995 Could not open a session.

Text	Could not open a session.
Explanation	A runtime error occurred in a command which requires an open session. The command tried to open the default session. You must specify a default session in the user properties or first open a session using the CONNECT command.
Action	Correct error.

12-996 Host session lost.

Text	Host session lost.
Explanation	A runtime error occurred in the WAITM command - host session lost. The host session was closed while the WAITM command was active.
Action	Check your host connection.

14-020 Unable to open SSL connection. SSL_CTX_new failed.

Text	Unable to open SSL connection. SSL_CTX_new failed.
Explanation	The SSL connection could not be opened because the function SSL_CTX_new failed.
Action	Check your SSL installation and configuration. If the error persists, report the error to your local our support.

14-021 Unable to open SSL connection. SSL_new failed.

Text	Unable to open SSL connection. SSL_new failed.
Explanation	The SSL connection could not be opened because the function SSL_new failed.
Action	Check your SSL installation and configuration. If the error persists, report the error to your local our support.

14-022 Unable to open SSL connection. SSL_connect failed.

Text	Unable to open SSL connection. SSL_connect failed.
Explanation	The SSL connection could not be opened because the function SSL_connect failed. Error-code: <i>error</i> , IP address: <i>IP-address</i> , Port: <i>port</i> .
Action	Check the TCP/IP address and port in the SSL configuration. If the error persists, report the error to your local our support.

14-023 SSL_write failed.

Text	SSL_write failed.
Explanation	An error occurred while sending data to the host. Error-code: <i>error</i> .
Action	Check your SSL installation and configuration. If the error persists, report the error to your local our support.

14-024 SSL_read failed.

Text	SSL_read failed.
Explanation	An error occurred while reading data from the host. Error-code: <i>error</i> .
Action	Check your SSL installation and configuration. If the error persists, report the error to your local our support.

14-026 SSL connection aborted - could not read certificate file calist.pem.

Text	SSL connection aborted - could not read certificate file calist.pem.
Explanation	The SSL connection aborted because the certificate file calist.pem could not be read.
Action	Check your SSL configuration and make sure that the file calist.pem exists and can be read.

14-027 Unable to open SSL connection. Random number generation failed.

Text	Unable to open SSL connection. Random number generation failed.
Explanation	The SSL connection could not be opened because the generation of a random number failed.
Action	Check your SSL installation and configuration. If the error persists, report the error to your local our support.

14-028 SSL connection aborted - host name mismatch.

Text	SSL connection aborted - host name mismatch.
Explanation	The host name <i>host</i> is different from the name in the certificate: <i>host</i> .
Action	Check your SSL configuration and provide a valid certificate for the selected host.

14-029 Unable to open SSL connection - could not read client certificate file.

Text	Unable to open SSL connection - could not read client certificate file.
Explanation	The SSL connection could not be opened because the client certificate file <i>certificate-file</i> could not be read.
Action	Check your SSL configuration and provide a valid client certificate.

14-030 Unable to open SSL connection - could not read client private key file.

Text	Unable to open SSL connection - could not read client private key file.
Explanation	The SSL connection could not be opened because the client private key file <i>key-file</i> could not be read.
Action	Check your SSL configuration and provide a valid client private key file.

14-031 SSL connection aborted - host name not found in the certificate.

Text	SSL connection aborted - host name not found in the certificate.
Explanation	The SSL connection aborted because the host name could not be found in the certificate.
Action	Check your SSL configuration and provide a valid certificate.

14-050 Unable to open SSH connection. libssh2 initialization failed.

Text	Unable to open SSH connection. libssh2 initialization failed.
Explanation	The SSH connection could not be opened. The SSH library could not be initialized and returned an error <i>error-code</i> .
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-051 Unable to open SSH connection. Could not initialize an SSH session.

Text	Unable to open SSH connection. Could not initialize an SSH session.
Explanation	The SSH connection could not be opened. The SSH session could not be initialized.
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-052 Unable to open SSH connection. Failed to establish SSH session.

Text	Unable to open SSH connection. Failed to establish SSH session.
Explanation	The SSH connection could not be opened. No SSH session could be established.
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-053 Unable to open SSH connection. "Password" authentication failed.

Text	Unable to open SSH connection. "Password" authentication failed.
Explanation	The SSH connection could not be opened. The supplied values for user ID and password are not valid.
Action	Check and correct.

14-054 Unable to open SSH connection. No supported authentication methods found.

Text	Unable to open SSH connection. No supported authentication methods found.
Explanation	The SSH connection could not be opened. The host did not return an authentication method supported by Entire Connection.
Action	Check your host SSH installation and configuration. If the error persists, report the error to your local our support.

14-055 Unable to open SSH connection. "Keyboard-interactive" authentication method failed.

Text	Unable to open SSH connection. "Keyboard-interactive" authentication method failed.
Explanation	The SSH connection could not be opened. The supplied values for user ID and password are not valid. The host returned an error <i>error-code</i> .
Action	Check and correct.

14-056 Unable to open SSH connection. No authentication schemes received from host.

Text	Unable to open SSH connection. No authentication schemes received from host.
Explanation	The SSH connection could not be opened. The host did not return any authentication schemes.
Action	Check your host SSH installation and configuration. If the error persists, report the error to your local our support.

14-057 Unable to open SSH connection. Unable to open a session.

Text	Unable to open SSH connection. Unable to open a session.
Explanation	The SSH connection could not be opened. The SSH session could not be opened.
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-058 Unable to open SSH connection. Failed to request pty.

Text	Unable to open SSH connection. Failed to request pty.
Explanation	The SSH connection could not be opened. The function "request pty" returned an error <i>error-code</i> .
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-059 Unable to open SSH connection. Unable to request shell on allocated pty.

Text	Unable to open SSH connection. Unable to request shell on allocated pty.
Explanation	The SSH connection could not be opened. The request of a shell on the allocated pty failed.
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-060 Unable to open SSH connection. Too many authentication failures.

Text	Unable to open SSH connection. Too many authentication failures.
Explanation	The SSH connection could not be opened. There were too many authentication failures for the user <i>user-name</i> .
Action	Check the supplied user credentials and try again. Note that you cannot change the user ID if you received an authentication error. In this case, you have to close and re-open the session and enter the correct user ID.

14-061 Unable to open SSH connection. Error in "keyboard-interactive" authentication.

Text	Unable to open SSH connection. Error in "keyboard-interactive" authentication.
Explanation	The SSH connection could not be opened. The authentication by keyboard-interactive returned an error <i>error-code</i> .
Action	Check the supplied user credentials and try again.

14-062 Opening of SSH connection canceled by user.

Text	Opening of SSH connection canceled by user.
Explanation	The SSH connection was not be opened because the user pressed the Cancel button.
Action	No action required.

14-063 Unable to open SSH connection. Internal error.

Text	Unable to open SSH connection. Internal error.
Explanation	The SSH connection could not be opened. An internal error occurred because a server interface was not available.
Action	Check your Entire Connection installation and configuration. If the error persists, report the error to your local our support.

14-064 Unable to open SSH connection. "Publickey" authentication failed.

Text	Unable to open SSH connection. "Publickey" authentication failed.
Explanation	The SSH connection could not be opened. The authentication by public key failed.
Action	Check the supplied user credentials and the public and private keys and try again. Also check the host configuration for the "publickey" authentication.

14-065 SSH_write failed.

Text	SSH_write failed.
Explanation	Error in the host communication. The data entered could not be sent to the host. The function SSH_write failed with error <i>error-code</i> .
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-066 The SSH key file must be located in the folder %LOCALAPPDATA%\Software AG\Entire Connection\certs.

Text	The SSH key file must be located in the folder %LOCALAPPDATA%\Software AG\Entire Connection\certs.
Explanation	The private key file for the "publickey" authentication must be located in the folder %LOCALAPPDATA%\Software AG\Entire Connection\certs.
Action	Check and correct.

14-067 SSH key file name too long.

Text	SSH key file name too long.
Explanation	The file name of the private key file is too long. The maximum length is 47 characters.
Action	Check and correct.

14-080 Fatal communication error.

Text	Fatal communication error.
Explanation	Error in the host communication. A timeout occurred in CallMethodToThread. Caller: <i>name</i> .
Action	Check your SSH installation and configuration. If the error persists, report the error to your local our support.

14-102 SSL connection aborted. Unable to get issuer certificate.

Text	SSL connection aborted. Unable to get issuer certificate.
Explanation	The SSL connection aborted because the issuer certificate could not be found. This error occurs if the issuer certificate of an untrusted certificate cannot be found.
Action	Check your SSL configuration and provide a valid issuer certificate.

14-103 SSL connection aborted - unable to get certificate CRL.

Text	SSL connection aborted - unable to get certificate CRL.
Explanation	The SSL connection aborted because the CRL of a certificate could not be found.
Action	Check your SSL configuration and provide a valid certificate.

14-104 SSL connection aborted. Unable to decrypt certificate's signature.

Text	SSL connection aborted. Unable to decrypt certificate's signature.
Explanation	The SSL connection aborted because the signature could not be decrypted. This means that the actual signature value could not be determined rather than it not matching the expected value. This is only meaningful for RSA keys.
Action	Check your SSL configuration and provide a valid certificate.

14-105 SSL connection aborted. Unable to decrypt CRL's signature.

Text	SSL connection aborted. Unable to decrypt CRL's signature.
Explanation	The SSL connection aborted because the CRL signature could not be decrypted. This means that the actual signature value could not be determined rather than it not matching the expected value.
Action	Check your SSL configuration and provide a valid certificate.

14-106 SSL connection aborted. Unable to decode issuer public key.

Text	SSL connection aborted. Unable to decode issuer public key.
Explanation	The SSL connection aborted because the public key in the certificate SubjectPublicKeyInfo could not be read.
Action	Check your SSL configuration and provide a valid certificate.

14-107 SSL connection aborted. Certificate signature failure.

Text	SSL connection aborted. Certificate signature failure.
Explanation	The SSL connection aborted because the signature of the certificate is invalid.
Action	Check your SSL configuration and provide a valid certificate.

14-108 SSL connection aborted. CRL signature failure.

Text	SSL connection aborted. CRL signature failure.
Explanation	The SSL connection aborted because the CRL signature of the certificate is invalid.
Action	Check your SSL configuration and provide a valid certificate.

14-109 SSL connection aborted. Certificate is not yet valid.

Text	SSL connection aborted. Certificate is not yet valid.
Explanation	The SSL connection aborted because the certificate is not yet valid. The notBefore date is after the current time.
Action	Check your SSL configuration and provide a valid certificate.

14-110 SSL connection aborted. Certificate has expired.

Text	SSL connection aborted. Certificate has expired.
Explanation	The SSL connection aborted because the certificate has expired. The notAfter date is before the current time.
Action	Check your SSL configuration and provide a valid certificate.

14-111 SSL connection aborted. CRL is not yet valid.

Text	SSL connection aborted. CRL is not yet valid.
Explanation	The SSL connection aborted because the certificate is not yet valid. The CRL is not yet valid.
Action	Check your SSL configuration and provide a valid certificate.

14-112 SSL connection aborted. CRL has expired.

Text	SSL connection aborted. CRL has expired.
Explanation	The SSL connection aborted because the certificate is not valid. The CRL has expired.
Action	Check your SSL configuration and provide a valid certificate.

14-113 SSL connection aborted. Format error in certificate's notBefore field.

Text	SSL connection aborted. Format error in certificate's notBefore field.
Explanation	The SSL connection aborted because the certificate is not valid. The notBefore field of the certificate contains an invalid time.
Action	Check your SSL configuration and provide a valid certificate.

14-114 SSL connection aborted. Format error in certificate's notAfter field.

Text	SSL connection aborted. Format error in certificate's notAfter field.
Explanation	The SSL connection aborted because the certificate is not valid. The notAfter field of the contains an invalid time.
Action	Check your SSL configuration and provide a valid certificate.

14-115 SSL connection aborted. Format error in CRL's lastUpdate field.

Text	SSL connection aborted. Format error in CRL's lastUpdate field.
Explanation	The SSL connection aborted because the certificate is not valid. The lastUpdate field of the CRL contains an invalid time.
Action	Check your SSL configuration and provide a valid certificate.

14-116 SSL connection aborted. Format error in CRL's nextUpdate field.

Text	SSL connection aborted. Format error in CRL's nextUpdate field.
Explanation	The SSL connection aborted because the certificate is not valid. The nextUpdate field of the CRL contains an invalid time.
Action	Check your SSL configuration and provide a valid certificate.

14-117 SSL connection aborted. Out of memory.

Text	SSL connection aborted. Out of memory.
Explanation	The SSL connection aborted because an error occurred while trying to allocate memory. This should never happen.
Action	Check your PC hardware.

14-118 SSL connection aborted. Untrusted self-signed certificate.

Text	SSL connection aborted. Untrusted self-signed certificate.
Explanation	The SSL connection aborted because the certificate is not valid. The passed certificate is self-signed and the same certificate cannot be found in the list of trusted certificates.
Action	Check your SSL configuration and provide a valid certificate.

14-119 SSL connection aborted. Self signed-certificate in certificate chain.

Text	SSL connection aborted. Self signed-certificate in certificate chain.
Explanation	The SSL connection aborted because the certificate chain is not valid. The certificate chain could be built up using the untrusted certificates but the root could not be found locally.
Action	Check your SSL configuration and provide a valid certificate chain.

14-120 SSL connection aborted. Unable to get local issuer certificate.

Text	SSL connection aborted. Unable to get local issuer certificate.
Explanation	The issuer certificate of a locally looked up certificate could not be found. This normally means that the list of trusted certificates is not complete.
Action	Check your SSL configuration and provide a valid issuer certificate.

14-121 SSL connection aborted. Unable to verify the first certificate.

Text	SSL connection aborted. Unable to verify the first certificate.
Explanation	The SSL connection aborted because the first certificate could not be verified. No signatures could be verified because the chain contains only one certificate and it is not self-signed.
Action	Check your SSL configuration and provide a valid certificate.

14-122 SSL connection aborted. Certificate chain too long.

Text	SSL connection aborted. Certificate chain too long.
Explanation	The SSL connection aborted because the certificate chain is too long. The certificate chain length is greater than the supplied maximum depth.
Action	Check your SSL configuration and provide a valid certificate.

14-123 SSL connection aborted. Certificate revoked.

Text	SSL connection aborted. Certificate revoked.
Explanation	The SSL connection aborted because the certificate has been revoked.
Action	Check your SSL configuration and provide a valid certificate.

14-124 SSL connection aborted. Invalid CA certificate.

Text	SSL connection aborted. Invalid CA certificate.
Explanation	The SSL connection aborted because the CA certificate is not valid. The CA certificate is invalid. Either it is not a CA certificate or its extensions are not consistent with the supplied purpose.
Action	Check your SSL configuration and provide a valid CA certificate.

14-125 SSL connection aborted. Path length constraint exceeded.

Text	SSL connection aborted. Path length constraint exceeded.
Explanation	The SSL connection aborted because the certificate is not valid. The basicConstraints path length parameter has been exceeded.
Action	Check your SSL configuration and provide a valid certificate.

14-126 SSL connection aborted. Unsupported certificate purpose.

Text	SSL connection aborted. Unsupported certificate purpose.
Explanation	The SSL connection aborted because the certificate is not valid. The supplied certificate cannot be used for the specified purpose.
Action	Check your SSL configuration and provide a valid certificate.

14-127 SSL connection aborted. Certificate not trusted.

Text	SSL connection aborted. Certificate not trusted.
Explanation	The SSL connection aborted because the certificate is not valid. The root CA is not marked as trusted for the specified purpose.
Action	Check your SSL configuration and provide a valid CA certificate.

14-128 SSL connection aborted. Certificate rejected.

Text	SSL connection aborted. Certificate rejected.
Explanation	The SSL connection aborted because the certificate is not valid. The root CA is marked to reject the specified purpose.
Action	Check your SSL configuration and provide a valid certificate.

14-129 SSL connection aborted. Subject issuer mismatch.

Text	SSL connection aborted. Subject issuer mismatch.
Explanation	The SSL connection aborted because the certificate is not valid. The current candidate issuer certificate was rejected because its subject name did not match the issuer name of the current certificate. The verification is done when the -issuer_checks option is set.
Action	Check your SSL configuration and provide a valid certificate.

14-130 SSL connection aborted. Authority and subject key identifier mismatch.

Text	SSL connection aborted. Authority and subject key identifier mismatch.
Explanation	The SSL connection aborted because the certificate is not valid. The current candidate issuer certificate was rejected because its subject key identifier was present and did not match the authority key identifier of the current certificate. The verification is done when the -issuer_checks option is set.
Action	Check your SSL configuration and provide a valid certificate.

14-131 SSL connection aborted. Authority and issuer serial number mismatch.

Text	SSL connection aborted. Authority and issuer serial number mismatch.
Explanation	The SSL connection aborted because the certificate is not valid. The current candidate issuer certificate was rejected because its issuer name and serial number was present and did not match the authority key identifier of the current certificate. The verification is done when the -issuer_checks option is set.
Action	Check your SSL configuration and provide a valid certificate.

14-132 SSL connection aborted. Key usage does not include certificate signing.

Text	SSL connection aborted. Key usage does not include certificate signing.
Explanation	The SSL connection aborted because the certificate is not valid. The current candidate issuer certificate was rejected because its keyUsage extension does not permit certificate signing.
Action	Check your SSL configuration and provide a valid certificate.

14-150 SSL connection aborted. Application verification failure.

Text	SSL connection aborted. Application verification failure.
Explanation	The SSL connection aborted because of an application-specific error. This should never happen.
Action	Check your SSL installation and configuration. If the error persists, report the error to your local our support.

15-000 Initialization of the selected communication method timed out.

Text	Initialization of the selected communication method timed out.
Explanation	Failed to open session because there was no answer from the host within the specified maximum response time.
Action	Check your host connection and the session properties. Try to increase the "Open session timeout" parameter on the Terminal page of the session properties.

15-001 Cannot execute procedure file at this time.

Text	Cannot execute procedure file at this time.
Explanation	The procedure file cannot be executed at this time. You are already nested in terminal emulation. This happens, for example, if a host command was executed from a procedure file, and the host response contains a command to start another procedure file.
Action	Check and correct your procedure file logic.

15-002 Unable to disconnect - communication in progress.

Text	Unable to disconnect - communication in progress.
Explanation	The DISCONNECT command cannot be executed because the current communication process has to finish first.
Action	Try again later.

15-003 Unable to connect - communication in progress.

Text	Unable to connect - communication in progress.
Explanation	The CONNECT command cannot be executed because the current communication process has to finish first.
Action	Try disconnecting first.

15-004 Connect request failed - session not found.

Text	Connect request failed - session not found.
Explanation	The session could not be opened because a session with the specified name could not be found in the share file for your user ID.
Action	Check whether the session exists in the share file. Check your procedure file.

15-005 You are not allowed to enter terminal emulation at this time.

Text	You are not allowed to enter terminal emulation at this time.
Explanation	You are not allowed to enter terminal emulation at this time because you are already in terminal emulation.
Action	End/exit the task you are currently running. Check your procedure file logic.

15-006 Error loading communication DLL.

Text	Error loading communication DLL.
Explanation	Failed to open session because there was an error <i>error-number</i> while loading the communication DLL <i>DLL-name</i> .
Action	Check your Entire Connection installation. If the error persists, report the error to your local our support.

15-008 Start of the communication thread failed.

Text	Start of the communication thread failed.
Explanation	Failed to open session because the communication thread could not be started.
Action	Check your PC system for unusual load. If the error persists, report the error to your local our support.

15-011 Error creating translation table.

Text	Error creating translation table.
Explanation	Failed to open session. The translation table for the code pages <i>code-pages</i> could not be created.
Action	Check your Entire Connection installation. If the error persists, report the error to your local our support.

15-012 Error loading WinSocket interface DLL.

Text	Error loading WinSocket interface DLL.
Explanation	Failed to open session because the WinSocket interface could not be loaded. The function <i>function-name</i> could not be found in WS2_32.DLL.
Action	Check your PC system and the WinSocket installation. If the error persists, report the error to your local our support.

15-029 BS2000/975x communications initialization failed.

Text	BS2000/975x communications initialization failed.
Explanation	Failed to open session. The BS2000/975x communication could not be started. The initial request could not be started.
Action	Check the BS2000 host connection. If the error persists, report the error to your local our support.

15-041 Error reading translation table from share file.

Text	Error reading translation table from share file.
Explanation	Failed to open session. The translation table <i>table-name</i> could not be read from the share file.
Action	Check the national settings for the session. If the error persists, try restoring your share file from a backup and retry.

15-042 Error returned from HLLAPI function "Query Sessions".

Text	Error returned from HLLAPI function "Query Sessions".
Explanation	Failed to open session - the HLLAPI function "Query Sessions" returned an error: <i>error-code</i> .
Action	Check your HLLAPI software installation. If the error persists, create a trace with your HLLAPI software, and report the error to your local our support.

15-043 HLLAPI function "Query Sessions" did not return any host screen sessions.

Text	HLLAPI function "Query Sessions" did not return any host screen sessions.
Explanation	Failed to open session - the HLLAPI function "Query Sessions" did not return any host screen sessions.
Action	Check and correct the session definitions in your HLLAPI software.

15-044 Error from HLLAPI function "Connect to Presentation Space".

Text	Error from HLLAPI function "Connect to Presentation Space".
Explanation	Failed to open session - the HLLAPI function "Connect to Presentation Space" returned an error: <i>error-code</i> .
Action	Check your HLLAPI software installation. If the error persists, create a trace with your HLLAPI software, and report the error to your local our support.

15-045 Error returned from HLLAPI "put_key" function.

Text	Error returned from HLLAPI "put_key" function.
Explanation	Communication error - the HLLAPI function "put_key" returned an error: <i>error-code</i> .
Action	Check your HLLAPI software installation. If the error persists, create a trace with your HLLAPI software, and report the error to your local our support.

15-046 Error returned from HLLAPI "CopyPS2String" function.

Text	Error returned from HLLAPI "CopyPS2String" function.
Explanation	Communication error - the HLLAPI function "CopyPS2String" returned an error: <i>error-code</i> .
Action	Check your HLLAPI software installation. If the error persists, create a trace with your HLLAPI software, and report the error to your local our support.

15-047 Error returned from HLLAPI "Start_Host_Notification" function.

Text	Error returned from HLLAPI "Start_Host_Notification" function.
Explanation	Communication error - the HLLAPI function "Start_Host_Notification" returned an error: <i>error-code</i> .
Action	Check your HLLAPI software installation. If the error persists, create a trace with your HLLAPI software, and report the error to your local our support.

15-048 HLLAPI DLL could not be loaded.

Text	HLLAPI DLL could not be loaded.
Explanation	Failed to open session - the HLLAPI DLL <i>DLL name</i> could not be loaded. Error: <i>error-code</i> .
Action	Make sure that software providing the HLLAPI is installed and that it is in the PATH. If the error persists, report the error to your local our support.

15-049 HLLAPI function not found.

Text	HLLAPI function not found.
Explanation	Failed to open session - the HLLAPI function <i>function-name</i> was not found in the DLL <i>DLL-name</i> .
Action	Check your HLLAPI software installation and make sure that it is in the PATH. If the error persists, report the error to your local our support.

15-054 HLLAPI session no longer connected.

Text	HLLAPI session no longer connected.
Explanation	Communication error - the HLLAPI session is no longer connected.
Action	Check your host connection.

15-055 Error returned from HLLAPI function "CopyOIA"

Text	Error returned from HLLAPI function "CopyOIA"
Explanation	Communication error - the HLLAPI function "CopyOIA" returned an error: <i>error-code</i> .
Action	Check your HLLAPI software installation.

15-056 HLLAPI is already connected to an Entire Connection terminal.

Text	HLLAPI is already connected to an Entire Connection terminal.
Explanation	Failed to open session - the HLLAPI interface is already connected to another Entire Connection terminal.
Action	Use the HLLAPI session in the other Entire Connection terminal.

15-073 Error writing to the share file.

Text	Error writing to the share file.
Explanation	An error occurred when writing to the Entire Connection share file.
Action	Check your disk space and whether you have permission to write to the location. Restore your share file from a backup and retry.

15-074 Error reading from the share file.

Text	Error reading from the share file.
Explanation	An error occurred when reading from the Entire Connection share file.
Action	Check your disk and whether you have permission to read from the location. Restore your share file from a backup and retry.

15-076 CN01 PLEASE ENTER NET COMMAND.

Text	CN01 PLEASE ENTER NET COMMAND.
Explanation	CN01 PLEASE ENTER NET COMMAND: help text for BS2000 init dialog.
Action	No action required.

15-077 CN02 ERROR IN NET COMMAND; INVALID COMMAND SYNTAX.

Text	CN02 ERROR IN NET COMMAND; INVALID COMMAND SYNTAX.
Explanation	CN02 ERROR IN NET COMMAND; INVALID COMMAND SYNTAX - error message for BS2000 init dialog.
Action	Correct the BS2000 command.

15-078 CN02 ERROR IN NET COMMAND; NO DEFAULT FOR PARTNER NAME.

Text	CN02 ERROR IN NET COMMAND; NO DEFAULT FOR PARTNER NAME.
Explanation	CN02 ERROR IN NET COMMAND; NO DEFAULT FOR PARTNER NAME - error message for BS2000 init dialog.
Action	Correct the BS2000 command.

15-079 Connection refused by the communications partner.

Text	Connection refused by the communications partner.
Explanation	Failed to open session - the connection was refused by the communications partner.
Action	Check your communication settings or contact your network administrator.

15-081 Error when processing "put_keystroke".

Text	Error when processing "put_keystroke".
Explanation	A communication error occurred in the "put_keystroke" routine.
Action	Check your host connection. Close and re-open the session and try again. If the error persists, report the error to your local our support.

15-082 Error when processing "quit".

Text	Error when processing "quit".
Explanation	A communication error occurred in the BS2000 "quit" routine.
Action	Check your host connection. Close and re-open the session and try again. If the error persists, report the error to your local our support.

15-083 Error when processing "ptast".

Text	Error when processing "ptast".
Explanation	A communication error occurred when sending a BS2000 P-key to the host.
Action	Check your host connection. Close and re-open the session and try again. If the error persists, report the error to your local our support.

15-090 CN06 REJECTED; MISSING APPLICATION NAME.

Text	CN06 REJECTED; MISSING APPLICATION NAME.
Explanation	CN06 REJECTED; MISSING APPLICATION NAME - error message for BS2000 init dialog.
Action	Correct the BS2000 command.

15-091 CN06 REJECTED; APPLICATION NAME TOO LONG.

Text	CN06 REJECTED; APPLICATION NAME TOO LONG.
Explanation	CN06 REJECTED; APPLICATION NAME TOO LONG - error message for BS2000 init dialog.
Action	Correct the BS2000 command.

15-092 CN06 REJECTED; CHECK CONNECTION PARAMETER.

Text	CN06 REJECTED; CHECK CONNECTION PARAMETER.
Explanation	CN06 REJECTED; CHECK CONNECTION PARAMETER - error message for BS2000 init dialog.
Action	Correct the BS2000 command.

15-093 CN07 DISCONNECTED; NO REASON SPECIFIED BY PARTNER.

Text	CN07 DISCONNECTED; NO REASON SPECIFIED BY PARTNER.
Explanation	CN07 DISCONNECTED; NO REASON SPECIFIED BY PARTNER - error message for BS2000 init dialog.
Action	Correct the BS2000 command.

15-100 Could not load translation table ASC2HEB.

Text	Could not load translation table ASC2HEB.
Explanation	Failed to open session - could not load translation table ASC2HEB. This translation table is required if the option "Enable right-to-left support" is set in the Session Properties, National page.
Action	Import the missing table into the share file. See Configuration Manager, Tables, Translation Tables dialog.

15-312 Unable to initialize communications from prodecure file.

Text	Unable to initialize communications from prodecure file.
Explanation	A command in a procedure file which requires a host session tried to open the default session. An error occurred while opening the session.
Action	Check the communication parameters for your default session.

15-802 Command not valid for VTxxx communication methods.

Text	Command not valid for VTxxx communication methods.
Explanation	The command REC_BUFF is not supported with the VTxxx communication methods.
Action	Check and correct the procedure file.

15-803 Command not supported with the current communication method.

Text	Command not supported with the current communication method.
Explanation	The command <i>cmd</i> is not supported with the current communication method. There are terminal commands which are only available with specific communication methods.
Action	Check and correct the command usage.

15-901 Out of disk space. REC_SCR turned off.

Text	Out of disk space. REC_SCR turned off.
Explanation	A screen trace could not be written to the disk because the disk is full. The screen trace was turned off.
Action	Check your hard disk for errors and for free disk space.

15-902 Fatal disk error. REC_SCR turned off.

Text	Fatal disk error. REC_SCR turned off.
Explanation	A screen trace could not be written to the disk because of a write error. The screen trace was turned off.
Action	Check the "Log&Trace" parameter in the User Properties, Procedure page. Check whether you have privileges to write to this location. Check your hard disk for errors and for free disk space.

15-903 Out of disk space. REC_BUF turned off.

Text	Out of disk space. REC_BUF turned off.
Explanation	A buffer trace could not be written to the disk because the disk is full. The buffer trace was turned off.
Action	Check your hard disk for errors and for free disk space.

15-904 Fatal disk error. REC_BUF turned off.

Text	Fatal disk error. REC_BUF turned off.
Explanation	A buffer trace could not be written to the disk because of a write error. The buffer trace was turned off.
Action	Check the "Log&Trace" parameter in the User Properties, Procedure page. Check whether you have privileges to write to this location. Check your hard disk.

15-905 Out of disk space. REC_XFER turned off.

Text	Out of disk space. REC_XFER turned off.
Explanation	A file transfer trace could not be written to the disk because the disk is full. The file transfer trace was turned off.
Action	Check your hard disk for errors and for free disk space.

15-906 Fatal disk error. REC_XFER turned off.

Text	Fatal disk error. REC_XFER turned off.
Explanation	A file transfer trace could not be written to the disk because of a write error. The file transfer trace was turned off.
Action	Check the "Log&Trace" parameter in the User Properties, Procedure page. Check whether you have privileges to write to this location. Check your hard disk.

16-002 Error parsing the 3270 data stream.

Text	Error parsing the 3270 data stream.
Explanation	The interpreter of the 3270 data stream was not able to parse successfully and reported an error: <i>error</i> .
Action	Check your session communication settings and the host connection. If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter "Enable communication trace" in the Test page of the session properties.

16-201 Disk error initializing the monitor trace.

Text	Disk error initializing the monitor trace.
Explanation	The monitor trace file could not be initialized because of a disk write error.
Action	Check the "Log&Trace" parameter in the User Properties, Procedure page. Check whether you have privileges to write to this location. Check your hard disk.

16-300 Open Socket failed.

Text	Open Socket failed.
Explanation	The Open Socket function returned an error: <i>error-code</i> .
Action	Check the communication settings for the session. Check your network connection or contact your network administrator.

16-301 Error initializing the WinSocket interface.

Text	Error initializing the WinSocket interface.
Explanation	An error occurred while initializing the WinSocket interface. Error: <i>error-code</i> .
Action	Check your network connection or contact your network administrator.

16-302 Connect failed.

Text	Connect failed.
Explanation	The Connect function returned an error: <i>error-code</i> .
Action	Check the communication settings for the session. Make sure that the host is running.

16-303 Exceeded limit of tasks supported by the Windows Socket implementation.

Text	Exceeded limit of tasks supported by the Windows Socket implementation.
Explanation	Host communication error. The number of tasks supported by the Windows Socket implementation has been exceeded.
Action	Check your PC for unusual load. Contact your network administrator.

16-304 The underlying network subsystem is not ready for network communication.

Text	The underlying network subsystem is not ready for network communication.
Explanation	Host communication error. The underlying network subsystem is not ready for network communication.
Action	Contact your network administrator.

16-311 An error occurred while attempting to receive data from the host.

Text	An error occurred while attempting to receive data from the host.
Explanation	Host communication error with error-code <i>error-code</i> in receiving data from the host.
Action	Check your network connection or contact your network administrator.

16-312 Error from function getaddrinfo.

Text	Error from function getaddrinfo.
Explanation	Host communication error. The function getaddrinfo returned an error: <i>error-code</i> .
Action	Check your network connection or contact your network administrator.

16-313 Windows Socket DLL version out of range (WSAVERNOTSUPPORTED).

Text	Windows Socket DLL version out of range (WSAVERNOTSUPPORTED).
Explanation	The current Windows Socket implementation does not support the Windows Sockets specification version requested by the Entire Connection.
Action	Contact your PC administrator.

16-318 Host not found (WSAHOST_NOT_FOUND).

Text	Host not found (WSAHOST_NOT_FOUND).
Explanation	The host <i>host-name</i> was not found. The name you have used is not an official hostname or alias.
Action	Check the session properties or contact your network administrator.

16-319 Host not found or server failure (WSATRY_AGAIN).

Text	Host not found or server failure (WSATRY_AGAIN).
Explanation	Failed to open session with error WSATRY_AGAIN. This is usually a temporary error during the resolution of the host name and means that the local server did not receive a response from an authoritative server.
Action	Try again.

16-320 Host name not found on the name server (WSANO_DATA).

Text	Host name not found on the name server (WSANO_DATA).
Explanation	Failed to open session with error WSANO_DATA. The host name was not found on the name server (DNS).
Action	Check the session properties or contact your network administrator.

16-321 Connection refused (WSAECONNREFUSED).

Text	Connection refused (WSAECONNREFUSED).
Explanation	Failed to open session with error WSAECONNREFUSED. The connection to the host was refused. No specific error was reported.
Action	Check the session properties or contact your network administrator.

16-322 Socket type not supported (WSAESOCKTNOSUPPORT).

Text	Socket type not supported (WSAESOCKTNOSUPPORT).
Explanation	Failed to open session with error WSAESOCKTNOSUPPORT. The type of socket requested by Entire Connection is not supported by the installed Windows Socket implementation.
Action	Check your Windows installation. Contact your PC administrator.

16-324 The network subsystem or the associated service provider has failed (WSAENETDOWN).

Text	The network subsystem or the associated service provider has failed (WSAENETDOWN).
Explanation	Failed to open session with error WSAENETDOWN. The network subsystem or the associated service provider has failed.
Action	Contact your network administrator.

16-325 Address family not supported by the installed Windows sockets implementation.

Text	Address family not supported by the installed Windows sockets implementation.
Explanation	Failed to open session with error WSAEAFNOSUPPORT. The specified address family is not supported by the installed Windows sockets implementation.
Action	Check your Windows installation. Contact your PC administrator.

16-326 No more socket descriptors available (WSAEMFILE).

Text	No more socket descriptors available (WSAEMFILE).
Explanation	Failed to open session with error WSAEMFILE. No more socket descriptors available.
Action	Check your PC system for unusual high load or looping applications.

16-327 Specified protocol not supported (WSAEPROTONOSUPPORT).

Text	Specified protocol not supported (WSAEPROTONOSUPPORT).
Explanation	Failed to open session with error WSAEPROTONOSUPPORT. The specified protocol is not supported by the installed Windows sockets implementation.
Action	Check your Windows installation. Contact your PC administrator.

16-328 Not enough buffers available, too many connections (WSAENOBUFS).

Text	Not enough buffers available, too many connections (WSAENOBUFS).
Explanation	Failed to open session with error WSAENOBUFS. Not enough buffers available, too many connections.
Action	Check your PC system for unusual high number of TPC/IP connections.

16-329 Socket already bound to an address (WSAEINVAL).

Text	Socket already bound to an address (WSAEINVAL).
Explanation	Failed to open session with error WSAEINVAL. The socket is already bound to an address.
Action	Close and re-open the session and try again. If the error persists, report the error to your local our support.

16-330 Specified buffer not part of the application address space.

Text	Specified buffer not part of the application address space.
Explanation	TCP/IP communication error. The specified buffer is not part of the application address space.
Action	Close and re-open the session and try again. If the error persists, report the error to your local our support.

16-331 Connection broken due to the remote host resetting (WSAENETRESET).

Text	Connection broken due to the remote host resetting (WSAENETRESET).
Explanation	Communication error. The connection has been broken due to the remote host resetting.
Action	Check your host communication.

16-332 Socket has been shut down (WSAESHUTDOWN).

Text	Socket has been shut down (WSAESHUTDOWN).
Explanation	Communication error. The socket has already been shut down.
Action	Close and re-open the session and try again. If the error persists, report the error to your local our support.

16-333 Message size problem (WSAEMSGSIZE).

Text	Message size problem (WSAEMSGSIZE).
Explanation	Communication error. A message size problem occurred.
Action	Close and re-open the session and try again. If the error persists, report the error to your local our support.

16-334 Remote host cannot be reached (WSAEHOSTUNREACH).

Text	Remote host cannot be reached (WSAEHOSTUNREACH).
Explanation	Failed to open session with error WSAEHOSTUNREACH. The remote host cannot be reached from this computer at this time.
Action	Check your host communication.

16-335 Host connection aborted, reset or timed out.

Text	Host connection aborted, reset or timed out.
Explanation	Communication error with WinSocket error <i>error-code</i> . The connection to the host was aborted, reset or timed out.
Action	Check your host communication.

16-336 Received message size too large.

Text	Received message size too large.
Explanation	The message size received from the host was too large to fit into the buffer and was truncated.
Action	Close and re-open the session and try again. If the error persists, report the error to your local our support.

16-337 Failed to open session with error WSAEACCES.

Text	Failed to open session with error WSAEACCES.
Explanation	Failed to open session. The requested address is a broadcast address, but the appropriate flag was not set.
Action	Check and correct the "Host name / IP address" parameter in the session properties.

16-338 Failed to open session with error WSAEADDRNOTAVAIL.

Text	Failed to open session with error WSAEADDRNOTAVAIL.
Explanation	Failed to open session. The specified address is not available from the local machine.
Action	Check and correct the "Host name / IP address" parameter in the session properties.

16-344 TCP/IP connection refused by host.

Text	TCP/IP connection refused by host.
Explanation	Failed to open session - TCP/IP connection refused by the host you want to connect to.
Action	Contact your network administrator.

16-346 Communication error in send routine.

Text	Communication error in send routine.
Explanation	Communication error in the send routine - the specified buffer is not part of the application address space.
Action	Close and re-open the session, and try again. If the error persists, report the error to your local our support.

16-347 Communication error in ioctlsocket routine.

Text	Communication error in ioctlsocket routine.
Explanation	Communication error in the ioctlsocket routine - the specified buffer is not part of the application address space.
Action	Close and re-open the session, and try again. If the error persists, report the error to your local our support.

16-350 Communication error in send routine.

Text	Communication error in send routine.
Explanation	Communication error in the send routine - the socket is message oriented, and the message is larger than the maximum supported by the underlying transport.
Action	Close and re-open the session, and try again. If the error persists, report the error to your local our support.

16-351 Communication error in ioctlsocket routine.

Text	Communication error in ioctlsocket routine.
Explanation	Communication error in the ioctlsocket routine - a blocking WinSock 1.1 call is in progress, or the service provider is still processing a callback function.
Action	Try again.

16-353 Failed to open session. Socket request refused.

Text	Failed to open session. Socket request refused.
Explanation	The socket is defined as non-blocking, the call would block. So the request has been refused.
Action	Close and re-open the session, and try again. If the error persists, report the error to your local our support.

16-354 Winsock II interface function WSAEventSelect failed.

Text	Winsock II interface function WSAEventSelect failed.
Explanation	The Winsock II interface function WSAEventSelect returned a WinSock error: <i>error-code</i> .
Action	Close and re-open the session, and try again. If the error persists, report the error to your local our support.

16-359 Failed to connect TCP/IP socket.

Text	Failed to connect TCP/IP socket.
Explanation	The connect TCP/IP socket function failed. The host could not be connected with the given name and port.
Action	Check the host name and port number in the session settings. Check whether the host system is running.

16-363 Send data to socket failed.

Text	Send data to socket failed.
Explanation	The send data to socket function returned a WinSock error: <i>error-code</i> .
Action	Close and re-open the session, and try again. If the error persists, report the error to your local our support.

16-365 WinSocket returned an unspecific error.

Text	WinSocket returned an unspecific error.
Explanation	The call to the WinSocket interface returned an unspecific error. Failed to open session.
Action	Check your Windows WinSocket installation. Contact your network administrator.

16-401 Invalid value in data type field of a TN3270E message header.

Text	Invalid value in data type field of a TN3270E message header.
Explanation	An invalid value was found in the data type field of a the TN3270E message header.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-402 Invalid value in request flag field of a TN3270E message header.

Text	Invalid value in request flag field of a TN3270E message header.
Explanation	An invalid value was found in the request flag field of a TN3270E message header.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-403 Invalid value in response flag field of a TN3270E message header.

Text	Invalid value in response flag field of a TN3270E message header.
Explanation	An invalid value was found in the response flag field of a TN3270E message header.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-404 Invalid value in sequence number field of a TN3270E message header.

Text	Invalid value in sequence number field of a TN3270E message header.
Explanation	An invalid value was found in the sequence number field of a TN3270E message header.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-411 Connection request to printer failed.

Text	Connection request to printer failed.
Explanation	The connection request to a specific printer failed because <i>device-name</i> is the partner to some terminal.
Action	Check the definition of the printer in the Telnet server configuration.

16-412 Printer device already associated with another session.

Text	Printer device already associated with another session.
Explanation	The requested printer <i>device-name</i> is already associated with another screen session.
Action	Check the definition of the printer in the Telnet server configuration.

16-413 Association to a terminal device failed.

Text	Association to a terminal device failed.
Explanation	Association to a terminal device failed because <i>device-name</i> is not a terminal.
Action	Check the definition of the printer in the Telnet server configuration.

16-414 Device or resource name not known to the Telnet server.

Text	Device or resource name not known to the Telnet server.
Explanation	The device or resource <i>name</i> specified in the "TN3270E communication" dialog is not known to the Telnet server.
Action	Check the session settings in the Entire Connection Configuration Manager.

16-415 Telnet server does not support the requested device type.

Text	Telnet server does not support the requested device type.
Explanation	The Telnet server does not support the requested device type <i>device-type</i> .
Action	Check the session settings in the Entire Connection Configuration Manager. Contact your Telnet server administrator.

16-416 Incompatible device or resource name requested.

Text	Incompatible device or resource name requested.
Explanation	The requested device or resource <i>name</i> is incompatible with the requested device type <i>device-type</i> .
Action	Check the session settings in the Entire Connection Configuration Manager. Contact your Telnet server administrator.

16-417 Unknown error in device type or name processing.

Text	Unknown error in device type or name processing.
Explanation	An unknown error in device type or name processing has occurred.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-418 Telnet server unable to satisfy client request.

Text	Telnet server unable to satisfy client request.
Explanation	The Telnet server is unable to satisfy the type of request sent by the client. Possible reasons: a specific terminal or printer was requested but the Telnet server does not have any such pools of device names defined to it, or the "Associate to terminal" option was used but no partner printers are defined in the Telnet server.
Action	Check the settings in the Telnet server. Contact your Telnet server administrator.

16-419 Unknown device type reject command.

Text	Unknown device type reject command.
Explanation	The device type was rejected by the host with an unknown device type reject command.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-420 No device name returned for requested device type.

Text	No device name returned for requested device type.
Explanation	A TN3270E negotiation problem occurred. The Telnet server did not return a device name for device type <i>device-type</i> .
Action	Check the settings in the Telnet server. Contact your Telnet server administrator.

16-421 Unexpected 3270 or SCS data from host.

Text	Unexpected 3270 or SCS data from host.
Explanation	Entire Connection received 3270 or SCS data from the host but the session was not yet bound.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-422 Wrong host printer sessions returned.

Text	Wrong host printer sessions returned.
Explanation	The Telnet server tried to open a TN3270 printer session. Entire Connection only supports TN3270E host printer sessions.
Action	Check the settings on the Telnet server. Contact your Telnet server administrator.

16-423 Unexpected SCS data received.

Text	Unexpected SCS data received.
Explanation	The Telnet server sent SCS data although SCS was not negotiated.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-424 Unexpected SNA bind received.

Text	Unexpected SNA bind received.
Explanation	The Telnet server sent a SNA bind image although bind-image was not negotiated.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace, enable the parameter Communication Traces in the Test page of the Session Properties.

16-425 Unexpected SNA unbind received.

Text	Unexpected SNA unbind received.
Explanation	The Telnet server sent a SNA unbind notification although bind-image was not negotiated.
Action	If the error persists, create a communication trace and report the error to your local our support. To turn on the communication trace enable the parameter Communication Traces in the Test page of the Session Properties.

16-501 Open of associated printer session failed.

Text	Open of associated printer session failed.
Explanation	The associated printer session could not be opened. Your Telnet server only supports TN3270 sessions. Entire Connection only supports TN3270E host printer sessions.
Action	Check the settings in the Telnet server. Contact your Telnet server administrator.

17-000 Open file parameter error.

Text	Open file parameter error.
Explanation	A parameter error was returned from the open file function for <i>file-name</i> . Open file failed.
Action	Check the file name and the parameters passed.

17-001 File is write protected.

Text	File is write protected.
Explanation	Open file failed for <i>file-name</i> . The file is write-protected. Data transfer terminated abnormally.
Action	Check the file properties.

17-002 Invalid field type in format record.

Text	Invalid field type in format record.
Explanation	The format record received from Natural contains an unknown or invalid field type. Data transfer terminated abnormally.
Action	If the error persists, create a file transfer trace and report the error to your local our support. Press the CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-003 Data transfer terminated by user request.

Text	Data transfer terminated by user request.
Explanation	Data transfer terminated by user request. You have chosen the Cancel button while the data transfer was in progress. All currently running data transfers will be terminated.
Action	No action required.

17-004 Data transfer buffer error.

Text	Data transfer buffer error.
Explanation	The data transfer buffer received from Natural is in error. Data transfer terminated abnormally.
Action	If the error persists, create a file transfer trace and report the error to your local our support. Press CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-005 Disk space exceeded during download.

Text	Disk space exceeded during download.
Explanation	Data transfer terminated abnormally, disk space exceeded.
Action	Check your hard disk for errors and for free disk space.

17-006 Error uploading data from XML file.

Text	Error uploading data from XML file.
Explanation	Uploading data from the XML file failed. An error occurred while parsing the data from XML to the Natural data record. Data transfer terminated abnormally.
Action	Check the XML file for errors. Check that the data in the XML file matches the Natural record.

17-007 Missing <RECORD> tag.

Text	Missing <RECORD> tag.
Explanation	No <RECORD> tag was found in the XML file. Data transfer terminated abnormally.
Action	Check and correct the XML data file.

17-008 Cannot open temporary file for XML upload failed.

Text	Cannot open temporary file for XML upload failed.
Explanation	The temporary file <i>name</i> required for the XML data upload could not be opened. Data transfer terminated abnormally.
Action	Check your hard disk for errors and for free disk space. Check whether you have permissions to write to the location.

17-009 Missing TEMP or TMP environment variable.

Text	Missing TEMP or TMP environment variable.
Explanation	The file transfer aborted because the TEMP and TMP environment variables are not set. Entire Connection needs a temporary file for the XML data upload. Data transfer terminated abnormally.
Action	Check the Windows TEMP and TMP environment variables.

17-010 Open file for data transfer failed.

Text	Open file for data transfer failed.
Explanation	Open file failed for <i>file-name</i> . The file name, directory name, or volume label syntax is incorrect. Data transfer terminated abnormally.
Action	Check and correct the supplied file name.

17-011 Data type mismatch.

Text	Data type mismatch.
Explanation	The data format in the record <i>record</i> of the file to be uploaded does not match the record format specified in the Natural program. Data transfer terminated abnormally.
Action	Check the data in the input file. Check the field type specified in the Natural UPLOAD statement.

17-012 Data length greater than field length.

Text	Data length greater than field length.
Explanation	The data transfer function of Entire Connection detected that the data sent by Natural for a field exceeds the field length as specified in the field format. The excess data will be lost.
Action	Check the Natural download coding in the Natural program.

17-013 File access error.

Text	File access error.
Explanation	Open file failed for <i>file-name</i> with access denied error. Data transfer terminated abnormally.
Action	Check whether you have the appropriate privileges for the file and the specified location.

17-014 Error writing to file.

Text	Error writing to file.
Explanation	An error occurred while writing to <i>file-name</i> . Data transfer terminated abnormally.
Action	Check your hard disk for errors and for free space.

17-015 Invalid usage of reserved file name.

Text	Invalid usage of reserved file name.
Explanation	"prn" and "lpt1" to "lpt3" are reserved names which cannot be used as file names for upload and download. Data transfer terminated abnormally.
Action	Supply a valid file name.

17-018 DOWNLOAD REPORT or DOWNLOAD VARIABLE conversion error.

Text	DOWNLOAD REPORT or DOWNLOAD VARIABLE conversion error.
Explanation	DOWNLOAD REPORT or DOWNLOAD VARIABLE must be set to ASCII (.ncd or .ncc) format only. Download to <i>file-name</i> failed. Data transfer terminated abnormally.
Action	Choose a file extension for ASCII conversion, that is, .ncd or .ncc or any extension not associated with a format conversion in Entire Connection such as .txt.

17-019 DOWNLOAD COMMAND string is too long.

Text	DOWNLOAD COMMAND string is too long.
Explanation	The command specified in the Natural DOWNLOAD COMMAND statement is too long. The maximum command length is 276 characters. The command will not be executed.
Action	Correct the Natural DOWNLOAD COMMAND statement in the Natural program.

17-020 Error writing to printer.

Text	Error writing to printer.
Explanation	Download to printer failed. An error occurred while writing to the printer. Data transfer terminated abnormally.
Action	Check your printer and the printer settings of the PC.

17-023 Internal error processing field names.

Text	Internal error processing field names.
Explanation	Internal error while processing field names received from Natural. Data transfer terminated abnormally.
Action	If the error persists, create a file transfer trace and report the error to your local our support. Press CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-024 Non-ASCII file specified for upload.

Text	Non-ASCII file specified for upload.
Explanation	You are attempting to upload a non-ASCII file. The file being uploaded contains binary zeros. Data transfer terminated abnormally.
Action	Check the file you want to upload.

17-026 Unknown Lotus field type.

Text	Unknown Lotus field type.
Explanation	Unknown Lotus field type <i>field-type</i> in the field <i>field</i> of the record <i>record</i> detected. Data transfer terminated abnormally.
Action	Check the Lotus data file.

17-027 Buffer count is in error.

Text	Buffer count is in error.
Explanation	Buffer count is in error. The data buffer received from Natural does not have the expected sequence number. Data transfer terminated abnormally.
Action	Check your host connection. If the error persists, create a file transfer trace and report the error to your local our support. Press CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-028 Variable length data cannot be uploaded.

Text	Variable length data cannot be uploaded.
Explanation	Upload data to a Natural record defined as variable is not supported. Data transfer terminated abnormally.
Action	Check and correct the UPLOAD statement in the Natural program.

17-029 Invalid data in response field.

Text	Invalid data in response field.
Explanation	The data buffer received from Natural contains invalid data in the response field. Data transfer terminated abnormally.
Action	Check your host connection. If the error persists, create a file transfer trace and report the error to your local our support. Press CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-030 Data transfer buffer out of sync.

Text	Data transfer buffer out of sync.
Explanation	The data transfer buffer is out of sync. A header data buffer was expected, but the buffer received from Natural is a normal data buffer. Data transfer terminated abnormally.
Action	Check your host connection. If the error persists, create a file transfer trace and report the error to your local our support. Press CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-031 Natural data transfer terminated abnormally.

Text	Natural data transfer terminated abnormally.
Explanation	A fatal error occurred and the data transfer terminated. This message is displayed after a message showing the specific error has been displayed.
Action	See the action for the specific error which was displayed before.

17-034 Buffer overrun during compression.

Text	Buffer overrun during compression.
Explanation	Buffer overrun during compression. The size of the record in the Natural UPLOAD statement is greater than a data transfer buffer. This only works as long as the data can be compressed enough.
Action	Check the upload logic in the Natural program. Try using a bigger 3270 terminal model.

17-036 Cannot download binary data to Excel application.

Text	Cannot download binary data to Excel application.
Explanation	You cannot download binary data to an Excel application. Data transfer terminated abnormally.
Action	Check and correct the DOWNLOAD statement in the Natural program.

17-042 Unknown format detected.

Text	Unknown format detected.
Explanation	An unknown format was detected in the data buffer received from Natural. You may be using an older version of Entire Connection which does not support a data format supported by your newer Natural version. Data transfer terminated abnormally.
Action	Check your Entire Connection version. Make sure you are using the latest version. If the error persists, create a file transfer trace and report the error to your local our support. Press CTRL+F to turn the file transfer trace on. An "X" at the end of the status line shows that the file transfer trace is enabled. Press CTRL+F again to turn the trace off.

17-043 File not found.

Text	File not found.
Explanation	The file specified for upload could not be found. Data transfer terminated abnormally.
Action	Check and correct the file name.

17-044 Too many open files.

Text	Too many open files.
Explanation	The file specified for upload could not be opened because there are too many open files on the PC. Data transfer terminated abnormally.
Action	Check why there are that many open files and close some files.

17-045 File already in use.

Text	File already in use.
Explanation	The file specified for upload could not be opened because the file has already been opened by another application. Data transfer terminated abnormally.
Action	Check which other application has opened the file and close it.

17-046 Network busy.

Text	Network busy.
Explanation	The file specified for upload could not be opened because your network is busy at this time. Data transfer terminated abnormally.
Action	Check your network connection and try again.

17-047 Open file failure.

Text	Open file failure.
Explanation	The file specified could not be opened. The Windows CreateFile function returned an error: <i>error-code</i> . Data transfer terminated abnormally.
Action	Try again. If the error persists, report the error to your local our support.

17-048 Conversion to the selected format not yet supported.

Text	Conversion to the selected format not yet supported.
Explanation	Conversion to the selected format is not yet supported. This should only happen in a development environment. Data transfer terminated abnormally.
Action	Try again. If the error persists, report the error to your local our support.

17-049 File path not found.

Text	File path not found.
Explanation	The file specified could not be opened. An invalid drive or path was specified. Data transfer terminated abnormally.
Action	Check and correct the file name.

17-053 Open printer failed.

Text	Open printer failed.
Explanation	Download to printer failed because there was an error in the open printer function. Data transfer terminated abnormally.
Action	Check the selected printer.

17-055 Not enough memory available for spooling.

Text	Not enough memory available for spooling.
Explanation	The Entire Connection host printer support could not be started because there was not enough memory available.
Action	Check your PC system for applications with unusually high memory usage.

17-058 Empty file error.

Text	Empty file error.
Explanation	You are attempting to upload a file with length 0. Data transfer terminated abnormally.
Action	Check the file you want to upload.

17-061 Binary data format cannot be used with this file type.

Text	Binary data format cannot be used with this file type.
Explanation	The Natural data record contains a binary data field. However, the file type you selected does not allow binary data. Data transfer terminated abnormally.
Action	Choose a file type which supports binary data.

17-064 Open printer failed.

Text	Open printer failed.
Explanation	Printing to the host printer failed because the configured PC or network printer could not be opened. There was an error with error-code <i>error-code</i> from the Windows OpenPrinter function.
Action	Check your PC or network printer.

17-065 Unable to spool print document to printer.

Text	Unable to spool print document to printer.
Explanation	Printing to the host printer failed. There was an error with error-code <i>error-code</i> from the Windows StartDocPrinter function.
Action	Check the printer setup in your Windows system.

17-066 Error reading temporary print file.

Text	Error reading temporary print file.
Explanation	Printing to the host printer failed. There was an error with error-code <i>error-code</i> while reading from the temporary print file.
Action	Check your hard disk.

17-067 Error writing data to printer.

Text	Error writing data to printer.
Explanation	Printing to the host printer failed. There was an error with error-code <i>error-code</i> while writing to the local printer <i>printer-name</i> .
Action	Check the printer setup in your Windows system.

17-068 Error closing printer.

Text	Error closing printer.
Explanation	Printing to the host printer failed. The Windows ClosePrinter function returned an error: <i>error-code</i> .
Action	Check the printer setup in your Windows system.

17-069 Error closing printer spooler.

Text	Error closing printer spooler.
Explanation	Printing to the host printer failed. The Windows EndDocPrinter function returned an error: <i>error-code</i> .
Action	Check the printer setup in your Windows system.

17-070 Record length exceeds 32767 bytes.

Text	Record length exceeds 32767 bytes.
Explanation	The record length of the record used in the Natural DOWNLOAD statement exceeds 32767 bytes. dBase and Lotus only support a maximum record length of 32767.
Action	Check and correct the DOWNLOAD statement in the Natural program.

17-071 Record read mismatch.

Text	Record read mismatch.
Explanation	Record read from file does not match the record requested from Natural. Data transfer terminated abnormally.
Action	Check the file you want to upload.

17-072 Too many fields for specified format.

Text	Too many fields for specified format.
Explanation	The number of fields in the Natural data transfer records is greater than the number of fields supported by the PC file data format. Data transfer terminated abnormally.
Action	Check and correct the data transfer statement in the Natural program.

17-073 Alphanumeric fields with length greater than 253 not supported.

Text	Alphanumeric fields with length greater than 253 not supported.
Explanation	The Natural data record contains an alphanumeric field with a length greater than 253. The PC file data format chosen, however, does not support alphanumeric fields with such a length. Data transfer terminated abnormally.
Action	Check and correct the data transfer statement in the Natural program.

17-074 Record length for DOWNLOAD VARIABLE exceeds 32767 bytes.

Text	Record length for DOWNLOAD VARIABLE exceeds 32767 bytes.
Explanation	The data record used in the Natural DOWNLOAD VARIABLE statement exceeds the limit of 32767 bytes. Data transfer terminated abnormally.
Action	Check and correct the data transfer statement in the Natural program.

17-075 Data formats X, Y and U not supported by the installed version.

Text	Data formats X, Y and U not supported by the installed version.
Explanation	The Natural data record contains a BLOB (X), LOB (Y) or Unicode (U) field. This is not supported in the version of Entire Connection you are using. Data transfer terminated abnormally.
Action	Check your Entire Connection version. Make sure you are using the latest version.

17-076 Insufficient memory available.

Text	Insufficient memory available.
Explanation	Insufficient memory available. Data transfer terminated abnormally.
Action	Check your Windows system for unusually high memory usage.

17-077 Too many fields of type U, X or Y.

Text	Too many fields of type U, X or Y.
Explanation	The Natural data record contains too many fields of the types BLOB (X), LOB (Y) or Unicode (U). Only up to 4000 fields of these types may be contained in one record. Data transfer terminated abnormally.
Action	Check and correct the data transfer statement in the Natural program.

17-078 Unicode fields with length greater than 253 not supported in PC file format.

Text	Unicode fields with length greater than 253 not supported in PC file format.
Explanation	The Natural data record contains a Unicode type field with a length greater than 253. The chosen PC file format (for example, XLS), however, does not support Unicode fields with a length greater than 253. Data transfer terminated abnormally.
Action	Check and correct the data transfer statement in the Natural program.

17-090 Error parsing XML file for upload.

Text	Error parsing XML file for upload.
Explanation	An error in the XML data file was detected in <i>line, column</i> .
Action	Check and correct the XML data file you want to upload.

17-091 Fatal error parsing XML file for upload.

Text	Fatal error parsing XML file for upload.
Explanation	An fatal error in the XML data file was detected in <i>line, column</i> .
Action	Check and correct the XML data file you want to upload.

17-092 Warning while uploading XML file.

Text	Warning while uploading XML file.
Explanation	Warning for the XML data file in line <i>line</i> , column <i>column</i> .
Action	Check and correct the XML data file you want to upload.

17-093 Error while uploading XML file.

Text	Error while uploading XML file.
Explanation	An error was detected in line <i>line</i> of the XML file you want to upload. Data transfer terminated abnormally.
Action	Check and correct the XML data file you want to upload.

17-101 Error opening print data output file.

Text	Error opening print data output file.
Explanation	Opening of the print data output file <i>file-name</i> failed with error <i>error-code</i> . The host print job failed.
Action	Check your hard disk for errors and for free disk space.

17-102 Error closing print data output file.

Text	Error closing print data output file.
Explanation	Closing of the print data output file <i>file-name</i> failed with error <i>error-code</i> . The host print job failed.
Action	Check your hard disk for errors and for free disk space.

17-103 Error writing print data to output file.

Text	Error writing print data to output file.
Explanation	Writing the print data to the output file <i>file-name</i> failed with error <i>error-code</i> . The host print job failed.
Action	Check your hard disk for errors and for free disk space.

17-104 Wrong host printer support print destination.

Text	Wrong host printer support print destination.
Explanation	The print destination setting in the host printer session properties is wrong.
Action	Check and correct the print destination setting in the host printer session properties.

17-106 Host Printer Manager could not start user print program.

Text	Host Printer Manager could not start user print program.
Explanation	The Host Printer Manager could not start a user-supplied print program. Windows returned an error: <i>error-code</i> .
Action	Check and correct the program name in the host printer session, Printer LU settings.

17-111 Error opening temporary printer file.

Text	Error opening temporary printer file.
Explanation	An error with error-code <i>error-code</i> was returned from the open file call for the temporary printer file <i>file-name</i> .
Action	Check your hard disk for errors and for free disk space.

17-112 Natural UNIX data transfer could not be started.

Text	Natural UNIX data transfer could not be started.
Explanation	Natural UNIX data transfer could not be started. A network address or port setting conflict was detected on your computer. Additional information was written to the Windows event log.
Action	Check the Windows event log for additional information. If the error persists, report the error to your local our support.

17-114 Unix File Transfer via Port Communication is not allowed for this session.

Text	Unix File Transfer via Port Communication is not allowed for this session.
Explanation	Unix File Transfer via Port Communication is not allowed for this session.
Action	Check File Transfer Setup in Session Communication.

19-004 Out of disk space.

Text	Out of disk space.
Explanation	A disk space error was returned when writing to the file <i>file-name</i> .
Action	Check your hard disk for errors and for free disk space.

19-006 Error opening output file.

Text	Error opening output file.
Explanation	The file <i>file-name</i> could not be opened.
Action	Check the file name and path setting.

19-012 Cannot allocate memory.

Text	Cannot allocate memory.
Explanation	A memory request to the Windows operating system failed. The current Entire Connection operation failed.
Action	Stop Entire Connection, close other Windows applications and then try again.

19-013 Error creating NCF file.

Text	Error creating NCF file.
Explanation	The creation of the data transfer format file <i>file-name</i> failed with error <i>error-code</i> .
Action	Check your hard disk for errors and for free disk space.

19-014 Error creating Excel Automation Server.

Text	Error creating Excel Automation Server.
Explanation	The Excel Automation Server could not be created. Data transfer from or to Excel format failed.
Action	Check your Windows setup. Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-015 Error setting Excel worksheet name.

Text	Error setting Excel worksheet name.
Explanation	An error occurred while setting the Excel worksheet name <i>worksheet-name</i> . Download to the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-016 Error opening Excel workbook.

Text	Error opening Excel workbook.
Explanation	An error occurred while opening the Excel workbook <i>workbook-name</i> . Upload from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works. Check whether you can open the workbook in Excel.

19-017 Error writing data to Excel file.

Text	Error writing data to Excel file.
Explanation	An error occurred while writing the Natural field names to the Excel file. Download to the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-018 Error saving Excel worksheet or workbook.

Text	Error saving Excel worksheet or workbook.
Explanation	An error occurred while writing the Excel worksheet or workbook to disk. Download to the Excel file failed.
Action	Check your hard disk for errors and for free disk space.

19-019 Error reading Excel value.

Text	Error reading Excel value.
Explanation	An error occurred while reading values from Excel. Upload from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works. Check whether you can open the file in Excel.

19-020 Error reading last Excel cell.

Text	Error reading last Excel cell.
Explanation	An error occurred while reading a cell from Excel. Upload from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works. Check whether you can open the file in Excel.

19-021 Cannot convert variant data type.

Text	Cannot convert variant data type.
Explanation	An error occurred while reading data from Excel in the convert variant data type function. Upload from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works. Check whether you can open the file in Excel.

19-022 Error closing workbook.

Text	Error closing workbook.
Explanation	An error occurred while closing the Excel workbook <i>workbook-name</i> . Data transfer to or from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-023 Error closing workbooks.

Text	Error closing workbooks.
Explanation	An error occurred while closing the Excel workbooks. Data transfer to or from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-024 Error closing Excel Automation Server.

Text	Error closing Excel Automation Server.
Explanation	An error occurred while closing the Excel Automation Server. Data transfer to or from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-025 Error retrieving decimal character from Excel Automation Server.

Text	Error retrieving decimal character from Excel Automation Server.
Explanation	An error occurred while retrieving the decimal character from the Excel Automation Server. Data transfer to or from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-026 Error retrieving thousands separator character from Excel Automation Server.

Text	Error retrieving thousands separator character from Excel Automation Server.
Explanation	An error occurred while retrieving the thousands separator character from the Excel Automation Server. Data transfer to or from the Excel file failed.
Action	Check whether a version of Excel is installed which is supported by Entire Connection and make sure that it works.

19-027 Maximum number of rows per worksheet exceeded.

Text	Maximum number of rows per worksheet exceeded.
Explanation	Maximum number of rows per worksheet exceeded. The maximum number of rows per worksheet is limited. The limit depends on the Excel version. Download to the Excel file failed.
Action	Change the download logic in the Natural program. Check the Excel version and consider using a higher version.

19-028 Maximum number of rows per worksheet exceeded.

Text	Maximum number of rows per worksheet exceeded.
Explanation	An Excel worksheet of version 7 can store the maximum number of 16384 rows.
Action	Change the download logic in the Natural program. Check the Excel version and consider using a higher version.

19-030 Error writing header to the Multiplan file.

Text	Error writing header to the Multiplan file.
Explanation	An error occurred while writing the header to the Multiplan file <i>file-name</i> . Download to the Multiplan file failed.
Action	Check the file name and path setting.

19-031 Error writing data to the Multiplan file.

Text	Error writing data to the Multiplan file.
Explanation	An error occurred while writing data to the Multiplan file <i>file-name</i> . Download to the Multiplan file failed.
Action	Check your hard disk for errors and for free disk space.

19-032 Error writing trailer to the Multiplan file.

Text	Error writing trailer to the Multiplan file.
Explanation	An error occurred while writing the trailer to the Multiplan file <i>file-name</i> . Download to the Multiplan file failed.
Action	Check your hard disk for errors and for free disk space.

19-035 No column labels in Excel worksheet.

Text	No column labels in Excel worksheet.
Explanation	The option to use column labels is switched on but there are no column labels in the Excel worksheet. Upload from Excel file failed.
Action	Check and correct the option usage.

19-036 Unexpected column labels in Excel worksheet.

Text	Unexpected column labels in Excel worksheet.
Explanation	The option to use column labels is switched off but there are column labels in the Excel worksheet. Upload from Excel file failed.
Action	Check and correct the option usage.

19-040 Error writing header to the dBase file.

Text	Error writing header to the dBase file.
Explanation	An error occurred while writing the header to the dBase file <i>file-name</i> . Download to the dBase file failed.
Action	Check the file name and path setting.

19-041 Error writing data to a dBase file.

Text	Error writing data to a dBase file.
Explanation	An error occurred while writing data to the dBase file <i>file-name</i> . Download to the dBase file failed.
Action	Check your hard disk for errors and for free disk space.

19-042 Error writing trailer to the dBase file.

Text	Error writing trailer to the dBase file.
Explanation	An error occurred while writing the trailer to the dBase file <i>file-name</i> . Download to the dBase file failed.
Action	Check your hard disk for errors and for free disk space.

19-045 Error writing data to the NCD file.

Text	Error writing data to the NCD file.
Explanation	An error occurred while writing data to the file <i>file-name</i> . Download to NCD format failed.
Action	Check your hard disk for errors and for free disk space.

19-046 Binary data will be written to the NCD file.

Text	Binary data will be written to the NCD file.
Explanation	Warning: Binary data will be written to the NCD file <i>file-name</i> .
Action	Check the data that are downloaded if binary data are allowed.

19-047 Unicode data download to NCC file format not supported.

Text	Unicode data download to NCC file format not supported.
Explanation	Download of Unicode data to NCC file format is not supported by Entire Connection. Data transfer aborted.
Action	Choose a different data file format.

19-048 Upload Unicode data from NCC file format not supported.

Text	Upload Unicode data from NCC file format not supported.
Explanation	Upload of Unicode data from a NCC file format is not supported by Entire Connection. Data transfer aborted.
Action	Check and change the UPLOAD statement in the Natural program.

19-049 Download Unicode data to printer not supported.

Text	Download Unicode data to printer not supported.
Explanation	Download of Unicode data to a printer is not supported by Entire Connection. Data transfer aborted.
Action	Download to a file as intermediate step. Check and change the DOWNLOAD statement in the Natural program.

19-050 Error writing header to the DIF file.

Text	Error writing header to the DIF file.
Explanation	An error occurred while writing the header to the DIF file <i>file-name</i> . Download to the DIF file failed.
Action	Check the file name and path setting.

19-051 Error writing data to the DIF file.

Text	Error writing data to the DIF file.
Explanation	An error occurred while writing data to the DIF file <i>file-name</i> . Download to the DIF file failed.
Action	Check your hard disk for errors and for free disk space.

19-052 Error writing trailer to the DIF file.

Text	Error writing trailer to the DIF file.
Explanation	An error occurred while writing the trailer to the DIF file <i>file-name</i> . Download to the DIF file failed.
Action	Check your hard disk for errors and for free disk space.

19-055 Error writing header to the ENC file.

Text	Error writing header to the ENC file.
Explanation	An error occurred while writing the header to the ENC file <i>file-name</i> . Download to the ENC file failed.
Action	Check the file name and path setting.

19-056 Error writing data to the ENC file.

Text	Error writing data to the ENC file.
Explanation	An error occurred while writing data to the ENC file <i>file-name</i> . Download to the ENC file failed.
Action	Check your hard disk for errors and for free disk space.

19-057 Error writing trailer to the ENC file.

Text	Error writing trailer to the ENC file.
Explanation	An error occurred while writing the trailer to the ENC file <i>file-name</i> . Download to the ENC file failed.
Action	Check your hard disk for errors and for free disk space.

19-060 Error writing header to the PRN file.

Text	Error writing header to the PRN file.
Explanation	An error occurred while writing the header to the PRN file <i>file-name</i> . Download to the PRN file failed.
Action	Check the file name and path setting.

19-061 Error writing data to the PRN file.

Text	Error writing data to the PRN file.
Explanation	An error occurred while writing data to the PRN file <i>file-name</i> . Download to the PRN file failed.
Action	Check your hard disk for errors and for free disk space.

19-062 Error writing trailer to the PRN file.

Text	Error writing trailer to the PRN file.
Explanation	An error occurred while writing the trailer to the PRN file <i>file-name</i> . Download to the PRN file failed.
Action	Check your hard disk for errors and for free disk space.

19-065 No table found in this HTML file.

Text	No table found in this HTML file.
Explanation	An error was detected in the HTML file - no more table entries found. Upload from the HTML file failed.
Action	Check the HTML file you want to upload.

19-066 HTML file character set not supported.

Text	HTML file character set not supported.
Explanation	The character set <i>name</i> used in the HTML file is not supported by Entire Connection.
Action	Save the file with another encoding and try again.

19-067 No more table entries found in HTML file.

Text	No more table entries found in HTML file.
Explanation	An error was detected in the HTML file <i>file-name</i> - no more table entries found. Upload from the HTML file failed.
Action	Check the HTML file you want to upload.

19-068 Failed to write trailer to the HTML file.

Text	Failed to write trailer to the HTML file.
Explanation	An error occurred while writing the trailer to the HTML file <i>file-name</i> . Download to the HTML file failed.
Action	Check your hard disk for errors and for free disk space.

19-069 Failed to write data to the HTML file.

Text	Failed to write data to the HTML file.
Explanation	An error occurred while writing data to the HTML file <i>file-name</i> . Download to the HTML file failed.
Action	Check your hard disk for errors and for free disk space.

19-070 Error writing header to the Lotus file.

Text	Error writing header to the Lotus file.
Explanation	An error occurred while writing the header to the Lotus file <i>file-name</i> . Download to the Lotus file failed.
Action	Check the file name and path setting.

19-071 Error writing data to the Lotus file.

Text	Error writing data to the Lotus file.
Explanation	An error occurred while writing data to the Lotus file <i>file-name</i> . Download to the Lotus file failed.
Action	Check your hard disk for errors and for free disk space.

19-072 Error writing trailer to the Lotus file.

Text	Error writing trailer to the Lotus file.
Explanation	An error occurred while writing the trailer to the Lotus file <i>file-name</i> . Download to the Lotus file failed.
Action	Check your hard disk for errors and for free disk space.

19-073 Error writing header to the XML file.

Text	Error writing header to the XML file.
Explanation	An error occurred while writing the header to the XML file <i>file-name</i> . Download to the XML file failed.
Action	Check the file name and path setting.

19-074 Error writing data to the XML file.

Text	Error writing data to the XML file.
Explanation	An error occurred while writing data to the XML file <i>file-name</i> . Download to the XML file failed.
Action	Check your hard disk for errors and for free disk space.

19-080 Error converting PRN file.

Text	Error converting PRN file.
Explanation	Error converting PRN file. The field separator (comma) was not found. Upload from the PRN file failed.
Action	Check the PRN file you want to upload.

19-081 Start of text field not found.

Text	Start of text field not found.
Explanation	Error in conversion. The start of the text field was not found; the beginning quotes are missing. Upload failed.
Action	Check and correct the file you want to upload.

19-082 End of text field not found.

Text	End of text field not found.
Explanation	Error in conversion. The end of the text field was not found; the ending quotes are missing. Upload failed.
Action	Check and correct the file you want to upload.

19-083 Invalid format of number/decimal in input file.

Text	Invalid format of number/decimal in input file.
Explanation	Error in conversion. An invalid format of a number/decimal was detected in the input file. Upload failed.
Action	Check and correct the file you want to upload.

19-084 Invalid format of float in input file.

Text	Invalid format of float in input file.
Explanation	Error in conversion. An invalid format of float was detected in the input file. Upload failed.
Action	Check and correct the file you want to upload.

19-085 Missing leading minus, plus or blank for numeric or decimal in input file.

Text	Missing leading minus, plus or blank for numeric or decimal in input file.
Explanation	Numeric or decimal values in NCD or DBF input files must have a leading blank, plus sign or minus sign. Upload failed.
Action	Check and correct the file you want to upload.

19-086 Error converting input file.

Text	Error converting input file.
Explanation	A fatal error occurred while converting the data from the input file format. Upload failed.
Action	Check and correct the file you want to upload.

19-090 Upload of binary data of Unicode UTF-16 data not supported.

Text	Upload of binary data of Unicode UTF-16 data not supported.
Explanation	There is a binary data field in the Natural UPLOAD statement. And you specified a UTF-16 coded file for upload. This is not supported by Entire Connection. Upload failed.
Action	Check and correct the input file.

19-201 Cannot find online documentation folder.

Text	Cannot find online documentation folder.
Explanation	The folder for the online documentation could not be found. A folder named "doc" should exist either in ProgramData\Software AG\Entire Connection or in the folder which contains the Entire Connection executables.
Action	Check and correct your Entire Connection installation.

19-202 Cannot find online documentation.

Text	Cannot find online documentation.
Explanation	The Entire Connection online documentation file PCCxxxxy.chm (were xxx is the version number, and yy is the language code) could not be found.
Action	Check and correct your Entire Connection installation.

19-203 Cannot start online help.

Text	Cannot start online help.
Explanation	The Entire Connection online documentation could not be started. An error occurred while processing the help file.
Action	Check and correct your Entire Connection installation.

19-204 Cannot display Software AG web pages.

Text	Cannot display Software AG web pages.
Explanation	An error occurred while trying to display the Software AG web page in the internet browser.
Action	Check your browser and check the URL used.

19-210 Error occurred in online help.

Text	Error occurred in online help.
Explanation	An unknown error occurred in online help.
Action	Check and correct your Entire Connection installation.

19-800 Could not delete object.

Text	Could not delete object.
Explanation	Deletion failed for share file object <i>object-name</i> .
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-801 Could not delete user properties record.

Text	Could not delete user properties record.
Explanation	The user properties record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-802 Could not delete user group record.

Text	Could not delete user group record.
Explanation	The user group record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-803 Could not delete menu record.

Text	Could not delete menu record.
Explanation	The menu record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-804 Could not delete task record.

Text	Could not delete task record.
Explanation	The task record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-805 Could not delete host session record.

Text	Could not delete host session record.
Explanation	The host session record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-806 Could not delete host printer session record.

Text	Could not delete host printer session record.
Explanation	The host printer session record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-807 Could not delete color scheme record.

Text	Could not delete color scheme record.
Explanation	The color scheme record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-808 Could not delete key scheme record.

Text	Could not delete key scheme record.
Explanation	The key scheme record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-809 Could not delete translation table record.

Text	Could not delete translation table record.
Explanation	The translation table record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-810 Could not delete physical keyboard table record.

Text	Could not delete physical keyboard table record.
Explanation	The physical keyboard table record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-811 Could not delete terminal function code table record.

Text	Could not delete terminal function code table record.
Explanation	The terminal function code table record <i>object-name</i> in the share file could not be deleted.
Action	Check whether you have the required privileges to delete objects from the share file. Check your hard disk for errors.

19-821 Could not rename user properties record.

Text	Could not rename user properties record.
Explanation	The user properties record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-822 Could not rename user group record.

Text	Could not rename user group record.
Explanation	The user group record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-823 Could not rename menu record.

Text	Could not rename menu record.
Explanation	The menu record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-824 Could not rename task record.

Text	Could not rename task record.
Explanation	The task record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-825 Could not rename host session record.

Text	Could not rename host session record.
Explanation	The host session record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-826 Could not rename host printer session record.

Text	Could not rename host printer session record.
Explanation	The host printer session record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-827 Could not rename color scheme record.

Text	Could not rename color scheme record.
Explanation	The color scheme record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-828 Could not rename key scheme record.

Text	Could not rename key scheme record.
Explanation	The key record <i>object-name</i> in the share file could not be renamed.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-832 Could not rename system object.

Text	Could not rename system object.
Explanation	The object <i>object-name</i> in the share file could not be renamed because it is a default system object.
Action	You cannot rename the default system objects.

19-841 Could not create user properties record.

Text	Could not create user properties record.
Explanation	The user properties record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-842 Could not create user group record.

Text	Could not create user group record.
Explanation	The user group record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-843 Could not create menu record.

Text	Could not create menu record.
Explanation	The menu record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-844 Could not create task record.

Text	Could not create task record.
Explanation	The task record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-845 Could not create host session record.

Text	Could not create host session record.
Explanation	The host session record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-846 Could not create host printer session record.

Text	Could not create host printer session record.
Explanation	The host printer session record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-847 Could not create color scheme record.

Text	Could not create color scheme record.
Explanation	The color scheme record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-848 Could not create key scheme record.

Text	Could not create key scheme record.
Explanation	The key scheme record <i>object-name</i> could not be created in the share file.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-861 Could not duplicate user properties record.

Text	Could not duplicate user properties record.
Explanation	The user properties record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-862 Could not duplicate user group record.

Text	Could not duplicate user group record.
Explanation	The user group record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-863 Could not duplicate menu record.

Text	Could not duplicate menu record.
Explanation	The menu record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-864 Could not duplicate task record.

Text	Could not duplicate task record.
Explanation	The task record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-865 Could not duplicate host session record.

Text	Could not duplicate host session record.
Explanation	The host session record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-866 Could not duplicate host printer session record.

Text	Could not duplicate host printer session record.
Explanation	The host printer record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-867 Could not duplicate color scheme record.

Text	Could not duplicate color scheme record.
Explanation	The color scheme record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-868 Could not duplicate key scheme record.

Text	Could not duplicate key scheme record.
Explanation	The key scheme record <i>object-name</i> in the share file could not be duplicated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-880 Could not update system properties.

Text	Could not update system properties.
Explanation	The system properties record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors

19-881 Could not update user properties record.

Text	Could not update user properties record.
Explanation	The user properties record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-882 Could not update user group record.

Text	Could not update user group record.
Explanation	The group record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-883 Could not update menu record.

Text	Could not update menu record.
Explanation	The menu record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-884 Could not update task record.

Text	Could not update task record.
Explanation	The task record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-885 Could not update host session record.

Text	Could not update host session record.
Explanation	The host session record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-886 Could not update host printer session record.

Text	Could not update host printer session record.
Explanation	The host printer session record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-887 Could not update color scheme record.

Text	Could not update color scheme record.
Explanation	The color scheme record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-888 Could not update key scheme record.

Text	Could not update key scheme record.
Explanation	The key scheme record <i>object-name</i> in the share file could not be updated.
Action	Check whether you have write privileges for objects in the share file. Check your hard disk for errors.

19-890 Fatal error writing key scheme to the share file.

Text	Fatal error writing key scheme to the share file.
Explanation	Fatal error writing key scheme <i>object-name</i> to the share file.
Action	Check your hard disk. Restore your share file from a backup and retry.

19-900 Share file write-protected or locked.

Text	Share file write-protected or locked.
Explanation	Share file is write-protected or locked. You can only list and view the share file objects. The commands Modify, Delete, Duplicate, New and Make Public cannot be used because they require write-access permission.
Action	Check with your system administrator if you need to write to the share file.

20-001 Error removing the user's private objects.

Text	Error removing the user's private objects.
Explanation	Deleting a user properties record partly failed. The user properties record was deleted, but an error occurred while deleting the user's private objects. Unreferenced objects which are not visible in the Configuration Manager remain in the share file.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

20-004 Could not read user properties record.

Text	Could not read user properties record.
Explanation	A fatal error occurred while reading the user properties for user <i>user-name</i> .
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

20-007 Invalid user ID.

Text	Invalid user ID.
Explanation	You entered an invalid user ID. The user ID can be 1 to 16 characters long and may contain embedded blanks.
Action	Check and correct the user ID.

20-008 Invalid object name.

Text	Invalid object name.
Explanation	You entered an invalid object name. The object name can be 1 to 32 characters long.
Action	Check and correct the object name.

20-009 Passwords do not match.

Text	Passwords do not match.
Explanation	The passwords you entered in the "Password" and "Confirm Password" fields do not match.
Action	Check and correct the password.

20-010 "Confirm Password" field is empty.

Text	"Confirm Password" field is empty.
Explanation	You did not enter your password in the "Confirm Password" field.
Action	Confirm your password in this field.

20-011 "Password" field is empty.

Text	"Password" field is empty.
Explanation	You did not enter a password in the "Password" field. The password can be 1 to 16 characters long.
Action	Enter a valid password.

20-013 Invalid embedded blanks in name.

Text	Invalid embedded blanks in name.
Explanation	Embedded blanks are not allowed for this object name.
Action	Enter a valid name.

20-014 Administrator user ID may not be deleted.

Text	Administrator user ID may not be deleted.
Explanation	The administrator's user ID may not be deleted. You can only modify or rename the administrator's user ID.
Action	No action required.

20-015 No name specified.

Text	No name specified.
Explanation	You must enter a name for the object.
Action	Enter a name.

20-016 Invalid HLLAPI DLL name.

Text	Invalid HLLAPI DLL name.
Explanation	You did not enter a HLLAPI DLL name or you entered an invalid name. The name may also contain path information.
Action	Enter a valid HLLAPI DLL name.

20-017 Invalid HLLAPI entry name.

Text	Invalid HLLAPI entry name.
Explanation	You did not enter a HLLAPI entry function name or you entered an invalid name.
Action	Enter a valid HLLAPI entry function name.

20-018 Object name too long.

Text	Object name too long.
Explanation	The name entered for the BS2000 P-key is too long. Maximum length is 16 characters.
Action	Enter a valid name.

20-020 Name already in use.

Text	Name already in use.
Explanation	The name <i>name</i> you entered is already in use for an object of the current user.
Action	Choose a different name for this object.

20-027 Invalid object name.

Text	Invalid object name.
Explanation	You entered an invalid name for the object. The name can be 1 to 32 characters long and must not contain embedded blanks.
Action	Enter a valid name for the object.

20-100 Invalid session name.

Text	Invalid session name.
Explanation	You did not enter a session name. A session name can be 1 to 32 characters long.
Action	Enter a valid session name.

21-005 Value entered is out of range.

Text	Value entered is out of range.
Explanation	The value entered for the TCP/IP port is not valid. The valid value range is 0 to 9999.
Action	Enter a value within the specified range.

21-801 Missing TCP/IP address or host name.

Text	Missing TCP/IP address or host name.
Explanation	You did not enter a TCP/IP address or host name. This field may not be blank.
Action	Enter a TCP/IP address or host name.

21-802 Invalid character in BS2000 station name.

Text	Invalid character in BS2000 station name.
Explanation	An invalid character was found in the BS2000 name. The first character of this name must not be a number.
Action	Enter a correct BS2000 station name.

21-803 Missing device name.

Text	Missing device name.
Explanation	Missing device name. The device name can be 1 to 8 characters long.
Action	Enter a device name.

21-804 Invalid value for columns.

Text	Invalid value for columns.
Explanation	The value for columns is not valid. The value range is 20 to 200 for TN3270 sessions, and 80 to 255 for VT sessions.
Action	Enter a valid value in the specified range.

21-805 Invalid value for rows.

Text	Invalid value for rows.
Explanation	The value for rows is not valid. The value range is 24 to 80 for TN3270 sessions, and 24 to 7380/columns for VT sessions.
Action	Enter a valid value in the specified range.

21-900 Number of group links exceeded.

Text	Number of group links exceeded.
Explanation	Cannot add object to the group. The object is already linked to 32 other groups. It is not possible to link one object to more than 32 groups.
Action	Check your group design.

21-901 Error deleting group link for objects.

Text	Error deleting group link for objects.
Explanation	The group could be deleted, but an error occurred while deleting the group link in the objects. This leads to inconsistent data for the objects.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

21-902 The group name is already in use.

Text	The group name is already in use.
Explanation	Cannot add the group <i>group-name</i> . The group name is already in use.
Action	Enter a different name for the group.

21-903 Cannot delete or rename the group EVERYONE.

Text	Cannot delete or rename the group EVERYONE.
Explanation	The group EVERYONE is a required system group which must exist with this name.
Action	No action required.

21-904 Could not read user properties record.

Text	Could not read user properties record.
Explanation	A fatal error occurred while reading the user properties record for user <i>user-name</i> .
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

22-000 A public object with the name already exists.

Text	A public object with the name already exists.
Explanation	Cannot make the object public. A public object with the name already exists.
Action	Check the objects for data consistency.

22-001 Could not make object public.

Text	Could not make object public.
Explanation	Could not make the object public. An error with error-code <i>error-code</i> occurred.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

24-000 Invalid task description.

Text	Invalid task description.
Explanation	You must enter a valid task description. The description can be 1 to 62 characters long.
Action	Enter a valid task description.

24-001 Cannot delete a Software AG task.

Text	Cannot delete a Software AG task.
Explanation	Software AG tasks are required system tasks which cannot be deleted.
Action	No action required.

24-002 Invalid program name for the task.

Text	Invalid program name for the task.
Explanation	You did not enter a valid program name for the program to be run by this task.
Action	Enter the name (and path) for the program to be run by this task.

24-003 Task is in use as startup task or shutdown task.

Text	Task is in use as startup task or shutdown task.
Explanation	You are not allowed to rename or delete this task. This task is also your startup task or shutdown task.
Action	No action required.

24-007 Invalid extension in task program name.

Text	Invalid extension in task program name.
Explanation	The program name for the task does not have a valid extension. The program name must have an extension of .COM or .EXE .
Action	Check and correct the program name.

24-008 Cannot delete object.

Text	Cannot delete object.
Explanation	You are not allowed to delete this object. The object is either a system object, or it is a public object and you are not logged in as administrator.
Action	Contact your administrator if you need to delete the object.

24-010 Cannot duplicate Software AG task.

Text	Cannot duplicate Software AG task.
Explanation	You cannot duplicate a Software AG task. Software AG tasks are predefined tasks required by the system.
Action	No action required.

24-011 Cannot rename object.

Text	Cannot rename object.
Explanation	You are not allowed to rename this object. The object is either a system object, or it is a public object and you are not logged in as administrator.
Action	Contact your administrator if you need to rename the object.

24-012 Cannot modify private objects.

Text	Cannot modify private objects.
Explanation	You are not allowed to modify this object. This is a private object of a user and you are logged in as administrator.
Action	Contact the owner of the object if it needs to be modified.

24-013 Cannot delete private objects.

Text	Cannot delete private objects.
Explanation	You are not allowed to delete this object. This is a private object of a user and you are logged in as administrator.
Action	Contact the owner of the object if it needs to be deleted.

24-014 Cannot rename private objects.

Text	Cannot rename private objects.
Explanation	You are not allowed to rename this object. This is a private object of a user and you are logged in as administrator.
Action	Contact the owner of the object if it needs to be renamed.

24-015 Cannot modify public objects.

Text	Cannot modify public objects.
Explanation	You are not allowed to modify this object. This is a public object and you are not logged in as administrator.
Action	Contact your administrator if you need to modify the object. You also can duplicate the object and then modify it as your private object.

24-020 Invalid P-key name.

Text	Invalid P-key name.
Explanation	You did not enter a valid name for the P-key. The name can be 1 to 16 characters long.
Action	Enter a valid name.

24-021 Error reading the key definition details.

Text	Error reading the key definition details.
Explanation	An error occurred while reading the detailed commands used in the key definition.
Action	Restore your share file from a backup and retry.

25-000 Error deleting scheme.

Text	Error deleting scheme.
Explanation	An error occurred in the delete scheme function. The scheme could not be deleted.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

25-001 Unable to create new scheme.

Text	Unable to create new scheme.
Explanation	An error occurred in the create scheme function. The scheme could not be created.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

25-002 A scheme with this name already exists.

Text	A scheme with this name already exists.
Explanation	The name you entered is already used by another scheme.
Action	Correct and enter a unique name.

25-003 Error setting scheme for this session.

Text	Error setting scheme for this session.
Explanation	An error occurred in the setting scheme function in the session properties.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

25-004 No P-key schemes are currently defined.

Text	No P-key schemes are currently defined.
Explanation	No BS2000 P-key schemes are defined in the share file.
Action	Currently there is no default BS2000 P-key scheme in the share file from the installation. You have to create your own P-key schemes.

25-006 Error in P-key content.

Text	Error in P-key content.
Explanation	There is an error in the definition of the BS2000 P-key at the shown position. The element is not a valid 9750 terminal function.
Action	Check and correct the P-key definition.

25-008 No color schemes currently defined.

Text	No color schemes currently defined.
Explanation	No color schemes are defined in the share file. This should never happen.
Action	Check your hard disk for errors. Restore your share file from a backup and retry.

25-009 No valid key scheme selected.

Text	No valid key scheme selected.
Explanation	You did not select a key scheme or the selected scheme was not found in the share file.
Action	Select a valid scheme. Check your share file.

25-010 No valid color scheme selected.

Text	No valid color scheme selected.
Explanation	You did not select a color scheme or the selected scheme was not found in the share file.
Action	Select a valid scheme.

30-018 Same value for background and foreground colors.

Text	Same value for background and foreground colors.
Explanation	The settings for the background and foreground colors in the color scheme have the same value. No characters will be visible in the terminal emulation screen.
Action	Correct the color setting in the color scheme.

