

Message Class 1017 - EntireX RPC Online Maintenance Facility

Messages have the format:

1017nnnn

where 1017 is the message class, and

nnnn is the message number in the range 0000 - 9999.

Overview of Messages

10170000 | 10170001 | 10170002 | 10170003 | 10170004 | 10170005 |
 10170006 | 10170007 | 10170008 | 10170009 | 10170010

10170000

Reserved

Explanation

N.A.

Action

N.A.

10170001 Invalid arg= argument

Explanation EntireX RPC Online Maintenance Facility was started with an invalid argument. The menu could not be started.

Action Check documentation for valid arguments and start EntireX RPC online maintenance facility again.

10170002 Input command invalid command

Explanation An invalid command was entered. The command was ignored.

Action Check documentation for valid commands and syntax and issue again. The Online Maintenance Facility will continue to run.

10170003 Server already active

Explanation An attempt was made to start an RPC server although a server instance is already running. Multiple server instances cannot use the same shared memory block at the same time.

Action Check reasons:

1. An instance may be running by mistake: cancel this instance (CICS: with CEMT INQUIRE TASK, force, reload the shared memory).
2. If more than 1 instance is required, generate a new shared memory block (ERXMAIN) and restart with the new block.

10170004 A server instance is already running with this control block

Explanation There was an attempt to change the content of a shared memory block which is used by a running server instance. The change has been rejected.

Action If the changes are required for the current shared memory block, stop the associated server first.

If the changes are meant for a different server (different shared memory block), first switch to the other memory block.

10170005 Cannot start RPC server: Reason= reason-code

Explanation The request to start an RPC server failed for a reason other than "1017 0003 Server already active". The (system-dependent) reason code will be added to this error message.

Action See reason code.

10170006 Cannot load member

Explanation Either the Online Maintenance Menu was started with an invalid memory control block (default: MEM=ERXMAIN) or an invalid command (MEM=) was issued that refers to an unknown memory block.

- Action**
1. If the message is displayed during the start of the Online Maintenance menu, check if the memory control block can be accessed.
 2. If the message is displayed after a MEM= command, check for typing errors and if the target control block is available.

10170007 No resources: resource

Explanation This is a collecting message for system resource problems. The type of resource problems will be added into this message.

Action Check *resource* for more information.

10170008 RPC server termination in progress

Explanation For information purposes. The RPC server received a shutdown command, either issued via the Online Maintenance Menu or some external control facility.

Action None. The server terminates.

10170009 Invalid ERX control block found: <Name of control block>

Explanation For some unknown reasons, the EntireX Online Maintenance menu received an invalid control block. The Online Maintenance menu terminates.

Action Contact Software AG support.

10170010 Server successfully launched

Explanation Informational. The user requested to start an RPC server instance.

Action None. Check launch process if RPC server starts successfully.