

Message Class 1018 - EntireX RPC-ACI Bridge

Messages have the format:

1018nnnn

where 1018 is the message class, and

nnnn is the message number in the range 0000 - 9999.

Overview of Messages

| | | | | | |
|----------|----------|----------|----------|----------|----------|
| 10180000 | 10180001 | 10180002 | 10180003 | 10180004 | 10180009 |
| 10180010 | 10180011 | 10180012 | 10180013 | 10180015 | 10180022 |

10180000

Explanation This error can occur if the ACI server sends an invalid message. The ACI server is not able to return an error code. It can only send a valid message or quit the Broker communication.

Action Correct the ACI server.

10180001 **Process request and reply: illegal action <number indicating action>**

Explanation During request/reply processing the next action is illegal in the current state.

Action Contact Software AG support.

10180002 **<Broker Exception with detailed message>**

Explanation An exception with the Broker for ACI occurred during SEND.

Action See message class and message code of the Broker exception and follow detailed message.

10180003 **<Broker Exception with detailed message>**

Explanation An exception with the Broker for ACI occurred during RECEIVE.

Action See message class and message code of the Broker exception and follow detailed message.

10180004 <Broker Exception with detailed message>

Explanation An exception with the Broker for ACI occurred during shutdown and logoff.

Action See message class and message code of the Broker exception and follow detailed message.

10180009 <Exception with detailed message>

Explanation An exception occurred while formatting the message. In most cases, the reason is an inconsistency in the metadata.

Action See detailed message or contact Software AG support.

10180010 Compression=off not possible

Explanation An RPC with compression 0 is not supported.

Action Change compression to 1 or 2.

**10180011 Type of marshalling not allowed
or
Unsupported call type <number of call type>**

Explanation There are two reasons for this error code.

1. for the marshalling property the values 'cobol', 'natural', and '' are allowed. Reason: The value of the property may be invalid.
or:
The RPC from the client is in the wrong marshalling.
2. The RPC call type is wrong.

Action Check configuration and client.

10180012 <Exception with detailed message>

Explanation This exception occurs in message processing.

Action See detailed message and contact Software AG support.

10180013 **Preparing message failed, see log for details**
or:
Message received from server does not fit buffer

Explanation There are two reasons for this error code:

1. Marshalling of message failed before sending to CICS ECI.
2. The received message does not have the expected layout and the values cannot be unmarshalled from it.

Action Check the following metadata for consistency or contact Software AG support:

- IDL file, see *Software AG IDL File*.
- Server mapping file. A server mapping file is an EntireX Workbench file with extension .svm or .cvm. See *Server Mapping Files for COBOL*.
- Adapter connections.

10180015 **Transformation error on request: <Exception with detailed message>**

Explanation This exception occurs in message processing.

Action See detailed message or contact Software AG support.

10180022 **Unsupported command <command>**
or
Exception: <Exception with detailed message>

Explanation There are two reasons for this error code:

1. An unknown internal command is used.
2. An exception occurred during action processing.

The log files contain a stack trace.

Action See detailed message and log files or contact Software AG support.