

EntireX Broker Security Server for BS2000/OSD

These messages are returned by the EntireX Broker Security Server for BS2000/OSD and have the format `SECxnnnn`

where SEC indicates a security message

x indicates the type of message

I information

E error; function cannot be performed

T trace message

nnn is the message number

SECI0001 Broker Security Server V n.n.n started

Explanation Broker Security Server start up message.

Action None.

SECI0002 Broker Security Server V n.n.n terminated normally

Explanation Broker Security Server termination message.

Action None.

SECI0003 Broker Security Server V n.n.n terminated with errors

Explanation Broker Security Server termination message. This message always appears together with a SECEnnn message.

Action None.

SECI0004 Running with FORCE = YES, the security CMP will be newly initialized

Explanation If the Broker Security Server was started with FORCE= ' YES ' and the security common memory pool was newly initialised the above message is issued.

Action None.

SECE0001 Unexpected return code from DISMP

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0002 Unexpected return code from SOLSIG

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0003 Unexpected return code from ENAEI

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0004 Unexpected return code from DISEI

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0005 Unexpected return code from ENAMP

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0006 Unexpected return code from ENAMP

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0007 Unexpected return code from REQMP

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0008 Unexpected return code from CLEANUP

Explanation Server will terminate with dump and a SECT0008 Return Code: rc is issued.

Action Contact Software AG support.

SECE0009 Unexpected end of security CMP detected

Explanation An internal error occurred. The server will terminate with dump and a SECI0003 message is issued.

Action Contact Software AG support.

SECE0010 Broker Security Server already active

Explanation The Broker Security Server found an active security common memory pool in the system. The startup process is suppressed.

Action If there is no other server active in the system, the FORCE parameter may be used to newly initialize the security common memory pool.

SECT0001 Authentication successful

Explanation This message follows a SECT0013 USERID user ID message.

Action None.

SECT0002 Authentication failed, password mismatch

Explanation The user ID is known, the supplied password does not match. This message follows a SECT0013 USERID user ID message.

Action None.

SECT0003 Authentication failed, password mismatch

Explanation The user ID is known, no password exists but there was one supplied. This message follows a SECT0013 USERID user ID message.

Action None.

SECT0004 Authentication failed, user unknown or server not authorized

Explanation Either the user ID is unknown or the Broker Security Server has no privileges to access the user catalog, e.g. it does not run under a privileged user ID (TSOS). This message follows a SECT0013 USERID user ID message.

Action None.

SECT0005 Authentication failed, error from encryption

Explanation The password could not be encrypted. This message follows a SECT0013 USERID user ID message.

Action None.

SECT0006 Authentication failed, unsupported crypt algorithm

Explanation The operating system returned an unexpected encryption mode.

Action None.

SECT0007 Security CMP established successfully

Explanation The Security Server common memory pool was established and initialized successfully.

Action None.

SECT0008 Return Code: rc

Explanation This message always occurs together with a SECEnnn message where rc contains the return code from the corresponding BS2000/OSD macro or Security Server function, respectively.

Action None.

SECT0009 Security CMP disabled successfully

Explanation The Security Server common memory pool was disabled and deleted.

Action None.

SECT0010 Security CMP disabled successfully, CMP kept

Explanation The Security Server common memory pool was disabled but could be not deleted due to other BS2000/OSD tasks holding the pool.

Action None.

SECT0011 Authentication failed, reason is unknown

Explanation The user authentication failed and the Security Server could not determine a reason for that.

Action None.

SECT0012 Security CMP cleanup done

Explanation The Security Server cleaned its request queue from not posted authentication requests.

Action None.

SECT0013 USERID: userID

Explanation This message occurs together with one of the following messages SECT0001, SECT0002, SECT0003, SECT0004, SECT0005, SECT0006, where userID is the user for which the authentication was done.

Action None.

SECT0014 ENAMP done

Explanation The Security Server common memory pool was enabled successfully. This message follows a SECT0008 Return Code: rc message.

Action None.