


# %KN, %KO and %KS - Siemens Function-Key Logic



These commands are only applicable to Siemens terminals.

%KN	With terminal types 8160, 974n, 9750 - 9755	This command causes the literals "%K1" to "%K20" to be loaded to the keys P1 to P20.
	With terminal types 9756, 9758, 976n	This command causes the send-key codes "F1" to "F20" to be loaded to the keys P1 to P20.
%KO	This command causes the literals "01" to "20" as well as the send-key code "F5" to be loaded to the keys P1 to P20.	
%KS	This command causes the literals "A" to "T" as well as the send-key code "F5" to be loaded to the keys P1 to P20.	
%KON	If an "N" is specified after the terminal command %KN, %KO or %KS, only the corresponding function-key mode (KN, KO or KS mode) will be activated, but no values will be loaded to the P-keys.	
%KNN		
%KSN		

See also *Natural under BS2000/OSD* (in the *Operations* documentation).