

Listing Report Definitions

The List Report Definition (LR) function lists all reports. From the list, you can

- directly update the DBID and Auto Start report options. All report definitions on the screen can be updated in a single operation.
- use commands to maintain a report. The commands are entered on the selection line preceding the name of the report.

▶ **To access the List Report Definition function**

1. Enter the code LR on the command line.

The Report Definitions screen appears as shown in the following example:

20:34:50		A D A B A S - R E V I E W				2003-07-07	
		Report Definitions				LOCL=00222	
Sel	Report Name	DBID	Auto	Sum/ Detail	Hist	Display Program	
—	APPLICATION FILE FIELD USAGE	12345	N	S	N	SR-00030	
—	BUFFER POOL DISPLAY	12345	N	S	N	BUFFPOOL	
_>	COMMAND LOGGING	12345	N	D	N	SR-00025	
_>	COMMANDS BY HOUR	12345	N	S	N	SR-00004	
—	COST ACCOUNTING EXAMPLE	12345	N	S	N	SR-00028	
—	DESCRIPTOR USAGE REPORT	12345	N	S	N	SR-00020	
—	EXCEPTIONAL RESPONSE CODES	12345	N	S	N	SR-00002	
—	FILE USAGE	12345	N	S	N	SR-00031	
—	HOURLY DATABASE OVERVIEW	12345	N	S	N	SR-00032	
—	IO COUNT BY HOUR	12345	N	S	N	SR-00023	
—	IO SUMMARY BY RABN	12345	N	S	N	SR-00022	
Command:							
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---							
Help		Exit Mod		-	+	Menu	

The columns of the Report Definitions screen are explained as follows:

Sel	Selection line. Enter commands on the selection line preceding the report name. For a list of available commands, enter a ? on the selection line.
Report Name	An arrow (>) preceding the report name indicates that the report has been started.
DBID	Database from which the report collects data. If this field is left blank, you are prompted for the DBID when you start the report.
Auto	Indicates whether the report is started automatically at database initialization.
Sum/Detail	"S" indicates a summary report; "D" indicates a detail report.
Hist	Indicates whether the report writes history data.
Display Program	Lists the name of the program generated to display report output online.

PF7 and PF8 have been provided as scroll keys. If more than one screen of report names exists, PF8 or (+) scrolls the list forward and PF7 or (-) scrolls the list backward.

 **To update the values of the DBID and/or Auto Start report options**

1. Press PF4 (Mod).

All DBID and Auto fields become modifiable (modify mode).

2. Modify the values as required.
3. Press PF5 (Updat) to save the changes or PF3 (Exit) to abandon your changes.

Only the report definitions listed on the current screen may be modified. Pressing PF8 to move forward or PF7 to move backward cancels the modify mode.

 **To issue a command from the Report Definitions screen**

1. Enter one of the following commands on the selection line preceding the report name.

Cmd	
CD	Change DBID
CP	Change display program
CR	Copy report definition
DD	Display report information
EB	Edit buffer pool report
EL	Edit Pulse Report
EX	Edit Cluster Services Report
EP	Edit display program
ER	Edit report
PR	Purge report definition
RG	Regenerate display program
ST	Start report
VW	View started report