

CORnnn Messages

CORnnn messages are issued by the Adabas System Coordinator kernel.

Overview of Messages

COR001S	COR002S	COR003S	COR004S	COR005E	COR006S	COR007E
COR008S	COR009S	COR010S	COR012S	COR015S	COR016S	COR017I
COR019E	COR020I	COR022S	COR023S	COR026E	COR028E	COR030I
COR031I	COR032S	COR033S	COR034S	COR035S	COR037I	COR038E
COR040S						

COR001S RUNTIME ENVIRONMENT CANNOT INITIALIZE, KERNEL LOAD ERROR

Explanation The Adabas System Coordinator client (CORSnn) failed to locate or load the runtime kernel module CORKRN.

Action Ensure that the load library containing the kernel module is available to the TP monitor or batch job that issued the message.

COR002S RUNTIME ENVIRONMENT CANNOT INITIALIZE, CONFIGURATION FILE RESPONSE=nnnn, SUBCODE=nnnn

Explanation A configuration module (CORCFG) has been located that indicates the SVC, DBID, and file number of the Adabas System Coordinator configuration file. An error occurred when trying to read this configuration file.

Action Refer to the *Adabas Messages and Codes* documentation to determine the reason for the error.

COR003S FAILED TO REGISTER JOB WITH COR DAEMON, RESPONSE=nnnn, SUBCODE=nnnn. SERVICE CONTINUING IN LOCAL MODE

Explanation The job is defined to run in daemon-mode, but an active local daemon could not be found.

Action A response code 148 is returned if the required daemon server is not running. For other errors, refer to the *Adabas Messages and Codes* documentation to determine the reason for the error. The job continues in local mode. COR daemon services are not available.

If daemon-mode is critical to the correct operation of the job or service you should designate one or more add-on products with the “CRITICAL” specification in the COR configuration module (CORCFG). See message COR040S for further information.

**COR004S GROUP group-name NOT FOUND IN CONFIGURATION FILE
RESPONSE=nnnn, SUBCODE=nnnn**

Explanation An error occurred when attempting to read the defined group parameters.

Action If the Adabas System Coordinator group parameters have not been defined, use the SYSCOR online application to define them and resubmit the job.

**COR005E RUNTIME CONFIGURATION MODULE CORCFG NOT LOCATED – JOB
TYPE DEFAULTS ASSUMED**

Explanation The configuration module CORCFG cannot be loaded. This module contains the SVC, DBID, and file number for reading the configuration file. The job continues to run but the Adabas System Coordinator operates in a default mode for the job. This may be acceptable, depending on the optional products installed.

Action Refer to the section Installation for information about assembling a configuration module.

COR006S NO MEMBERS DEFINED FOR DAEMON GROUP #####

Explanation A job is defined to expect an Adabas System Coordinator group. The group has been defined but no daemon members have been defined within the group.

Action Use the SYSCOR online application to define required daemon members in the group.

**COR007E NO DAEMON CONTACTED FOR COORDINATOR GROUP #####, JOB
CANNOT INITIALIZE**

Explanation A job is defined to expect an Adabas System Coordinator group, but none of the Coordinator daemons defined in the group are active on this system.

Action After ensuring that the local Coordinator daemon is started, restart the job.

COR008S CANNOT LOCATE ID TABLE FOR SVC nnn

Explanation A job is defined to expect an Adabas System Coordinator group, but no ID table was found for the Adabas SVC number specified in the group definition.

Action Use the SYSCOR online application to enter the correct SVC number in the group record.

COR009S ##### IXLCACHE READ ERROR, RC=##, RSN=###

Explanation The Coordinator daemon is running in an IBM sysplex environment and is using the coupling facility. An error occurred when trying to access data from the coupling facility cache memory. The coupling facility may be improperly set up or defined.

Action Ensure that the cache structure is defined correctly in the Adabas System Coordinator group.

COR010S ##### IXLCACHE WRITE ERROR, RC=##, RSN=###

Explanation The Coordinator daemon is running in an IBM sysplex environment and is using the coupling facility. An error occurred when trying to write data to the coupling facility cache memory. The coupling facility may be improperly set up or defined.

Action Ensure that the cache structure is defined correctly in the Adabas System Coordinator group.

COR012S MEMBER ##### FAILED TO JOIN SYSPLEX GROUP #####, RC=##, RSN=###

Explanation The Coordinator daemon failed to connect to the sysplex group. The sysplex may not be properly defined. The return and reason codes are from the IXCJOIN macro.

Action Consult the *IBM Sysplex Services Reference* to determine the cause of the problem.

COR015S ##### IXCQUERY ERROR, RC=##, RSN=###

Explanation A sysplex IXCQUERY service failed. The return and reason codes are from the IXCQUERY macro.

Action This is an internal error. Contact your Software AG technical support representative.

COR016S ##### IXLCONN ERROR, RC=##, RSN=###

Explanation The Coordinator daemon is running in an IBM sysplex environment and using the coupling facility. An error occurred when trying to connect to the coupling facility cache structure defined in the Adabas System Coordinator group record.

Action Ensure that the required cache structure is defined in the CFRM policy for this sysplex.

COR017I NO RUNTIME CONTROL FOUND FOR ##### - ADD-ON PRODUCTS ARE DEACTIVATED

Explanation The configuration file does not contain a runtime control record for this job. The Adabas System Coordinator and installed products will be deactivated until a run-time control is defined and the job is restarted.

It is likely that the Adabas System Coordinator link stub was added to the link module but no runtime control was defined for the job.

Action Use one of the online administration applications (SYSAVI, SYSAFP, SYSATM) to define a runtime control; then restart the job.

COR019E ##### ICXMSGO SENDTO ##### ERROR, RC=##, RSN=###

Explanation An error occurred when sending a message from one Coordinator daemon to another in an IBM sysplex.

Action Consult the *IBM Sysplex Services Reference* to determine the cause of the error.

COR020I SYSPLEX INTERFACE COMMAND QUEUE AT #####

Explanation Issued at startup of a Coordinator daemon, this message displays the address of the command queue used for communication among the Coordinator daemons.

Action None. This message is for information only.

COR022S ##### IXLCACHE DELETE ERROR, RC=##, RSN=###

Explanation The Coordinator daemon is running in an IBM sysplex environment and is using the coupling facility. An error occurred when trying to delete data from the coupling facility cache memory. The coupling facility may be improperly set up or defined.

Action Ensure that the cache structure is defined correctly in the Adabas System Coordinator group.

COR023S ##### IXLCACHE STATS ERROR, RC=##, RSN=###

Explanation The Coordinator daemon is running in an IBM sysplex environment and is using the coupling facility. An error occurred when trying to read statistical information from the coupling facility cache memory.

Action Ensure that the cache structure is defined correctly in the Adabas System Coordinator group. Note: This message will appear if you attempt to use the SYSCOR session monitoring "Display cache statistics" service, and the Coordinator daemon is not running with a coupling facility cache structure.

**COR026E CONFIGURATION FILE ##### / ##### READ ERROR (RSP ###) JOB #####
WAITING FOR ACTIVATION**

Explanation The database containing the configuration file is not active, and it has been requested (in the CORCFG configuration module) that client jobs should wait for the file to be activated. Adabas System Coordinator will attempt to read the configuration file every 15 seconds.

Action Activate the database containing the configuration file as soon as possible.

**COR028E CONFIGURATION FILE ##### / ##### READ ERROR (RSP ##),
INITIALIZATION DEFERRED FOR JOB #####**

Explanation The job parameter could not be read from the configuration file. Initialization of System Coordinator and add-on products is deferred.

It is likely that the database containing the configuration file is inactive (response code 148).

The COR client will automatically attempt a periodic retry if it receives an error reading the configuration file. This avoids the need to recycle jobs when the file becomes available again.

Action Activate the database containing the configuration file as soon as possible.

**COR030I RESPONSE ###, RETRY ACTIVE FOR FILE ##### / ##, JOB=#####,
COMMAND=##**

Explanation Command retry has been activated for the indicated response code, and it has been specified that a console message is to be issued whenever an retry is attempted.

Action Take appropriate (installation-defined) action.

**COR031I RESPONSE ###, RETRY ABANDONED FOR FILE ##### / ##, JOB=#####,
COMMAND=##**

Explanation The required number of command retries has been attempted, but the command has still not completed successfully. Retry is abandoned.

Action Take appropriate (installation-defined) action.

COR032S Memory Pool enable failure, RC=#####, Pool=#####

Explanation BS2000 only. A request to enable a memory pool has failed.

Action Contact your Software AG technical support representative.

COR033S Memory Pool allocation failure,RC=#####,Pool=#####

Explanation BS2000 only. There has been an error during allocation of a System Coordinator memory pool. The failure is probably due to a shortage of memory in the global memory pool defined in the Coordinator group parameter for the service.

Action Increase the size of the global memory pool in the group definition.

COR034S KERNEL(CORKRN) NOT FOUND, SERVICE CANNOT CONTINUE

Explanation One or more add-on products has been defined with the “CRITICAL” specification in the configuration module (CORCFG). The Coordinator kernel module could not be located and the product will not function correctly. All Adabas requests will be rejected with response 101 subcode 58.

Action Make the load library containing the COR kernel available, and restart the job or service.

COR035S SERVICE CANNOT CONTINUE, CRITICAL PRODUCTS ARE NOT OPERATIONAL

Explanation One or more add-on products has been defined with the “CRITICAL” specification in the configuration module (CORCFG). System Coordinator, or the product itself has detected that some product component is missing or not operational. All Adabas requests will be rejected with response 101 subcode 59.

There will normally be another COR or product message identifying the component in error.

Action Correct the error and restart the job or service.

COR037I SVC dump created

Explanation The Adabas System Coordinator daemon has produced an SVC dump dataset as a result of an abend. This message is only issued on z/OS systems when CORCFG specifies ZOSDUMP=SVC .

Action None

COR038E SVC dump failed, R15: hhhhhhhh

Explanation The Adabas System Coordinator daemon was configured to produce an SVC dump in the event of an abend. The SVC dump failed with the indicated error code (hhhhhhh) and a standard dump was produced instead.

Action Review the IBM SDUMPX documentation to determine the reason for the failure.

COR040S **FAILED TO REGISTER JOB WITH COR DAEMON, RESPONSE=nnnn,
SUBCODE=nnnn. CRITICAL SERVICE CANNOT CONTINUE**

Explanation The job is defined to. run in daemon-mode, but an active local daemon could not be found. One or more add-on products has been defined with the “CRITICAL” specification in the configuration module (CORCFG). In this mode, the daemon is considered to be critical to the correct operation of the job. All Adabas requests will be rejected with response code 101, subcode 59.

Action Make sure that the Coordinator daemon is active and restart the job or service.