


PCNTRL - Print-Control Characters

This Natural profile parameter specifies the line-advance characters for printing which are inserted in Column 0 of each print line.

Possible settings	Any character string	This parameter can be specified in character or hexadecimal format.
Default setting	Siemens Environments	X' 404142434445464748494A4B4C4D4E4F '
	IBM Environments	<p>The default setting (according to ASA standard settings) is:</p> <p>' 0 - '</p> <p>which means that a blank causes a line advance of 1 line, 0 of 2 lines and - of 3 lines.</p> <p> Warning: In any IBM environment, do not change the default setting of this parameter.</p>
Dynamic specification	yes	
Specification within session	no	