

Defining Field Properties

In this session, you will define the properties for a field.

▶ To define the properties for a field

1. In the **Code** field of the **Edit Map** menu, enter an E and, in the **Name** field, enter MAP001 (if it is not already entered).

The map editing screen appears and map MAP001 is displayed in the editing area.

2. Type in additional text as shown below:

```

Ob  _                               Ob D CLS ATT  DEL      CLS ATT  DEL
.                                     .   T  D   Blnk    T  I   ?
.                                     .   A  D   _      A  I   )
.                                     .   A  N   7      M  D   &
.                                     .   M  I   :      O  D   +
.                                     .   O  I   (
.
001  --010---+-----+-----030---+-----+-----050---+-----+-----070---+-----
*****
(XXXXXXXXX                PERSONNEL INFORMATION
(XXXXXXXXX

PLEASE ENTER NAME::XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX
PLEASE ENTER CITY::XXXXXXXXXXXXXXXXXXXXXXXXXXXX

TYPE IN?. TO STOP OR?? FOR HELP.

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help  Mset  Exit  Test  Edit  --   -   +   Full  <   >   Let
    
```

The question mark (?) shown in boldface is the delimiter character for intensified text fields.

3. Enter the field command .E as shown below:

```

Ob _                               Ob D CLS ATT DEL      CLS ATT DEL
.                                  .   T  D   Blnk   T  I   ?
.                                  .   A  D   _      A  I   )
.                                  .   A  N   7      M  D   &
.                                  .   M  I   :      O  D   +
.                                  .   O  I   (
.
001  --010---+-----+-----030---+-----+-----050---+-----+-----070---+-----
*****
(XXXXXXXXX                          PERSONNEL INFORMATION
(XXXXXXXXX

PLEASE ENTER NAME: .XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX
PLEASE ENTER CITY: :XXXXXXXXXXXXXXXXXXXXXXXXXXXX

TYPE IN?. TO STOP OR?? FOR HELP.

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help Mset Exit Test Edit -- - + Full < > Let

```

4. Press ENTER.

The extended field editing area for the field in which the command was entered appears:

```

Fld #NAME                                     Fmt A40
-----
AD= MIT'_'_____      ZP=          SG=          HE= _____      Rls 2
AL= _____          CD= ___      CV= _____          Mod User
PM= ___  DF=           DY= _____
EM= _____          SB= _____

001  --010---+-----+-----030---+-----+-----050---+-----+-----070---+-----
*****
(XXXXXXXXX                PERSONNEL INFORMATION
(XXXXXXXXX

PLEASE ENTER NAME: .XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX
PLEASE ENTER CITY: :XXXXXXXXXXXXXXXXXXXXXXXXXXXX

TYPE IN?. TO STOP OR?? FOR HELP.

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      HELP  Mset  Exit  <---  --->  --  -  +  <  >  Let
    
```

- In the **Fmt** field, replace the current value by A20, and, in the **HE=** field, enter 'HELP001' (within apostrophes) as shown below:

```

Fld #NAME                                     Fmt A20
-----
AD= MIT'_'_____ ZP=          SG=          HE= 'HELP001'_____ Rls 2
AL= _____ CD= ___ CV= _____ Mod User
PM= ___ DF=          DY= _____
EM= _____ SB= _____

001  --010---+---+---+---030---+---+---+---050---+---+---+---070---+---+
*****
(XXXXXXXXX                PERSONNEL INFORMATION
(XXXXXXXXX

PLEASE ENTER NAME: .XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX
PLEASE ENTER CITY: :XXXXXXXXXXXXXXXXXXXXXXXXX

TYPE IN?. TO STOP OR?? FOR HELP.

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      HELP Mset Exit <--- ---> -- - + < > Let
    
```

6. Press ENTER.

The extended field editing area disappears. HELP001 (which is yet to be created) is assigned as the help routine/help map to the field and the field length is reduced to 20:

```

Ob  _                               Ob D CLS ATT  DEL      CLS ATT  DEL
.                                     .   T  D   Blnk   T  I   ?
.                                     .   A  D   _      A  I   )
.                                     .   A  N   7      M  D   &
.                                     .   M  I   :      O  D   +
.                                     .   O  I   (
.
001  --010-----+-----+-----030-----+-----+-----050-----+-----+-----070-----+-----
*****
(XXXXXXXXX                                PERSONNEL INFORMATION
(XXXXXXXXX

PLEASE ENTER NAME::XXXXXXXXXXXXXXXXXXXXX
PLEASE ENTER CITY::XXXXXXXXXXXXXXXXXXXXX

TYPE IN?. TO STOP OR?? FOR HELP.

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help Mset Exit Test Edit -- - + Full < > Let
    
```

7. Press PF3 *twice*.

The **Edit Map** menu appears.

8. STOW MAP001 by using the appropriate menu function.

You can now proceed with *Creating and Testing a Help Map*.