

KEY - Setting Assignments to PA, PF and CLEAR Keys

This Natural profile parameter is used to assign settings to the CLEAR key, program attention keys (PA keys) and program function keys (PF keys) on video terminals.

Possible settings	any character string	Settings can be assigned to the keys PA1 to PA3, PF1 to PF24 and to the CLEAR key. The setting assigned to each key can be any character string. The character string must represent a Natural system command or a user command (user program). If the setting contains embedded blanks, it must be enclosed in apostrophes.
Default setting	none	
Dynamic specification	no	
Specification within session	yes	
Application Programming Interface	USR4005N	See <i>SYSEXT - Natural Application Programming Interfaces</i> in the <i>Utilities</i> documentation.

Assignments made with the profile parameter KEY are only valid from the Natural NEXT prompt.

The entire string specified with the profile parameter KEY must be enclosed in parentheses (except KEY=OFF). KEY=OFF un-assigns all keys.

Examples:

```
KEY=( PF4=OFF , PF1=HELP , PF3= ' EDIT MAP ' , PF2=USERPGM1 , CLR=LOGOFF )
KEY=OFF
KEY PF4=OFF
KEY PF3="EDIT MAP"
KEY CLR=LOGOFF
KEY OFF
```