## MAINPR - Override Default Output Report Number

This Natural profile parameter is used to override the default output report number for all Natural reports. It must be set to a valid printer number (0 - 31).

Possible settings	0 - 31	Valid printer number.
Default setting	0	
Dynamic specification	yes	
Specification within session	no	
Application Programming Interface	USR6002N	See SYSEXT - Natural Application Programming Interfaces in the Utilities documentation.

Specifying a MAINPR setting is the same as changing all of the DISPLAY, PRINT, WRITE or INPUT statements' printer references from the default setting (0) to the desired printer number.

A physical printer corresponding to the report number specified must be defined to Natural as described in the *Configuration Utility* documentation, section *Device/Report Assignments*.