

Message Class 4000 - EntireX Process Extractor

This message class contains messages that can occur with EntireX Process Extractor. The messages have the format:

4000nnnn

where 4000 is the message class, and

nnnn is the message number in the range 0000 - 9999

Overview of Messages

40000001 | 40000013 | 40000014 | 40000015 | 40000017

40000001 **Exception during processing call: <exception text>**

Explanation An unexpected error occurred during processing of a call from an RPC client or server.

Action Check the exception text for details.

40000013 **Character set for <character set type> not available**

Explanation No character set is available for an RPC call.

Action Contact Software AG support.

40000014 **Encoding LS=<char set name> not supported**

Explanation The specified character set is not available. Only character sets supported by the Java JVM can be used.

Action Change the configuration of the RPC client or server.

40000015 **<error message>**

Explanation An error during character set conversion.

Action See error message for details.

40000017 <detail message>

Explanation An error occurred on the connection from EntireX Process Extractor to the broker.

Action See error message for details. Check whether the broker is running and whether the connection from EntireX Process Extractor is available.